

IBM Mobile Systems

ThinkPad Computer
Hardware Maintenance Manual

February 2000

This manual supports:

ThinkPad A20m (MT 2628/MT 2633)

ThinkPad A20p (MT 2629)

Note

Before using this information and the product it supports, be sure to read the general information under "Notices" on page 103.

First Edition (February 2000)

The following paragraph does not apply to the United Kingdom or any country where such provisions are inconsistent with local law:

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT ANY WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE LIMITED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer or express or implied warranties in certain transactions; therefore, this statement may not apply to you.

This publication could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements or changes to the products or the programs described in this publication at any time.

It is possible that this publication may contain references to, or information about, IBM products (machines and programs), programming, or services that are not announced in your country. Such references or information must not be construed to mean that IBM intends to announce such IBM products, programming, or services in your country.

Requests for technical information about IBM products should be made to your IBM authorized dealer or your IBM marketing representative.

© Copyright International Business Machines Corporation 2000. All rights reserved. Note to U.S. Government Users – Documentation related to restricted rights – Use, duplication, or disclosure is subject to restrictions set forth in GSA ADP Schedule Contract with IBM Corp.

Contents

Introduction	1
Important service information	1
How to use error messages	2
How to read POST error messages	2
Drive and diskette compatibility matrix	3
Safety notices: multilingual translations	4
Safety information	11
General safety	11
Electrical safety	12
Safety inspection guide	13
Handling electrostatic discharge-sensitive devices	15
Grounding requirements	15
Laser compliance statement	16
General descriptions	19
Read this first	19
Related service information	21
Service Web site	21
Passwords	21
Power management	23
Checkout guide	26
Testing the computer	26
Detecting system information with PC-Doctor	28
Power system checkout	28
ThinkPad A20m and A20p	33
Product overview	35
Specifications	35
Status indicators	37
Fn key combinations	40
Symptom-to-FRU index	41
Numeric error codes	41
Error messages	43
Beep symptoms	44
LCD-related symptoms	45
Intermittent problems	46
Undetermined problems	46
FRU replacement notices	48
Screw notices	48
Retaining serial numbers	49
Removing and replacing a FRU	51
1010 Battery pack	52
1020 DIMM	53
1030 Backup battery	54
1040 Mini PCI adapter	55
1050 Hard disk drive or RF ID adapter	57
1060 Ultrabay 2000 device	58
1070 Keyboard	60
1080 Hinge cover	63
1090 Keyboard bezel and speaker	64
1100 Microphone cable	66

1110	Sub card	67
1120	PC Card slot assembly	68
1130	Fan assembly	69
1140	Diskette drive	70
1150	Upper shield	71
1160	TV card (The MT2629 model only)	72
1170	CPU socket and system board	73
2010	LCD assembly	74
2020	Front bezel	76
2030	Inverter card	77
2040	LCD panel	79
3010	ThinkPad Dock PCI cover	83
3010	ThinkPad Dock top cover	84
Locations		88
Front view		88
Rear view		90
Bottom view		91
Parts List		92
A20 series model matrix		92
LCD FRU		96
Keyboard		97
Miscellaneous parts		98
Options FRU list		100
Common parts list		101
Notices		103
Trademarks		103

Introduction

Important service information

Important

Diskette fixes are customer-installable. The diskette fixes are located on the PC Company Bulletin Board Service (BBS). The direct phone line for modem connection is 919-557-0001 or tieline 255-0001.

Advise customers to contact the PC Company HelpCenter at 800-772-2227 if they need assistance in obtaining or installing any diskette fixes.

Customers in Canada should call IBM HelpPC at 800-565-3344 for assistance or download information. The Canadian BBS phone numbers are:

Montreal	514-938-3022
Toronto	905-316-4255
Vancouver	604-664-6464
Winnipeg	204-934-2735

FRU replacement strategy

Before replacing parts

Ensure that all diskette fixes are installed before replacing any FRUs listed in this manual.

Use the following strategy to prevent unnecessary FRU replacement and service expense:

- **If you are instructed to replace a FRU but the replacement not correct the problem, reinstall the original FRU before you continue.**
- Some computers have both a processor board and a system board. If you are instructed to replace either the processor board or the system board, and the first board that you replace does not correct the problem, reinstall the original board, and then replace the other (processor or system) board.
- If an adapter or device consists of more than one FRU, any of the FRUs may be the cause of the error. Before replacing the adap the FRUs, one by one, to see if the symptoms change. Replace only the FRU that changed the symptoms.

Attention

A customized setup configuration (other than default settings) may exist on the computer you are servicing. Running Automatic Configuration may alter those settings. Note the current configuration settings (using the View Configuration option); then, when service has been completed, verify that the settings are in place.

Hard disk drive replacement strategy:

Always try to run a low-level format before replacing a hard disk drive.

Attention

The drive startup sequence in the computer you are servicing might have been changed. Be extremely careful during write operations such as copying, saving, or formatting. If you select an incorrect drive, data or programs can be overwritten.


How to use error messages

Use the error codes displayed on the screen to diagnose failures. If more than one error code is displayed, begin the diagnosis with the first error code. Whatever causes the first error code may also cause false error codes. If no error code is displayed, see if the error symptom is listed in the Symptom-to-FRU Index for the computer you are servicing.

How to read POST error messages

POST error messages are displayed on the screen as three, four, five, or eight digits. The error messages that can be displayed as shorter POST messages are highlighted in this index. Some digits have one meaning for SCSI errors and a different meaning for non-SCSI errors.

The following example shows which digits display the shorter POST error messages and also defines the SCSI information in each digit of an eight-digit error message.



Each SCSI device is assigned a unique SCSI ID. Duplicate SCSI ID settings can generate a false error message. Use the SCSI ID to determine whether an error message is coming from an internal or an external device.

Drive and diskette compatibility matrix

The following table provides identification information for 3.5-inch drives.

Diskette drive	Identifying mark
3.5-Inch - 1.44MB	1.44 on the eject button
3.5-Inch - 2.88MB	2.88 on the eject button

The following table provides compatibility information for 3.5-inch diskettes and 3.5-inch diskette drives.

Diskette capacity	1.44MB drive	2.88MB drive
1.0MB	Read/write	Read/write
2.0MB	Read/write	Read/write
4.0MB	Not compatible	Read/write

The following table provides identification information for 5.25-inch diskette drives.

Diskette drive	Identifying mark
5.25-Inch - 360KB (external)	Asterisk on bezel
5.25-Inch - 1.2MB (internal)	1.2 on the eject button

The following table provides compatibility information for 5.25-inch diskettes and 5.25-inch diskette drives.

Diskette capacity	360KB drive	1.2MB drive
360KB	Read/write	Read/write
1.2MB	Not compatible	Read/write

Note: A 360KB diskette written to or formatted on a 1.2MB drive can be read reliably only on a 1.2MB drive.

Safety notices: multilingual translations

In this manual, safety notices appear in English with a page number reference to the appropriate translation in this section.

The safety notices are provided in English, French, German, Italian, and Spanish, as follows:

Safety notice 1

Before the computer is powered-on after FRU replacement, make sure all screws, springs, and other small parts are in place and are not left loose inside the computer. Verify this by shaking the computer and listening for rattling sounds. Metallic parts or metal flakes can cause electrical shorts.

Avant de remettre l'ordinateur sous tension après remplacement d'une unité en clientèle, vérifiez que tous les ressorts, vis et autres pièces sont bien en place et bien fixées. Pour ce faire, secouez l'unité et assurez-vous qu'aucun bruit suspect ne se produit. Des pièces métalliques ou des copeaux de métal pourraient causer un court-circuit.

Bevor nach einem FRU-Austausch der Computer wieder angeschlossen wird, muß sichergestellt werden, daß keine Schrauben, Federn oder andere Kleinteile fehlen oder im Gehäuse vergessen wurden. Der Computer muß geschüttelt und auf Klappergeräusche geprüft werden. Metallteile oder -splitter können Kurzschlüsse erzeugen.

Prima di accendere l'elaboratore dopo che é stata effettuata la sostituzione di una FRU, accertarsi che tutte le viti, le molle e tutte le altri parti di piccole dimensioni siano nella corretta posizione e non siano sparse all'interno dell'elaboratore. Verificare scuotendo l'elaboratore e prestando attenzione ad eventuali rumori; eventuali parti o pezzetti metallici possono provocare cortocircuiti pericolosi.

Antes de encender el sistema despues de sustituir una FRU, compruebe que todos los tornillos, muelles y demás piezas pequeñas se encuentran en su sitio y no se encuentran sueltas dentro del sistema. Compruébelo agitando el sistema y escuchando los posibles ruidos que provocarían. Las piezas metálicas pueden causar cortocircuitos eléctricos.

Safety notice 2

Some standby batteries contain a small amount of nickel and cadmium. Do not disassemble a standby battery, recharge it, throw it into fire or water, or short-circuit it. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.

Certaines batteries de secours contiennent du nickel et du cadmium. Ne les démontez pas, ne les rechargez pas, ne les exposez ni au feu ni à l'eau. Ne les mettez pas en court-circuit. Pour les mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la pile de sauvegarde ou celle de l'horloge temps réel, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. Une batterie ou une pile inappropriée risque de prendre feu ou d'exploser.

Die Bereitschaftsbatterie, die sich unter dem Diskettenlaufwerk befindet, kann geringe Mengen Nickel und Cadmium enthalten. Sie darf nur durch die Verkaufsstelle oder den IBM Kundendienst ausgetauscht werden. Sie darf nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Die Batterie kann schwere Verbrennungen oder Verätzungen verursachen. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Bereitschafts- oder Systematterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

Alcune batterie di riserva contengono una piccola quantità di nichel e cadmio. Non smontarle, ricaricarle, gettarle nel fuoco o nell'acqua né cortocircuitarle.

Smaltirle secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). Quando si sostituisce la batteria dell'RTC (real time clock) o la batteria di supporto, utilizzare soltanto i tipi inseriti nell'appropriato Catalogo parti. L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

Algunas baterías de reserva contienen una pequeña cantidad de níquel y cadmio. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.

Safety notice 3

The battery pack contains small amounts of nickel. Do not disassemble it, throw it into fire or water, or short-circuit it. Dispose of the battery pack as required by local ordinances or regulations. Use only the battery in the appropriate parts listing when replacing the battery pack. Use of an incorrect battery can result in ignition or explosion of the battery.

La batterie contient du nickel. Ne la démontez pas, ne l'exposez ni au feu ni à l'eau. Ne la mettez pas en court-circuit. Pour la mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la batterie, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. En effet, une batterie inappropriée risque de prendre feu ou d'exploser.

Akkus enthalten geringe Mengen von Nickel. Sie dürfen nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

La batteria contiene piccole quantità di nichel. Non smontarla, gettarla nel fuoco o nell'acqua né cortocircuitarla. Smaltirla secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). Quando si sostituisce la batteria, utilizzare soltanto i tipi inseriti nell'appropriato Catalogo parti. L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

Las baterías contienen pequeñas cantidades de níquel. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas al sustituir la batería. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.

Safety notice 4

The lithium battery can cause a fire, an explosion, or a severe burn. Do not recharge it, remove its polarized connector, disassemble it, heat it above 100°C (212°F), incinerate it, or expose its cell contents to water. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.

La pile de sauvegarde contient du lithium. Elle présente des risques d'incendie, d'explosion ou de brûlures graves. Ne la rechargez pas, ne retirez pas son connecteur polarisé et ne la démontez pas. Ne l'exposez pas à une température supérieure à 100°C, ne la faites pas brûler et n'en exposez pas le contenu à l'eau. Mettez la pile au rebut conformément à la réglementation en vigueur. Une pile inappropriée risque de prendre feu ou d'exploser.

Die Systematterie ist eine Lithiumatterie. Sie kann sich entzünden, explodieren oder schwere Verbrennungen hervorrufen. Batterien dieses Typs dürfen nicht aufgeladen, zerlegt, über 100 C erhitzt oder verbrannt werden. Auch darf ihr Inhalt nicht mit Wasser in Verbindung gebracht oder der zur richtigen Polung angebrachte Verbindungsstecker entfernt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.

La batteria di supporto è una batteria al litio e può incendiarsi, esplodere o procurare gravi ustioni. Evitare di ricaricarla, smontarne il connettore polarizzato, smontarla, riscaldarla ad una temperatura superiore ai 100 gradi centigradi, incendiarla o gettarla in acqua. Smaltirla secondo la normativa in vigore (DPR 915/82, successive disposizioni e disposizioni locali). L'impiego di una batteria non adatta potrebbe determinare l'incendio o l'esplosione della batteria stessa.

La batería de repuesto es una batería de litio y puede provocar incendios, explosiones o quemaduras graves. No la recargue, ni quite el conector polarizado, ni la desmonte, ni caliente por encima de los 100°C (212°F), ni la incinere ni exponga el contenido de sus celdas al agua. Deséchela tal como dispone la normativa local.

Safety notice 5

If the LCD breaks and the fluid from inside the LCD gets into your eyes or on your hands, immediately wash the affected areas with water for at least 15 minutes. Seek medical care if any symptoms from the fluid are present after washing.

Si le panneau d'affichage à cristaux liquides se brise et que vous recevez dans les yeux ou sur les mains une partie du fluide, rincez-les abondamment pendant au moins quinze minutes. Consultez un médecin si des symptômes persistent après le lavage.

Die Leuchtstoffröhre im LCD-Bildschirm enthält Quecksilber. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Der LCD-Bildschirm besteht aus Glas und kann zerbrechen, wenn er unsachgemäß behandelt wird oder der Computer auf den Boden fällt. Wenn der Bildschirm beschädigt ist und die darin befindliche Flüssigkeit in Kontakt mit Haut und Augen gerät, sollten die betroffenen Stellen mindestens 15 Minuten mit Wasser abgespült und bei Beschwerden anschließend ein Arzt aufgesucht werden.

Nel caso che caso l'LCD si dovesse rompere ed il liquido in esso contenuto entrasse in contatto con gli occhi o le mani, lavare immediatamente le parti interessate con acqua corrente per almeno 15 minuti; poi consultare un medico se i sintomi dovessero permanere.

Si la LCD se rompe y el fluido de su interior entra en contacto con sus ojos o sus manos, lave inmediatamente las áreas afectadas con agua durante 15 minutos como mínimo. Obtenga atención medica si se presenta algún síntoma del fluido despues de lavarse.

Safety notice 6

To avoid shock, do not remove the plastic cover that protects the lower part of the inverter card.

Afin d'éviter tout risque de choc électrique, ne retirez pas le cache en plastique protégeant la partie inférieure de la carte d'alimentation.

Aus Sicherheitsgründen die Kunststoffabdeckung, die den unteren Teil der Spannungswandlerplatine umgibt, nicht entfernen.

Per evitare scosse elettriche, non rimuovere la copertura in plastica che avvolge la parte inferiore della scheda invertitore.

Para evitar descargas, no quite la cubierta de plástico que rodea la parte baja de la tarjeta invertida.

Safety notice 7

Though main batteries have low voltage, a shorted or grounded battery can produce enough current to burn personnel or combustible materials.

Bien que le voltage des batteries principales soit peu élevé, le court-circuit ou la mise à la masse d'une batterie peut produire suffisamment de courant pour brûler des matériaux combustibles ou causer des brûlures corporelles graves.

Obwohl Hauptbatterien eine niedrige Spannung haben, können sie doch bei Kurzschluß oder Erdung genug Strom abgeben, um brennbare Materialien zu entzünden oder Verletzungen bei Personen hervorzurufen.

Sebbene le batterie di alimentazione siano a basso voltaggio, una batteria in corto circuito o a massa può fornire corrente sufficiente da bruciare materiali combustibili o provocare ustioni ai tecnici di manutenzione.

Aunque las baterías principales tienen un voltaje bajo, una batería cortocircuitada o con contacto a tierra puede producir la corriente suficiente como para quemar material combustible o provocar quemaduras en el personal.

Safety notice 8

Before removing any FRU, power off the computer, unplug all power cords from electrical outlets, remove the battery pack, and then disconnect any interconnecting cables.

Avant de retirer une unité remplaçable en clientèle, mettez le système hors tension, débranchez tous les cordons d'alimentation des socles de prise de courant, retirez la batterie et déconnectez tous les cordons d'interface.

Die Stromzufuhr muß abgeschaltet, alle Stromkabel aus der Steckdose gezogen, der Akku entfernt und alle Verbindungskabel abgenommen sein, bevor eine FRU entfernt wird.

Prima di rimuovere qualsiasi FRU, spegnere il sistema, scollegare dalle prese elettriche tutti i cavi di alimentazione, rimuovere la batteria e poi scollegare i cavi di interconnessione.

Antes de quitar una FRU, apague el sistema, desenchufe todos los cables de las tomas de corriente eléctrica, quite la batería y, a continuación, desconecte cualquier cable de conexión entre dispositivos.

Safety information

The following section contains the safety information that you need to be familiar with before servicing an IBM mobile computer.

General safety

Follow these rules to ensure general safety:

- Observe good housekeeping in the area of the machines during and after maintenance.
- When lifting any heavy object:
 1. Ensure you can stand safely without slipping.
 2. Distribute the weight of the object equally between your feet.
 3. Use a slow lifting force. Never move suddenly or twist when you attempt to lift.
 4. Lift by standing or by pushing up with your leg muscles; this action removes the strain from the muscles in your back. *Do not attempt to lift any objects that weigh more than 16 kg (35 lb) or objects that you think are too heavy for you.*
- Do not perform any action that causes hazards to the customer, or that makes the equipment unsafe.
- Before you start the machine, ensure that other service representatives and the customer's personnel are not in a hazardous position.
- Place removed covers and other parts in a safe place, away from all personnel, while you are servicing the machine.
- Keep your toolbox away from walk areas so that other people will not trip over it.
- Do not wear loose clothing that can be trapped in the moving parts of a machine. Ensure that your sleeves are fastened or rolled up above your elbows. If your hair is long, fasten it.
- Insert the ends of your necktie or scarf inside clothing or fasten it with a nonconductive clip, approximately 8 centimeters (3 inches) from the end.
- Do not wear jewelry, chains, metal-frame eyeglasses, or metal fasteners for your clothing.

Attention: Metal objects are good electrical conductors.
- Wear safety glasses when you are hammering, drilling, soldering, cutting wire, attaching springs, using solvents, or working in any other conditions that might be hazardous to your eyes.
- After service, reinstall all safety shields, guards, labels, and ground wires. Replace any safety device that is worn or defective.
- Reinstall all covers correctly before returning the machine to the customer.

Electrical safety

Observe the following rules when working on electrical equipment.

Important

Use only approved tools and test equipment. Some hand tools have handles covered with a soft material that does not insulate you when working with live electrical currents.

Many customers have, near their equipment, rubber floor mats that contain small conductive fibers to decrease electrostatic discharges. Do not use this type of mat to protect yourself from electrical shock.

- Find the room emergency power-off (EPO) switch, disconnecting switch, or electrical outlet. If an electrical accident occurs, you can then operate the switch or unplug the power cord quickly.
- Do not work alone under hazardous conditions or near equipment that has hazardous voltages.
- Disconnect all power before:
 - Performing a mechanical inspection
 - Working near power supplies
 - Removing or installing main units
- Before you start to work on the machine, unplug the power cord. If you cannot unplug it, ask the customer to power-off the wall box that supplies power to the machine and to lock the wall box in the off position.
- If you need to work on a machine that has *exposed* electrical circuits, observe the following precautions:
 - Ensure that another person, familiar with the power-off controls, is near you.

Attention: Another person must be there to switch off the power, if necessary.
 - Use only one hand when working with powered-on electrical equipment; keep the other hand in your pocket or behind your back.

Attention: An electrical shock can occur only when there is a complete circuit. By observing the above rule, you may prevent a current from passing through your body.
 - When using testers, set the controls correctly and use the approved probe leads and accessories for that tester.
 - Stand on suitable rubber mats (obtained locally, if necessary) to insulate you from grounds such as metal floor strips and machine frames.

Observe the special safety precautions when you work with very high voltages; these instructions are in the safety sections of maintenance information. Use extreme care when measuring high voltages.

- Regularly inspect and maintain your electrical hand tools for safe operational condition.
- Do not use worn or broken tools and testers.
- *Never assume* that power has been disconnected from a circuit. First, *check* that it has been powered off.
- Always look carefully for possible hazards in your work area. Examples of these hazards are moist floors, nongrounded power extension cables, power surges, and missing safety grounds.
- Do not touch live electrical circuits with the reflective surface of a plastic dental mirror. The surface is conductive; such touching can cause personal injury and machine damage.
- Do not service the following parts *with the power on* when they are removed from their normal operating places in a machine:
 - Power supply units
 - Pumps
 - Blowers and fans
 - Motor generators
 and similar units. (This practice ensures correct grounding of the units.)
- If an electrical accident occurs:
 - **Use caution; do not become a victim yourself.**
 - **Switch off power.**
 - **Send another person to get medical aid.**

Safety inspection guide

The purpose of this inspection guide is to assist you in identifying potentially unsafe conditions. As each machine was designed and built, required safety items were installed to protect users and service personnel from injury. This guide addresses only those items. You should use good judgment to identify potential safety hazards due to attachment of non-IBM features or options not covered by this inspection guide.

If any unsafe conditions are present, you must determine how serious the apparent hazard could be and whether you can continue without first correcting the problem.

Consider these conditions and the safety hazards they present:

- Electrical hazards, especially primary power (primary voltage on the frame can cause serious or fatal electrical shock)
- Explosive hazards, such as a damaged CRT face or a bulging capacitor
- Mechanical hazards, such as loose or missing hardware

The guide consists of a series of steps presented in a checklist. Begin the checks with the power off, and the power cord disconnected.

Checklist:

1. Check exterior covers for damage (loose, broken, or sharp edges).
2. Power-off the computer. Disconnect the power cord.
3. Check the power cord for:
 - a. A third-wire ground connector in good condition. Use a meter to measure third-wire ground continuity for 0.1 ohm or less between the external ground pin and frame ground.
 - b. The power cord should be the type specified in the parts list.
 - c. Insulation must not be frayed or worn.
4. Remove the cover.
5. Check for any obvious non-IBM alterations. Use good judgment as to the safety of any non-IBM alterations.
6. Check inside the unit for any obvious unsafe conditions, such as metal filings, contamination, water or other liquids, or signs of fire or smoke damage.
7. Check for worn, frayed, or pinched cables.
8. Check that the power-supply cover fasteners (screws or rivets) have not been removed or tampered with.

Handling electrostatic discharge-sensitive devices

Any computer part containing transistors or integrated circuits (ICs) should be considered sensitive to electrostatic discharge (ESD). ESD damage can occur when there is a difference in charge between objects. Protect against ESD damage by equalizing the charge so that the machine, the part, the work mat, and the person handling the part are all at the same charge.

Notes

1. Use product-specific ESD procedures when they exceed the requirements noted here.
2. Make sure that the ESD protective devices you use have been certified (ISO 9000) as fully effective.

When handling ESD-sensitive parts:

- Keep the parts in protective packages until they are inserted into the product.
- Avoid contact with other people.
- Wear a grounded wrist strap against your skin to eliminate static on your body.
- Prevent the part from touching your clothing. Most clothing is insulative and retains a charge even when you are wearing a wrist strap.
- Use the black side of a grounded work mat to provide a static-free work surface. The mat is especially useful when handling ESD-sensitive devices.
- Select a grounding system, such as those listed below, to provide protection that meets the specific service requirement.

Note

The use of a grounding system is desirable but not required to protect against ESD damage.

- Attach the ESD ground clip to any frame ground, ground braid, or green-wire ground.
- Use an ESD common ground or reference point when working on a double-insulated or battery-operated system. You can use coax or connector-outside shells on these systems.
- Use the round ground-prong of the AC plug on AC-operated computers.

Grounding requirements

Electrical grounding of the computer is required for operator safety and correct system function. Proper grounding of the electrical outlet can be verified by a certified electrician.

Laser compliance statement

Some IBM Personal Computer models are equipped from the factory with a CD-ROM drive. CD-ROM drives are also sold separately as options. The CD-ROM drive is a laser product. The CD-ROM drive is certified in the U.S. to conform to the requirements of the Department of Health and Human Services 21 Code of Federal Regulations (DHHS 21 CFR) Subchapter J for Class 1 laser products. Elsewhere, the drive is certified to conform to the requirements of the International Electrotechnical Commission (IEC) 825 and CENELEC EN 60 825 for Class 1 laser products.

When a CD-ROM drive is installed, note the following:



CAUTION:

Use of controls or adjustments or performance of procedures other than those specified herein might result in hazardous radiation exposure.

O uso de controles, ajustes ou desempenho de procedimentos diferentes daqueles aqui especificados pode resultar em perigosa exposição à radiação.

凡未在这里指明的任何控制用法、调整、行为，都会导致严重后果。

Pour éviter tout risque d'exposition au rayon laser, respectez les consignes de réglage et d'utilisation des commandes, ainsi que les procédures décrites.

Werden Steuer- und Einstellelemente anders als hier festgesetzt verwendet, kann gefährliche Laserstrahlung auftreten.

Az itt előírt eljárásoktól, beállításoktól és vezérlésektől eltérni a lézersugárzás veszélye miatt kockázatos !

L'utilizzo di controlli, regolazioni o l'esecuzione di procedure diverse da quelle specificate possono provocare l'esposizione a

Использование элементов настройки и выполнение процедур иных, чем указано здесь, может привести к опасному радиационному облучению.

Použitie kontrol, úprav alebo iných vykonaní od iných výrobcov, ako je v tomto špecifikované, mohlo by mať za následok nebezpečenstvo vystavenia sa vyžiarovaniu.

El uso de controles o ajustes o la ejecución de procedimientos distintos de los aquí especificados puede provocar la exposición a radiaciones peligrosas.

Opening the CD-ROM drive could result in exposure to hazardous laser radiation. There are no serviceable parts inside the CD-ROM drive. **Do not open.**

Some CD-ROM drives contain an embedded Class 3A or Class 3B laser diode. Note the following.

DANGER:

Laser radiation when open. Do not stare into the beam, do not view directly with optical instruments, and avoid direct exposure to the beam.

Radiação por raio laser ao abrir. Não olhe fixo no feixe de luz, não olhe diretamente por meio de instrumentos óticos e evite exposição direta com o feixe de luz.

开启时会有激光发射时，请勿盯视激光光束，请勿直接查看视觉仪器，并且避免直接接触在激光光束之中。

Rayonnement laser si carter ouvert. Évitez de fixer le faisceau, de le regarder directement avec des instruments optiques, ou de vous exposer au rayon.

Laserstrahlung bei geöffnetem Gerät. Nicht direkt oder über optische Instrumente in den Laserstrahl sehen und den Strahlungsbereich meiden.

Kinyitáskor lézersugár ! Ne nézzen bele se szabad szemmel, se optikai eszközökkel. Kerülje a sugárnyalábbal való érintkezést !

Aprendo l'unità vengono emesse radiazioni laser. Non fissare il fascio, non guardarlo direttamente con strumenti ottici e evitare l'esposizione diretta al fascio.

Открывая, берегитесь лазерного излучения. Не смотрите на луч, не разглядывайте его с помощью оптических инструментов, а также избегайте прямого воздействия лазерного луча.

Keď je laserová jednotka otvorená. Vyhňte sa priamemu pohľadu a nehládte priamo s optickými nástrojmi do lúča a vyhňte sa priamemu vystaveniu lúčov.

Radiación láser al abrir. No mire fijamente ni examine con instrumental óptico el haz de luz. Evite la exposición directa al haz.

READ THIS FIRST

General descriptions

This chapter includes descriptions for any ThinkPad model that has the PC-Doctor DOS diagnostics program. Some descriptions might not apply to your particular computer.

Read this first

Before you go to the checkout guide, be sure to read this section.

Important notes

- **Only certified trained personnel should service the computer.**
- **Read the entire FRU removal and replacement page before replacing any FRU.**
- **Use new nylon-coated screws when you replace FRUs.**
- **Be extremely careful during such write operations as copying, saving, or formatting.** Drives in the computer that you are servicing might have been rearranged or the drive startup sequence might have been altered. If you select an incorrect drive, data or programs might be overwritten.
- **Replace FRUs only for the correct model.** When you replace a FRU, make sure the model of the machine and the FRU part number are correct by referring to the FRU parts list.
- **A FRU should not be replaced because of a single, unreproducible failure.** Single failures can occur for a variety of reasons that have nothing to do with a hardware defect, such as cosmic radiation, electrostatic discharge, or software errors. Consider replacing a FRU only when a problem recurs. If you suspect that a FRU is defective, clear the error log and run the test again. If the error does not recur, do not replace the FRU.
- **Be careful not to replace a nondefective FRU.**

What to do first: When you do return a FRU, you must include the following information in the parts exchange form or parts return form that you attach to it:

- ___ 1. Name and phone number of servicer
- ___ 2. Date of service
- ___ 3. Date on which the machine failed
- ___ 4. Date of purchase
- ___ 5. Failure symptoms, error codes appearing on the display, and beep symptoms

READ THIS FIRST

- ___ 6. Procedure index and page number in which the failing FRU was detected
- ___ 7. Failing FRU name and part number
- ___ 8. Machine type, model number, and serial number
- ___ 9. Customer's name and address

Note for warranty: During the warranty period, the customer may be responsible for repair costs if the computer damage was caused by misuse, accident, modification, unsuitable physical or operating environment, or improper maintenance by the customer. The following list provides some common items that are not covered under warranty and some symptoms that might indicate that the system was subjected to stress beyond normal use.

Before checking problems with the computer, determine whether the damage is covered under the warranty by referring to the following:

The following are not covered under warranty:

- LCD panel cracked from the application of excessive force or from being dropped
- Scratched (cosmetic) parts
- Cracked or broken plastic parts, broken latches, broken pins, or broken connectors caused by excessive force
- Damage caused by liquid spilled into the system
- Damage caused by the improper insertion of a PC Card or the installation of an incompatible card
- Damage caused by foreign material in the diskette drive
- Diskette drive damage caused by pressure on the diskette drive cover or by the insertion of a diskette with multiple labels
- Damaged or bent diskette eject button
- Fuses blown by attachment of a nonsupported device
- Forgotten computer password (making the computer unusable)

The following symptoms might indicate damage caused by nonwarranted activities:

- Missing parts might be a symptom of unauthorized service or modification.
- If the spindle of a hard disk drive become noisy, it may have been subjected to excessive force, or dropped. excessive force or from being dropped.
- I9990303 errors can be caused by exposure to strong magnetic fields.

Related service information

This section provides information about the following:

- “Service Web site”
- “Passwords”
- Power management

Service Web site

When the latest maintenance diskette and the system program service diskette are available, a notice will be posted on <http://pccbbs.raleigh.ibm.com/>

Passwords

As many as three passwords may be needed for any ThinkPad computers: the power-on password (POP), the hard disk password (HDP), and the supervisor password (PAP).

When the power-on password, the hard disk password, or the supervisor password is used, a password prompt appears on the screen whenever the computer is turned on. The computer does not start until the password is entered.

Power-on password: A power-on password (POP) protects the system from being powered on by an unauthorized person. Without knowing the password, nobody can start the system.

Hard disk password: There are two hard disk passwords (HDPs):

- User hard disk password—for the user
- Master hard disk password—for the system administrator, who can use it to get access to the hard disk even if the user hard disk password has been changed by the user

Attention

If the master HDP has been forgotten, there is no way to reset it and recover the data from the hard disk.

Supervisor password: A supervisor password (PAP) protects the system information stored in the IBM BIOS Setup Utility so that without knowing the password, nobody can change the configuration of the computer.

Attention

If the PAP has been forgotten, there is no way to reset it and recover the data from the hard disk.

RELATED SERVICE INFORMATION

How to remove the power-on password: To remove the POP, do the following:

1. Power on the computer by pressing and holding **F1**.
2. Enter the supervisor password. The IBM BIOS Setup Utility menu appears.
3. Select **Password**, using the cursor keys to move down the menu.
4. Select **Power-on password**. A pop-up window opens.
5. Enter the password. When the Enter New Password field opens, leave it blank and press **Enter** twice.
6. Press **F10**; then click **Exit**.
7. Select **Yes** in the Setup Configuration window.
The POP has been removed.

If you want to remove the POP but don't know what it is, do the following:

1. Turn off the computer.
2. Remove the DIMM cover from the bottom of the computer.
3. Remove the backup battery.
For how to remove the backup battery, see "1030 Backup battery" on page 54.
4. Turn on the computer and wait until the POST ends.
After the POST ends, the password prompt does not appear. The POP has been removed.
5. Reinstall the DIMM cover.

How to remove the hard disk password: To remove the HDP, do the following:

1. Power on the computer by pressing and holding **F1**.
2. Enter the supervisor password. The IBM BIOS Setup Utility menu appears.
3. Select **Password**, using the cursor keys to move down the menu.
4. Select **Hard disk x password**, where *x* is the letter of the hard disk drive. A pop-up window opens.
5. Select either **User only** or **Master + User**.
6. Enter the password. When the Enter New Password field opens, leave it blank and press **Enter** twice.
7. Press **F10**; then click **Exit**.
8. Select **Yes** in the Setup Configuration window.
The HDP has been removed.

RELATED SERVICE INFORMATION

How to remove the supervisor password:

To remove the PAP, do the following:

1. Power on the computer by pressing and holding **F1**.
 2. Enter the supervisor password. The IBM BIOS Setup Utility menu appears.
 3. Select **Password**, using the cursor keys to move down the menu.
 4. Select **Supervisor password**. A pop-up window opens.
 5. Select either **User only** or **Master + User**.
 6. Enter the password. When the Enter New Password field opens, leave it blank and press **Enter** twice.
 7. Press **F10**; then click **Exit**.
 8. Select **Yes** in the Setup Configuration window.
- The PAP has been removed.

Power management

To reduce power consumption, the computer has three power management modes: screen blank, standby, and hibernation.

Screen blank mode: In screen blank mode, the following occurs:

- The LCD backlight turns off.
- The hard disk drive motor stops.
- The speaker is muted.

Note: Screen blank mode in Windows 98 is called *standby mode* in Windows 95.

To enter screen blank mode, press **Fn + F3**. To end screen blank mode and resume normal operation, press any key.

Standby mode: When the computer enters standby mode, the following events occur in addition to what occurs in screen blank mode:

- The LCD is powered off.
- The hard disk drive is powered off.
- The CPU stops.

Note: Standby mode in Windows 98 is called *suspend mode* in Windows 95.

To enter standby mode by, do any of the following:

- Press **Fn + F4**.
- Close the LCD cover. (To prevent the computer from entering standby mode when the LCD is closed, click **Will not suspend even if LCD is closed** in the Power Management Properties window. Then only the LCD turns off.)

RELATED SERVICE INFORMATION

In certain circumstances, the computer goes into standby mode automatically:

- If a “suspend time” has been set on the timer, and the user does not do any operation with the keyboard, the TrackPoint, the hard disk, the parallel connector, or the diskette drive within the time set.
- If the ac adapter is plugged in.
- If the battery indicator blinks orange, indicating that the battery power is low. (Alternatively, if **Hibernate when battery becomes low** has been selected in the “Power Management Properties” window, the computer goes into hibernation mode.)

Note: Even if you don't set the low-battery alarm, the charge indicator lets you know that the battery is low, and then the computer enters the power-saving mode automatically. This default low-battery behavior is independent of the operating system: so if you have set the low-battery alarm, the computer may not do what you specified. It chooses either your setting or the default setting, whichever is appropriate.

Any one of the following events causes the computer to resume operation from standby mode:

- The **Fn** key is pressed.
- The LCD cover is opened.
- The ring indicator (RI) is signaled by a serial device or a PC Card device.
- The power switch is turned on.
- The resume timer is set. In Windows 98, the **Scheduled Tasks** setting has priority over the **Resume on timer** selection in the “Power Management Properties” window.

Note: The computer does not accept any input immediately after it enters suspend mode. Wait a few seconds before taking any action to reenter operation mode.

RELATED SERVICE INFORMATION

Hibernation mode

Note for Windows NT

A Windows NT user cannot create a hibernation file in a Windows NT system that uses NTFS format, the Windows NT default format. If you want to use hibernation mode, you will need to reinstall Windows NT with FAT format.

In hibernation mode, the following occurs:

- The system status, RAM, VRAM, and setup data are stored on the hard disk.
- The system is powered off.

Notes:

1. In the ThinkPad Configuration program, the computer can be set to **suspend/hibernate while docked**.
2. The computer cannot enter hibernation mode when it is powered with ac power and a communication PC Card is used.
3. If the computer enters the hibernation mode when it is docked to the docking station, do not undock it from the docking station before resuming normal operation. If you do undock it, then if you try to resume normal operation, you will get an error message, and you will have to restart the system.

Any one of the following events causes the computer to enter hibernation mode:

- The **Fn + F12** keys are pressed.
- The power switch is turned off and the mode is set to **Power switch mode [Hibernation]**.
- The timer conditions are satisfied in suspend mode (for operating systems other than Windows 98).
- A critically low battery condition occurs and the mode is set to **Hibernate when battery becomes low**.

When the power is turned on, the computer leaves hibernation mode and resumes operation. The hibernation file in the boot record on the hard disk drive is read, and system status is restored from the hard disk drive.

Checkout guide

Use the following procedures as a guide in identifying and correcting problems with the ThinkPad computer.

Note: The diagnostic tests are intended to test only IBM products. The use of non-IBM products, prototype cards, or modified options can lead to false indications of errors and invalid system responses.

1. Identify the failing symptoms in as much detail as possible.
2. Verify the symptoms. Try to re-create the failure by running the diagnostic test or by repeating the operation.

Testing the computer

The ThinkPad computer has a test program called PC-Doctor DOS (hereafter called *PC-Doctor*). You can detect errors by running the diagnostics test included in PC-Doctor. This section is an overview of the procedure. For details that depend on model-unique functions, refer to "Product overview" on page 35.

For some possible configurations of the computer, PC-Doctor might not run correctly. To avoid this problem, you need to initialize the computer setup by IBM BIOS Setup Utility before you run PC-Doctor. In the IBM BIOS Setup Utility screen, press **F9**, **Enter**, **F10**, then **Enter**.

Note: When you initialize the computer configuration, some devices are disabled, such as the serial port. If you test one of these devices, you will need to enable it by using PS2.EXE.

PC-Doctor cannot be used to test a device that is in the docking station. If a device is in the Ultrabay 2000 or connect to the USB connector of the docking station, remove it and install it in the Ultrabay 2000 or connect it to the USB connector of the computer. Then test it with PC-Doctor.

To run the test, do as follows:

Note: In the following procedure, you can select an item not only with the arrow keys, but also with the TrackPoint. Instead of pressing **Enter**, click the left button.

1. Insert the PC-Doctor disk into the diskette drive; then power on the computer.

If the computer cannot be powered on, go to "Power system checkout" on page 28, and check the power sources.

If an error code appears, go to "Symptom-to-FRU index" on page 41.

CHECKOUT GUIDE

On the first screen, select the model and press **Enter**. Follow the instructions on the screen.

2. The main panel of PC-Doctor appears.
3. Select **Diagnostics** with the arrow keys, and press **Enter**.


A pull-down menu appears. (Its exact form depends on the model.)

The options on the test menu are as follows:

Diagnostics	Interactive Tests
<ul style="list-style-type: none"> • Run Normal Test • Run Quick Test • CPU/Coprocessor • Systemboard • Video Adapter • Serial Ports • Parallel Ports • Fixed Disks • Diskette Drives • Other Devices • Memory Test – Full • Memory Test – Quick 	<ul style="list-style-type: none"> • Keyboard • Video • Internal Speaker • Mouse • Joystick • Diskette • System Load • CD-ROM/DVD Test • Stereo Speaker

Notes:

- In the **Keyboard** test in **Interactive Tests**, the **F_n** key is scanned only once. Each key should be held down for at least 2 seconds; otherwise, it cannot be sensed.
- Sound Card is not recognized in the **Stereo Speaker** in the **Interactive Tests**. To test it, use **Audio** in the **Other Devices (Diagnostics)**.



4. Run the applicable function test.
5. Follow the instructions on the screen. If there is a problem, PC-Doctor shows messages describing it.
6. To exit the test, select **Quit — Exit Diag**.
To cancel the test, press **Esc**.

Detecting system information with PC-Doctor

PC-Doctor can detect the following system information:

Hardware Info:

- System Configuration
- Memory Contents
- Physical Disk Drives
- Logical Disk Drives
- VGA Information
- IDE Drive Info
- PCI Information
- PNPIISA Info
- SMBIOS Info
- VESA LCD Info

Utility:

- Run External Tests
- Surface Scan Hard Disk
- Benchmark System
- DOS Shell
- Tech Support Form
- Battery Rundown
- View Test Log
- Print Log
- Save Log
- Full Erase Hard Drive
- Quick Erase Hard Drive

Power system checkout

To verify the symptom of a problem, do the following:

1. Power off the computer.
2. Remove the battery pack.
3. Connect the ac adapter.
4. Check that power is supplied when you power on the computer.
5. Power off the computer.
6. Disconnect the ac adapter and install the charged battery pack.
7. Check that the battery pack supplies power when you power on the computer.


If you suspect a power problem, see the appropriate one of the following power supply checkouts:

- "Checking the ac adapter" on page 29
- "Checking operational charging" on page 29
- "Checking the battery pack" on page 30
- "Checking the backup battery" on page 30

CHECKOUT GUIDE

Checking the ac adapter: You are here because the computer fails only when the ac adapter is used:

- If the power problem occurs only when the port replicator is used, replace the port replicator.
 - If the power-on indicator does not turn on, check the power cord of the ac adapter for correct continuity and installation.
 - If the computer does not charge during operation, go to “Checking operational charging.”
1. Unplug the ac adapter cable from the computer and measure the output voltage at the plug of the ac adapter cable. See the following figure:



(16 - 10 V)

Pin	Voltage (V dc)
1	+15.5 to +17.0
2	Ground

If the voltage is not correct, replace the ac adapter.

If the voltage is acceptable, do the following:

- Replace the system board.
- If the problem persists, go to “Product overview” on page 35.

Note: Noise from the ac adapter does not always indicate a defect.

Checking operational charging: To check operational charging, use a discharged battery pack or a battery pack that has less than 50% of the total power remaining when installed in the computer.

Perform operational charging. If the battery status indicator or icon does not turn on, remove the battery pack and let it return to room temperature. Reinstall the battery pack. If the charge indicator or icon still does not turn on, replace the battery pack.


If the charge indicator still does not turn on, replace the system board. Then reinstall the battery pack. If the reinstalled battery pack has not been charged, go to the next section.

Checking the battery pack: Battery charging does not start until the Fuel Gauge shows that less than 95% of the total power remains; under this condition the battery pack can charge to 100% of its capacity. This protects the battery pack from being overcharged or from having a shortened life.

Note: If the battery pack becomes hot, it may not be able to charge. Remove it from the computer and leave it at room temperature for a while. After it cools down, reinstall and recharge it.

To check the battery pack, do the following:

1. Power off the computer.
2. Remove the battery pack and measure the voltage between battery terminals 1 (+) and 4 (-). See the following figure:



Terminal	Voltage (V dc)
1	+ 0 to + 12.6
4	Ground (-)

3. If the voltage is less than +11.0 V dc, the battery pack has been discharged.

Note: Recharging will take at least 3 hours, even if the indicator does not turn on.

If the voltage is still less than +11.0 V dc after recharging, replace the battery.


4. If the voltage is more than +11.0 V dc, measure the resistance between battery terminals 3 and 4. The resistance must be 4 to 30 K ohm.

If the resistance is not correct, replace the battery pack. If the resistance is correct, replace the system board.

Checking the backup battery: Do the following:

1. Power off the computer, and unplug the ac adapter from it.
2. Turn the computer upside down.
3. Remove the backup battery (see "Checking the battery pack").
4. Measure the voltage of the backup battery. See the following figure.

CHECKOUT GUIDE



Wire	Voltage (V dc)
Red	+2.5 to +3.2
Black	Ground

- If the voltage is correct, replace the system board.
- If the voltage is not correct, replace the backup battery.
- If the backup battery discharges quickly after replacement, replace the system board.

CHECKOUT GUIDE

ThinkPad A20m and A20p

This chapter presents the descriptions of the ThinkPad A20 series computer.

Product overview	35
Specifications	35
Status indicators	37
Fn key combinations	40
Symptom-to-FRU index	41
Numeric error codes	41
Error messages	43
Beep symptoms	44
LCD-related symptoms	45
Intermittent problems	46
Undetermined problems	46
FRU replacement notices	48
Screw notices	48
Retaining serial numbers	49
Removing and replacing a FRU	51
1010 Battery pack	52
1020 DIMM	53
1030 Backup battery	54
1040 Mini PCI adapter	55
1050 Hard disk drive or RF ID adapter	57
1060 Ultrabay 2000 device	58
1070 Keyboard	60
1080 Hinge cover	63
1090 Keyboard bezel and speaker	64
1100 Microphone cable	66
1110 Sub card	67
1120 PC Card slot assembly	68
1130 Fan assembly	69
1140 Diskette drive	70
1150 Upper shield	71
1160 TV card (The MT2629 model only)	72
1170 CPU socket and system board	73
2010 LCD assembly	74
2020 Front bezel	76
2030 Inverter card	77
2040 LCD panel	79
3010 ThinkPad Dock PCI cover	83
3010 ThinkPad Dock top cover	84
Locations	88
Front view	88
Rear view	90
Bottom view	91
Parts List	92
A20 series model matrix	92
LCD FRU	96
Keyboard	97
Miscellaneous parts	98

THINKPAD A20M AND A20P

Options FRU list	100
Common parts list	101

Product overview

This section presents the following product-unique information:

- “Specifications”
- “Status indicators” on page 37
- “Fn key combinations” on page 40

Specifications

The following table lists the specifications of the ThinkPad A20 series:


Feature	Description
Processor	<p>MT2628 and MT2633 (A20m)</p> <ul style="list-style-type: none"> • Intel® mobile Pentium® III 500 MHz, L2 256-KB cache • Intel® mobile Pentium® processor 650 featuring Intel® SpeedStep™ technology • Intel® Celeron™ processor 500 MHz, L2 256-KB cache <p>MT2629 (A20p)</p> <ul style="list-style-type: none"> • Intel® mobile Pentium® processor 700 featuring Intel® SpeedStep™ technology
Bus architecture	<ul style="list-style-type: none"> • PCI Bus
Memory (standard)	<p>MT2628 and MT2633 (A20m)</p> <ul style="list-style-type: none"> • 64 MB (on the system board) <p>MT2629 (A20p)</p> <ul style="list-style-type: none"> • 128 MB (on the system board)
Memory (optional)	<ul style="list-style-type: none"> • 64 MB, 128 MB, or 256 MB DIMM card (maximum of 512 MB)
CMOS RAM	114 bytes +4 Kbytes
Display	<p>MT2628 and MT2633 (A20m)</p> <ul style="list-style-type: none"> • 12.1-inch, 16M colors SVGA (800×600 resolution) TFT color LCD • 14.1-inch, 16M colors, XGA (1024×768 resolution) TFT color LCD • 15.0-inch, 16M colors, XGA (1024×768 resolution) TFT color LCD <p>MT2629 (A20p)</p> <ul style="list-style-type: none"> • 15.0-inch, 16M colors, SXGA+ (1400×1050 resolution) TFT color LCD
Diskette drive	1.44 MB (3-mode), 3.5-inch

PRODUCT OVERVIEW

Feature	Description
Hard disk drive	<p>MT2628 and MT2633 (A20m)</p> <ul style="list-style-type: none"> • 6.0 GB, 2.5-inch, IDE interface • 12 GB, 2.5-inch, IDE interface <p>MT2629 (A20p)</p> <ul style="list-style-type: none"> • 18.0 GB, 2.5-inch, IDE interface
I/O port	<ul style="list-style-type: none"> • External monitor • Line-in • Headphone • Microphone • Mouse or keyboard • Parallel • Expansion connector • Serial • USB • RJ11 • RJ45
Internal modem	<ul style="list-style-type: none"> • 56.6 Kbps
Audio	<ul style="list-style-type: none"> • Internal microphone • Internal speaker • Software control volume
Infrared transfer	IrDA 1.1
PC Card	One Type-III or two Type-II
AC adapter	56-watt type or 72-watt type
Bay device	<p>MT2628 and MT2633 (A20m)</p> <ul style="list-style-type: none"> • 10-24 x CD-ROM drive <p>MT2629 (A20p)</p> <ul style="list-style-type: none"> • 6 x DVD drive

Status indicators

The system status indicators show the current computer status in different colors (green or orange):



Indicator	Meaning
1 Battery	<p>Green: The battery is fully charged.</p> <p>Blinking green: The battery has enough power to operate but is charging.</p> <p>Orange: The battery power is low. The battery is charging.</p> <p>Blinking orange: The battery needs charging.</p>
2 Standby status	<p>Green: The computer is in standby mode.</p> <p>Blinking green: The computer is entering standby mode or hibernation mode, or is resuming normal operation.</p>
3 Drive in use	<p>Green: Data is read from or written to the hard disk drive, diskette drive, or drive in the Ultrabay 2000.</p>
4 Num lock	<p>Green: The numeric keypad on the keyboard is enabled.</p>
5 Caps lock	<p>Green: Caps Lock mode is enabled.</p>
6 Scroll lock	<p>Green: Arrow keys can be used as screen-scroll function keys.</p>
7 Power on	<p>Green: The power is on.</p>

PRODUCT OVERVIEW

The following table shows the test for each FRU.

FRU	Applicable test
System board	<ol style="list-style-type: none"> 1. Diagnostics --> CPU/Coprocessor 2. Diagnostics --> Systemboard
Power	Diagnostics --> IBM AC Adapter, IBM Battery 1, IBM Battery 2 in Other Devices
LCD unit	<ol style="list-style-type: none"> 1. Diagnostics --> Video Adapter 2. Interactive Tests --> Video
Modem	<ol style="list-style-type: none"> 1. Make sure the modem is set up correctly. 2. Replace the modem jack and the modem card in turn, and run the following test in Other Devices (Diagnostics): <ol style="list-style-type: none"> a. Modem Register Test b. Modem DTMF/LoopBack Test c. Internal Modem Register d. Internal Modem LoopBack/DTMT
Audio	<ol style="list-style-type: none"> 1. Interactive Tests --> Internal Speaker 2. Diagnostics --> Crystal SoundFusion™ Test in Other Devices
Speaker	Interactive Tests --> Internal Speaker
PC Card slots	Diagnostic --> PCMCIA, PCMCIA External Loop in Systemboard
Keyboard	<ol style="list-style-type: none"> 1. Diagnostics --> Keyboard in Systemboard 2. Interactive Test --> Keyboard

PRODUCT OVERVIEW

FRU	Applicable test
TrackPoint or pointing device	<p>If the TrackPoint does not work, check the configuration in the ThinkPad Configuration program. If the TrackPoint is disabled, select Enable to enable it.</p> <p>After you use the TrackPoint, the pointer may drift on the screen for a short time. This drift can occur when a slight, steady pressure is applied to the TrackPoint pointer. This symptom is not a hardware problem. No service action is necessary if the pointer stops after a short time.</p> <p>If enable the TrackPoint does not correct the problem, continue with the following.</p> <ul style="list-style-type: none"> • Interactive Tests --> Mouse
Hard disk drive	Diagnostics --> Fixed Disks
Diskette drive	<ol style="list-style-type: none"> 1. Diagnostics --> Diskette Drives 2. Interactive Tests --> Diskette
CD-ROM or DVD drive	<ol style="list-style-type: none"> 1. Diagnostics --> CD-ROM/DVD in Other Devices 2. Interactive Tests --> CD-ROM/DVD
Memory	<ol style="list-style-type: none"> 1. If two DIMMs are installed, remove one of them and run Memory Test - Quick (Diagnostics). 2. If the problem does not recur, replace the DIMM, remove the other one, and run the test again. 3. If the test does not detect the error, run Memory Test - Full (Diagnostics).
Fan	<ol style="list-style-type: none"> 1. Turn on the computer and check the air turbulence at the louver near the power switch. 2. In Other Devices (Diagnostics), run IBM Fan

Fn key combinations

The following table shows the function of each combination of **Fn** with a function key.

The **Fn** key works independently from the operating system.

Key combination	Description
Fn + F1	Reserved.
Fn + F2	Reserved.
Fn + F3	Turn off the LCD display, leaving the screen blank. Press any key or the TrackPoint stick to turn the LCD display on again.
Fn + F4	Turn standby mode on. Press the Fn key to return to normal operation.
Fn + F5	Reserved.
Fn + F6	Reserved.
Fn + F7	Switch between the LCD and an external monitor.
Fn + F8	Turn screen expansion on or off. (There is no symbol on the key.)
Fn + F9	Reserved.
Fn + F10	Reserved.
Fn + F11	Reserved.
Fn + F12	Turn hibernation mode on.
Fn + PgUp	Turn the ThinkLight on or off.
Fn + Home	The LCD becomes brighter.
Fn + End	The LCD becomes less bright.

Symptom-to-FRU index

The symptom-to-FRU index lists symptoms and errors and their possible causes. The most likely cause is listed first, in boldface type.

Note: Do the FRU replacement or other actions in the sequence shown in the column headed "FRU or action, in Sequence". If replacing a FRU does not solve the problem, put the original part back in the computer. Do not replace a nondefective FRU.

This index can also help you determine, during regular servicing, what FRUs are likely to need to be replaced next.

A numeric error is displayed for each error detected in POST or system operation. In the displays, **n** can be any number.

If no numeric code is displayed, check the narrative descriptions of symptoms. If the symptom is not described there, go to "Intermittent problems" on page 46.

Note: For an IBM devices not supported by diagnostic codes in the ThinkPad notebook computers, see the manual for that device.

Numeric error codes

Symptom or error	FRU or action, in sequence
0175 Bad CRC1, stop POST task. The EEPROM checksum is not correct.	1. System board.
0187 EAIA data access error	1. System board.
0188 Invalid RFID serialization information area or bad CRC2.	1. System board.
0189 Invalid RFID configuration information area.	1. System board.
0190 Critical low battery error.	1. Charge the battery pack. 2. Battery pack.
0193 RF antenna has been removed.	1. Enter the supervisor password.

SYMPTOM-TO-FRU INDEX

Symptom or error	FRU or action, in sequence
0194 The computer has been carried through a security gate.	1. Enter the supervisor password.
0200 Fixed disk failure	1. Reseat the hard disk drive. 2. Load Setup Defaults in IBM BIOS Setup Utility. 3. Hard disk drive. 4. System board.
021x Stuck key Keyboard error	1. Run an interactive tests of the keyboard and auxiliary input device.
0220 Monitor type does not match CMOS	1. Load Setup Defaults in IBM BIOS Setup Utility.
0230 Shadow RAM failure at offset nnnn	1. System board.
0231 System RAM failure at offset nnnn	1. DIMM. 2. System board.
0232 Extended RAM failure at offset nnnn	1. DIMM. 2. System board.
0250 System battery is dead—replace and run setup	1. Replace the backup battery and run IBM BIOS Setup Utility to reset the time and date.
0251 System CMOS checksum bad—Default configuration used	1. Replace the backup battery and run IBM BIOS Setup Utility to reset the time and date.
0252 Password checksum bad.	1. Reset the password by running IBM BIOS Setup Utility.
0260 System timer error	1. Replace the backup battery. and run IBM BIOS Setup Utility to reset the time and date. 2. System board.
0270 Real time clock error	1. Replace the backup battery and run IBM BIOS Setup Utility to reset the time and date. 2. System board.

SYMPTOM-TO-FRU INDEX

Symptom or error	FRU or action, in sequence
0271 Date and time error	1. Run IBM BIOS Setup Utility to reset the time and date.
0280 Boot incomplete error— Default configuration used	1. Load Setup Defaults in IBM BIOS Setup Utility. 2. DIMM. 3. System board.
02F4 EISA CMOS not writable.	1. Load Setup Defaults in IBM BIOS Setup Utility. 2. Replace the backup battery. 3. System board.
02F5 DIMM test failure	1. DIMM. 2. System board.
02F6 Software NMI failure	1. DIMM. 2. System board.
02F7 Fail-safe timer NMI failure	1. DIMM. 2. System board.

Error messages

Symptom or error	FRU or action, in sequence
Device address conflict	1. Load Setup Defaults in IBM BIOS Setup Utility. 2. Backup battery. 3. System board.
Allocation error for device	1. Load Setup Defaults in IBM BIOS Setup Utility. 2. Backup battery. 3. System board.
Failing bits: nnnn	1. DIMM. 2. System board.
Invalid system configuration data	1. DIMM. 2. System board.
I/O device IRQ conflict	1. Load Setup Defaults in IBM BIOS Setup Utility. 2. Backup battery. 3. System board.

SYMPTOM-TO-FRU INDEX

Symptom or error	FRU or action, in sequence
Operating system not found	<ol style="list-style-type: none"> 1. Enter IBM BIOS Setup Utility and see whether the hard disk drive and the diskette drive are properly identified. 2. Diskette drive. 3. Hard disk drive. 4. System board.
Hibernation error	<ol style="list-style-type: none"> 1. Restore the system configuration to what it was the before the computer entered hibernation mode. 2. If memory size has been changed, re-create the hibernation file.
Operating system not found	<ol style="list-style-type: none"> 1. Reseat the hard disk drive. 2. Check the book sequence by use of IBM BIOS Setup Utility.
Fan error	<ol style="list-style-type: none"> 1. Fan.

Beep symptoms

Symptom or error	FRU or action, in sequence
One beep and a blank, unreadable, or flashing LCD	<ol style="list-style-type: none"> 1. Reseat the LCD connector. 2. LCD assembly. 3. System board.
One long and two short beeps, and a blank or unreadable LCD	<ol style="list-style-type: none"> 1. System board. 2. LCD assembly.
Two short beeps with error codes	POST error. See "Numeric error codes" on page 41.
Two short beeps with blank screen	<ol style="list-style-type: none"> 1. System board.
Only cursor appears	<ol style="list-style-type: none"> 1. Reinstall operating system.

SYMPTOM-TO-FRU INDEX

No beep symptoms

Symptom or error	FRU or action, in sequence
No beep, power-on indicator on, LCD blank, and no POST	<ol style="list-style-type: none"> 1. Make sure that every connector is connected tightly and correctly. 2. DIMM. 3. System board.
No beep, power-on indicator on, and LCD blank during POST	<ol style="list-style-type: none"> 1. Reseat DIMM. 2. System board.
No beep during POST, but system runs correctly	<ol style="list-style-type: none"> 1. Speaker.
The power-on password prompt	A power-on password or a supervisor password is set. Type the password and press Enter .
The hard disk password prompt	A hard disk password is set. Type the password and press Enter .
The DOS-full screen looks smaller.	Start the ThinkPad Configuration program and set the Screen expansion function.

LCD-related symptoms

Important

The TFT LCD for the notebook computer contains many thin-film transistors (TFTs). A small number of dots that are missing, discolored, or always lighted is characteristic of TFT LCD technology, but excessive pixel problems can cause viewing concerns. The LCD should be replaced if the number of missing, discolored, or lighted dots in any background is:

- **SVGA:** 5 or more bright dots, 5 or more dark dots, or a total of 9 or more bright and dark dots.
- **XGA:** 8 or more bright dots, 8 or more dark dots, or a total of 9 or more bright and dark dots.
- **SXGA+:** 11 or more bright dots, 11 or more dark dots, or a total of 16 or more bright and dark dots.

Symptom or error	FRU or action, in sequence
No beep, power-on indicator on, and a blank LCD during POST	<ol style="list-style-type: none"> 1. System board.

SYMPTOM-TO-FRU INDEX

Symptom or error	FRU or action, in sequence
<ul style="list-style-type: none"> • LCD backlight not working • LCD too dark • LCD brightness cannot be adjusted • LCD contrast cannot be adjusted 	<ol style="list-style-type: none"> 1. Reseat the LCD connectors. 2. LCD assembly. 3. System board.
<ul style="list-style-type: none"> • LCD screen unreadable • Characters missing pixels • Screen abnormal • Wrong color displayed 	<ol style="list-style-type: none"> 1. See important note for “LCD-related symptoms”. 2. Reseat all LCD connectors. 3. LCD assembly. 4. System board.
Horizontal or vertical lines displayed on LCD	<ol style="list-style-type: none"> 1. LCD assembly.

Intermittent problems

Intermittent system hang problems can be due to a variety of causes that have nothing to do with a hardware defect, such as: cosmic radiation, electrostatic discharge, or software errors. FRU replacement should be considered only when a recurring problem exists.

When analyzing an intermittent problem, do the following:

1. Run the diagnostic test for the system board in loop mode **at least 10 times**.
2. If no error is detected, do **not** replace any FRUs.
3. If any error is detected, replace the FRU shown by the FRU code. Rerun the test to verify that no more errors exist.

Undetermined problems

You are here because the diagnostic tests did not identify which adapter or device failed, installed devices are incorrect, a short circuit is suspected, or the system is inoperative. Follow these procedures to isolate the failing FRU (do not isolate FRUs that have no defects).

Verify that all attached devices are supported by the computer.

Verify that the power supply being used at the time of the failure is operating correctly. (See “Power system checkout” on page 28.)

1. Power off the computer.
2. Visually check each FRU for damage. Replace any damaged FRU.
3. Remove or disconnect all of the following devices:
 - a. Non-IBM devices
 - b. Devices attached to the port replicator
 - c. Printer, mouse, and other external devices

SYMPTOM-TO-FRU INDEX

- d. Battery pack
 - e. Hard disk drive
 - f. External diskette drive
 - g. DIMM
 - h. CD-ROM and diskette drive in the UltraslimBay
 - i. PC Cards
4. Power on the computer.
 5. Determine whether the problem has changed.
 6. If the problem does not recur, reconnect the removed devices one at a time until you find the failing FRU.
 7. If the problem remains, replace the following FRUs one at a time (do not replace a nondefective FRU):
 - a. System board
 - b. LCD assembly

FRU replacement notices

This section contains notices related to removing and replacing parts. Read this section carefully before replacing any FRU.

Screw notices

Loose screws can cause a reliability problem. The an IBM ThinkPad computer address this problem with special nylon-coated screws that have the following characteristics:

- They maintain tight connections.
- They do not easily come loose, even with shock or vibration.
- They are harder to tighten.
- They should be used only once.

Do the following when you service this machine:


- Keep the screw kit (P/N 05K4841) in your tool bag.
- Always use new screws.
- Use a torque screwdriver if you have one.

Tighten screws as follows:

- **Plastic to plastic**

Turn an additional **90 degrees** after the screw head touches the surface of the plastic part:

90 degrees more




(Cross section)

- **Logic card to plastic**

Turn an additional **180 degrees** after the screw head touches the surface of the logic card:

180 degrees more



(Cross section)

- **Torque driver**

If you have a torque driver, refer to the "Torque" column with each step.

FRU REPLACEMENT NOTICES

- Make sure you use the correct screw. If you have a torque screwdriver, tighten all screws firmly to the torque shown in the table. **Never use a screw that you removed. Use a new one. Make sure the screws are tightened firmly**

Retaining serial numbers

This section includes the following descriptions:

- "Restoring the serial number of the system unit"
- "Retaining the UUID"

Restoring the serial number of the system

unit: When the computer was manufactured, the EEPROM on the system board was loaded with the serial numbers of the system and all major components. The numbers need to remain the same throughout the life of the computer.

If you replace the system board, you must restore serial number of the system unit to its original value.

Before replacing the system board, save the original serial number by doing the following:

1. Install the ThinkPad Hardware Maintenance Diskette Version 1.60, and restart the computer.
2. From the main menu, select **1. Set System Identification**.
3. Select **2. Read S/N data from EEPROM**.

The serial number for each device is displayed. Write down the serial number of the system unit, designated as follows:

20: System unit serial number

After you have replaced the system board, restore the serial number by doing the following:

1. Install the ThinkPad Hardware Maintenance Diskette Version 1.60 and restart the computer.
2. From the main menu, select **1. Set System Identification**.
3. Select **1. Add S/N data from EEPROM**.

Follow the instructions on the screen.

Note: The serial number of the system unit is written on the label attached on the bottom of the computer.

Retaining the UUID: The Universally Unique Identifier (UUID) is a 128-bit number uniquely assigned to your computer at production and stored in the EEPROM of your system board. The algorithm that generates the unique number is designed to provide unique IDs until the

FRU REPLACEMENT NOTICES

year A.D. 3400. No two computers in the world have the same number.

When you replace the system board, you must set the UUID on the new system board as follows:

1. Install the ThinkPad Hardware Maintenance Diskette Version 1.60, and restart the computer.
2. Select **4. Assign UUID** from the main menu.

A new UUID is created and written. If a valid UUID already exists, it is not overwritten.

Removing and replacing a FRU

This section presents information and drawings for use in removing and replacing a FRU. Be sure to observe the following general rules:

1. Do not try to service the computer unless you have been trained and certified. An untrained person runs the risk of damaging parts.
2. Before replacing any FRU, review "FRU replacement notices" on page 48.
3. Begin by removing any FRUs that have to be removed before the failing FRU. Any such FRUs are listed at the top of the page. Remove them in the order in which they are listed.
4. Follow the correct sequence in the steps for removing the FRU, as indicated in the drawings by the numbers in square callouts.
5. When turning a screw to replace a FRU, turn it in the direction indicated by the arrow in the drawing.
6. When removing the FRU, move it in the direction indicated by the arrow in the drawing.
7. To put the new FRU in place, reverse the removal procedure and follow any notes that pertain to replacement. For information about connecting and arranging internal cables, see "Locations" on page 88.
8. When replacing a FRU, use the correct screw as shown in the procedures.

CAUTION:

Before removing any FRU, power off the computer, unplug all power cords from electrical outlets, remove the battery pack, and then disconnect any interconnecting cables.

CAUTION:

Do not disassemble it, throw it into fire or water, or short-circuit it. Dispose of the battery pack as required by local ordinances or regulations.


Attention: Before the computer is powered on after FRU replacement, make sure all screws, springs, and other small parts are in place and are not loose inside the computer. Verify this by shaking the computer gently and listening for rattling sounds. Metallic parts or metal flakes can cause electrical short circuits.

Attention: The system board is sensitive to, and can be damaged by, electrostatic discharge. Establish personal grounding by touching a ground point with one hand before touching these units.

You must use an electrostatic discharge (ESD) strap (P/N 6405959) to establish personal grounding.

REMOVING AND REPLACING A FRU

1010 Battery pack




REMOVING AND REPLACING A FRU

1020 DIMM

- Battery pack (1010)

Note: Loosen the screw **1**, but do not remove it.




1030 Backup battery

CAUTION:

The backup battery is a lithium battery and can cause a fire, an explosion, or severe burns. Do not recharge it, remove its polarized connector, disassemble it, heat it above 100°C (212°F), incinerate it, or expose its cell contents to water. Dispose of the battery as required by local ordinances or regulations. The use of an incorrect battery can result in ignition or explosion of the battery.


- Battery pack (1010)
- DIMM (1020)



REMOVING AND REPLACING A FRU


1040 Mini PCI adapter

- Battery pack (1010)



(continued)

REMOVING AND REPLACING A FRU



Note: The illustration shows the combo card. Connector **(A)** is for the LAN feature and **(B)** is for the modem. This slot also supports a Mini PCI modem card or Mini PCI network card. Step **5** depends on the card type. Disconnect either **(A)**, **(B)**, or both.

1050 Hard disk drive or RF ID adapter


Attention

Do not drop the hard disk drive or apply any shock to it. The hard disk drive is sensitive to physical shock. Incorrect handling can cause damage and permanent loss of data.

Before removing the drive, have the user make a backup copy of all the information on the drive if possible.


Never remove the drive while the system is operating or is in suspend mode.

- Battery pack (1010)



Note: The hard disk is attached to the cover.

Step	Screw (quantity)
1	Coin screw (1) or security screw (1)
Note: Use a 2.5-mm allen wrench to remove the security screw.	




When installing: Make sure that the HDD connector is firmly connected.

REMOVING AND REPLACING A FRU

1060 Ultrabay 2000 device


Any of several devices can be inserted into the Ultrabay 2000. The procedure for installing and removing is the same for every device.

Note: When you release the switch in step **1** the lever pops out. Pull the lever a little in step **2** to release the device from the bay.



(continued)


REMOVING AND REPLACING A FRU



REMOVING AND REPLACING A FRU

1070 Keyboard


- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)



Step	Screw (quantity)	Torque
1	M2.5 × 15 mm, nylon-coated (3)	39.2 Ncm (4 kgfcm)

(continued)

REMOVING AND REPLACING A FRU




(continued)


REMOVING AND REPLACING A FRU

When installing: When installing the keyboard, do as follows:

1. Install the new keyboard, following the directions in the figure. Make sure that the keyboard edges, shown in the figure as **(A)**, **(B)**, and **(C)**, are under the frame.




2. Push the **Y** key **1** to connect the keyboard to the connector on the underside of the key; then push the frame of the keyboard **2** to latch the latches.



REMOVING AND REPLACING A FRU

1080 Hinge cover

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)




Step	Screw (quantity)	Torque
1	M2.5 × 15 mm, nylon-coated (1)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

1090 Keyboard bezel and speaker


- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)




Step	Screw (quantity)	Torque
1	M2.5 × 4.8 mm, nylon-coated (7)	39.2 Ncm (4 kgfcm)

(continued)

REMOVING AND REPLACING A FRU



Step	Screw (quantity)	Torque
2	M2.5 × 15 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)




Cable routine:

When replacing the cable, see the preceding figure for its cable routing.

REMOVING AND REPLACING A FRU

1100 Microphone cable

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)




When installing: Make sure that you fasten the connector firmly.

REMOVING AND REPLACING A FRU

1110 Sub card

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)




Step	Screw (quantity)	Torque
2	M2.5 × 4.8 mm, nylon-coated (1)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

1120 PC Card slot assembly

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- Sub card (1110)




Step	Screw (quantity)	Torque
1	M2.0 × 9.5 mm, nylon-coated (2)	24.5 Ncm (2.5 kgfcm)

REMOVING AND REPLACING A FRU

1130 Fan assembly

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)

Note: Step **1a** is for the MT2629 model only.




Step	Screw (quantity)	Torque
1a	M2.5 × 4.8 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)
1	M2.5 × 4.8 mm, nylon-coated (3)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

1140 Diskette drive

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)

Note: The heatpipe **A** and the screw **1a** are for the MT2629 model only. Other models do not have them.




Step	Screw (quantity)	Torque
1a	M2.5 × 4.8 mm, nylon-coated (1)	39.2 Ncm (4 kgfcm)
1	M2.5 × 4.8 mm, nylon-coated (1)	39.2 Ncm (4 kgfcm)
2	M2.5 × 15 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

1150 Upper shield

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- Sub card (1110)
- PC Card slot assembly (1130)
- Fan assembly(1130)
- Diskette drive (1140)




Step	Screw (quantity)	Torque
1	M2.5 × 15 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)
2	M2.5 × 4.8 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

1160 TV card (The MT2629 model only)

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- Sub card (1110)
- PC Card slot assembly (1130)
- Fan assembly(1130)
- Diskette drive (1140)
- Upper shield (1150)



Cable routine:

When replacing the modem cable, see the figure for the cable routing.


REMOVING AND REPLACING A FRU

1170 CPU socket and system board

- Battery pack (1010)
- DIMM (1020)
- Backup battery (1030)
- Mini PCI adapter (1040)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- Sub card (1110)
- PC Card slot assembly (1130)
- Fan assembly(1130)
- Diskette drive (1140)
- Upper shield (1150)

1 2 for the CPU socket

1 2 3 4 for the system board




Step	Screw (quantity)	Torque
1	M2.5 × 15 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)
3	M2.5 × 4.8 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

2010 LCD assembly

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)


Note: Step **1a** is for the MT2629 model only.



Step	Screw (quantity)	Torque
1a	M2.5 × 4.8 mm, nylon-coated (3)	39.2 Ncm (4 kgfcm)
1	M2.5 × 4.8 mm, nylon-coated (4)	39.2 Ncm (4 kgfcm)

(continued)

REMOVING AND REPLACING A FRU




Step	Screw (quantity)	Torque
2	Special, nylon-coated (2)	—
4	M2.5 × 4.8 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

2020 Front bezel

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- LCD assembly (2010)




Step	Screw (quantity)	Torque
1	M2.5 × 4.8 mm, nylon-coated (2)	39.2 Ncm (4 kgfcm)

REMOVING AND REPLACING A FRU

2030 Inverter card

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- LCD assembly (2010)
- Front bezel (2020)

12.1-in. panel




Step	Screw (quantity)	Torque
1	M2.5 × 4.8 mm, nylon-coated (1)	39.2 Ncm (4 kgfcm)


(continued)

REMOVING AND REPLACING A FRU

14.1-in. and 15.0-in. panels



Step	Screw (quantity)	Torque
1	M2.5 × 4.8 mm, nylon-coated (1)	39.2 Ncm (4 kgfcm)




REMOVING AND REPLACING A FRU

2040 LCD panel

- Battery pack (1010)
- Hard disk drive (1050)
- Ultrabay 2000 device (1060)
- Keyboard (1070)
- Hinge cover (1080)
- Keyboard bezel and speaker (1090)
- LCD assembly (2010)
- Front bezel (2020)
- Inverter card (2030)


12.1-in. panel



Step	Screw (quantity)	Torque
1	M2.5 × 5.7 mm, nylon-coated (4)	See note.
Note:		
MT2628-1xx, -2xx:	39.2 Ncm (4 kgfcm)	
MT2628-3xx:	24.5 Ncm (2.5 kgfcm)	
MT2628-4xx, MT2633:	16.7 Ncm (1.7 kgfcm)	
MT2629:	19.6 Ncm (2 kgfcm)	

(continued)


REMOVING AND REPLACING A FRU



(continued)

REMOVING AND REPLACING A FRU

14.1-in. and 15.0-in. panels





Step	Screw (quantity)	Torque
1	M2.5 × 4.8 mm, nylon-coated (4)	39.2 Ncm (4 kgfcm)

(continued)

REMOVING AND REPLACING A FRU


Notes:

1. For the 14-in. LCD, the LCD cable is taped onto the connector. Tear off the tape before disconnecting the LCD cable in step **3**.
2. Only the LCD cable for the 15.0-in SVGA+ LCD (27L0488) has the UltraPort connector and need step **5**. If the UltraPort adapter has been screwed onto the LCD, remove the adapter before step **5**. To do this, remove the screw from both sides of the adapter.




REMOVING AND REPLACING A FRU

3010 ThinkPad Dock PCI cover




REMOVING AND REPLACING A FRU

3010 ThinkPad Dock top cover



(Rear view)

Step	Screw (quantity)	Torque
1	M2.5 × 4.8 mm (2)	39.2 Ncm (4 kgfcm)




(Bottom view)

Step	Screw (quantity)	Torque
2	M2.5 × 4.8 mm (8)	39.2 Ncm (4 kgfcm)

(continued)

REMOVING AND REPLACING A FRU


Make sure that the system lock key **A** is set to the Unlock position. Release the front latches in step **3**, and then remove the top cover **4**. For step **5**, see the inside view, shown in the circle.




REMOVING AND REPLACING A FRU

When replacing: When replacing the top cover, make sure of the following:

- The springs placed correctly.




- The device release lever is seated correctly.



(continued)

REMOVING AND REPLACING A FRU

- The release button works correctly.



LOCATIONS

Locations



Front view

- 1** System status indicators
- 2** Battery and standby mode status indicators
- 3** Built-in stereo speakers
- 4** PC Card slots
- 5** PC Card eject button
- 6** Bay latch
- 7** Eject button
- 8** Ultrabay 2000 device

Note: The Ultrabay 2000 accepts storage devices, such as a DVD drive or a CD-ROM drive.

- 9** Video-out connector
- 10** Video-in connector
- 11** TrackPoint pointing stick
- 12** TrackPoint buttons
- 13** ThinkPad button
- 14** Volume buttons
- 15** Power switch



LOCATIONS



LOCATIONS

Rear view


- 1** Security keyhole
- 2** Parallel connector
- 3** Modem connector
- 4** Power jack
- 5** Serial connector
- 6** External-monitor connector
- 7** Universal serial bus (USB) connector
- 8** External-input-device connector
- 9** Power jack



LOCATIONS

Bottom view

- 1** Battery pack
- 2** Battery pack latches
- 3** Mini PCI card slot
- 4** Docking connector
- 5** Stereo headphone jack
- 6** Stereo line-in jack
- 7** Diskette drive
- 8** Microphone jack
- 9** Infrared port
- 10** Hard disk drive
- 11** LCD latches
- 12** LCD latches



PARTS LIST


Parts List

A20 series model matrix

The A20 series includes several models. The following table summarizes the characteristics of each model, to help you determine which FRU in the part list meets your need. The table contains an entry for each of the three types of model A20 m (MT2628), they are labeled A, B, and C.

CPU	LCD (in.) Bay device	Video memory (V-mem) on the system board
MT2628 (A): A20m, MT2628-1xx and -2xx		
<ul style="list-style-type: none"> • Celeron 500 • Pentium III 500 	12.1 in. CD-ROM drive	4 MB
MT2628 (B): A20m, MT2628-3xx		
<ul style="list-style-type: none"> • Celeron 500 	15.0 in. CD-ROM drive	8 MB
MT2628 (C): A20m MT2628-4xx		
<ul style="list-style-type: none"> • Pentium III 650 with SpeedStep technology 	14.1 in. CD-ROM drive	8 MB
MT2633: A20m		
<ul style="list-style-type: none"> • Pentium III 650 with SpeedStep technology 	14.1 in. CD-ROM drive	8 MB
MT2629: A20p		
<ul style="list-style-type: none"> • Pentium III 700 with SpeedStep technology 	15.0 in. DVD drive	16 MB

PARTS LIST



PARTS LIST

No.	FRU	P/N
1	LCD unit (see "LCD FRU" on page 96)	
2	Hinge cover	
	MT2628 (A, C), and MT2633	08K5671
	MT2628 (B) and MT2629	08K5672
3	Speaker assembly	
	MT2628 (A, C), and MT2633	02K5007
	MT2628 (B) and MT2629	02K5008
4	Keyboard bezel	
	MT2628 (A, C), and MT2633	08K5667
	for Korea	08K5669
	MT2628 (B) and MT2629	08K5668
	for Korea	08K5670
5	Heatpipe, for MT2629	08K6650
6	Fan assembly, for MT2628 (A) and (B)	08K5650
	Fan assembly, for MT2628 (C), MT2633, and MT2629	08K6614
7	Sub card	10L1418
8	PC Card slots	08K5649
9	Stiffner, CPU socket (includes fan assembly)	
10	TV card, for MT2629	10L1419
11	Backup battery	02K6572
	Holder, backup battery (see base miscellaneous parts)	
12	Mini PCI combo card (see "Options FRU list" on page 100)	
	Mini PCI Ethernet (Intel)	10L1423
	Mini PCI modem	08K3146
13	Base cover	
	MT2628 (A, B)	08K5639
	for T-China	08K5641
	for Korea	08K5645
	MT2628 (C)	08K6647
	for T-China	08K6648
	for Korea	08K6649
	MT2629	08K5640
	for T-China	08K5642
	for Korea	08K5646
	MT2633	08K5901
	for T-China	08K5902
	for Korea	08K5904

(continued)

PARTS LIST

No.	FRU	P/N
14	UltralimBay CD-ROM drive (see "Options FRU list" on page 100)	
	UltralimBay DVD drive (MKE) (see "Options FRU list" on page 100)	
	UltralimBay DVD drive (TOSHIBA), for MT2629	05K9160
15	Cover, Mini PCI adapter slot	08K5673
16	Battery pack (6 cell), SANYO	02K6618
	Battery pack (6 cell), Panasonic	02K6614
	Battery pack (9 cell), SANYO, for MT2629	02K6619
	Battery pack (9 cell), Panasonic, for MT2629 (see "Options FRU list" on page 100)	
17	Cover, DIMM slot	08K5674
18	Hard disk drive (see "Options FRU list" on page 100)	
19	Cover, hard disk drive	
	MT2628 (A, C), and MT2633	08K5675
	MT2628 (B) and MT2629	08K5676
	Asset ID RF adapter (see "Options FRU list" on page 100)	
20	System board	
	V-mem 4 MB, for MT2628 (A)	10L1411
	V-mem 8 MB, for MT2628 (B)	10L1412
	V-mem 8 MB, for MT2628 (C) and MT2633	08K3152
	V-mem 16MB, for MT2629	10L1413
21	DIMM (see "Options FRU list" on page 100)	
22	CPU socket, Celeron 500 MHz	08K3149
	CPU socket, Pentium III 500 MHz	10L1415
	CPU socket, Pentium III 650 MHz with SpeedStep technology	10L1405
	CPU socket, Pentium III 700 MHz with SpeedStep technology	10L1417
23	Upper shield	08K5651
24	Diskette drive (TEAC)	05K9157
	Diskette drive (SONY)	05K9156
25	Microphone assembly	27L0484
26	Keyboard (see "Keyboard" on page 97)	
	Pointing stick cap	84G6536
	Telephone cable	05K2707

(continued)

PARTS LIST

LCD FRU

12.1-inch SVGA TFT

FRU	P/N
LCD cover assembly	08K5655
for Korea	08K5659
LCD cables	27L0485
LCD panel (SANYO)	05K9577
Hinges	08K5664
Inverter card	08K3120

14.1-inch XGA TFT

FRU	P/N
LCD cover assembly	08K5656
for Korea	08K5660
LCD cable	27L0486
LCD panel (DBU)	05K9578
LCD panel (SAMSUNG)	05K9588
Hinges	08K5665
Inverter card	08K3179

15.0-inch XGA TFT

FRU	P/N
LCD cover assembly	08K5657
for Korea	08K6443
LCD cable	27L0487
LCD panel (SAMSUNG)	05K9580
Hinges	08K5666
Inverter card	10L1421

15.0-inch SVGA+ TFT

FRU	P/N
LCD cover assembly	08K5658
for Korea	08K5662
LCD cable	27L0488
LCD panel (DBU)	05K9581
Hinges	08K5666
Inverter card	10L1422

PARTS LIST

Keyboard

Language	P/N
Arabic	02K5051
Belgian	02K5045
Canadian French	02K5035
Chinese, traditional	02K5057
Czech	02K5055
Danish	02K5042
Dutch	02K5039
European Spanish	02K5044
European French	02K5038
German	02K5037
Greek	02K5048
Hungary	02K5054
Hebrew	02K5049
Italian	02K5043
Japanese	02K5056
Korean	02K5058
Latin American Spanish	02K5059
Norwegian	02K5041
Polish	02K5150
Portuguese	02K5047
Russian	02K5052
Slovakian	02K5053
Slovenian	02K5151
Swedish or Finnish	02K5040
Swiss	02K5046
Turkish	02K5050
U.K. English	02K5036
U.S. English	02K5034

PARTS LIST

Miscellaneous parts

FRU	P/N
Screw kit (including nylon-coated screws): <ul style="list-style-type: none"> • M2 x 3.6 mm, flat head (3) • M2 x 5.7 mm, flat head (5) • M2 x 16 mm, bind head (3) • M2.5x 4.8 mm, flat head (38) • M2.5 x 15 mm, flat head (15) • M2.6 x 2.8 mm, bind head (7) • M3 x 2.8 mm, flat head (5) • Coin screw (1) • Security screw (1) • Screw caps (8) 	08K5677
Base miscellaneous parts <ul style="list-style-type: none"> • Lens, IR • Lens, Ultrabay 2000 LES • Lock, battery • Holder, backup battery • Spring, battery lock • Lid, docking FR • Lid, docking RR • Spring, Lid docking • Rubber foot • Sponge • Sponge, shield lower • Sponge, small • Blank cap, battery • Screw caps 	08K5647
System miscellaneous parts <ul style="list-style-type: none"> • Door, PC card slots • Spring, PC card slots • Lens, LED hinge • Blank cap, TV connector • Eject knob, Ultrabay 2000 • Lock lever, Ultrabay 2000 • Spring, Ultrabay 2000 • Insulator, hard disk drive • Insulator, keyboard CRU • Mini PCI guide • Screw caps 	08K5654

(continued)

PARTS LIST

FRU	P/N
Miscellaneous parts, for system board <ul style="list-style-type: none"> • I/O bracket (right/left) • Guide, keyboard connector • Hex stud • Card modem connector • Flat head screw (M2.5 x 4.8) • Screw caps 	08K5648
Miscellaneous parts, for diskette drive <ul style="list-style-type: none"> • Bezel • Bracket • Flexible cable • Screw caps 	08K6063
Miscellaneous parts, for LCD <ul style="list-style-type: none"> • Latch (right/left) • Spring • Spacer (for 15.0 in.) • Blank cap, UltraPort • Screw caps 	08K5663

PARTS LIST

Options FRU list

64-MB SDRAM SO DIMM	20L0264
128-MB SDRAM SO DIMM	20L0265
AC adapter (72W), 3-pin	02K6666
AC adapter (72W), 2-pin	02K6669
Battery pack (9 cell), Panasonic, for MT2629	02K6615
Ultrabay CD-ROM drive (TOSHIBA)	05K9158
Hard disk drive (6.0 GB), SSD	05K9227
Hard disk drive (6.0 GB), HITACHI	05K9228
Hard disk drive (12.0 GB), SSD	05K9229
Hard disk drive (12.0 GB), HITACHI	05K9230
Hard disk drive (18.0 GB)	05K9231
Mini PCI combo card	08K3125
Multiple battery charger	02K6642
Ultrabay 2000 2nd HDD adapter	08K6067
Ultrabay 2000 battery	02K6645
Ultrabay 2000 CD-ROM drive (LG)	05K9159
Ultrabay 2000 DVD drive (MKE), for MT2629	05K9188
Ultrabay 2000 SuperDisk drive	05K9235
UltraPort camera	02K5153
IBM tripod	08K6449
UltraPort adapter	08K6105
USB cable attachment	08K6108
USB cable	27L0542
ThinkPad Dock	02K8666
Top cover and screw kit	05K6244
PCI cover	05K6246
ThinkPad Port Replicator	02K8669
Video cable, for MT2629	27L0531

PARTS LIST

Common parts list

Tools

Triconnector wrap plug	72X8546
PC test card	35G4703
Audio wrap cable	66G5180
USB parallel test cable	05K2580
Screwdriver kit	95F3598
Torque screwdriver	05K4695
5mm socket wrench	05K4694
Screwdriver	27L8126
ThinkPad hardware maintenance diskette version 1.60 Note: Download the file from the Web site.	–

PARTS LIST

Power cords: IBM power cords for a specific country are usually available only in that region:

For 2-pin power cords:

Region	P/N
Canada, Taiwan, United States of America	13H5264
Japan	13H5273
Argentina	36L8870

For 3-pin power cords:

Region	P/N
Argentina	36L8867
Australia, New Zealand	76H3514
Canada, Taiwan, United States of America	76H3516
Chile, Ethiopia, Italy, Libya	76H3530
Denmark	76H3520
European countries	76H3524
India, South Africa	76H3522
Israel	76H3532
Korea	76H3535
People's Republic of China (other than Hong Kong)	02K0539
Switzerland	76H3528

Notices

References in this publication to IBM products, programs, or services do not imply that IBM intends to make these available in all countries in which IBM operates. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any of the intellectual property rights of IBM may be used instead of the IBM product, program, or service. The evaluation and verification of operation in conjunction with other products, except those expressly designated by IBM, are the responsibility of the user.

IBM may have patents or pending patent applications covering subject matter in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to the IBM Director of Licensing, IBM Corporation, 500 Columbus Avenue, Thornwood, NY 10594, U.S.A.

Trademarks

The following terms are trademarks of the IBM Corporation in the United States or other countries or both:

- IBM
- ThinkPad
- TrackPoint
- Ultrabay
- Asset ID

PC-Doctor DOS is a trademark of Watergate Software, Inc., in the United States and other countries.

Microsoft, Windows, Windows NT, and the Windows logo are trademarks of Microsoft Corporation in the United States and/or other countries.

Pentium and Celeron are trademarks of Intel Corporation in the United States and/or other countries. (For a complete list of Intel trademarks, see <http://www.intel.com/trademarx.htm>)

Other company, product, or service names may be the trademarks or service marks of others.



Part Number: 19K2330

Printed in U.S.A.