# N-P-N GROWN JUNCTION SILICON TRANSISTOR

# 76 to 333 beta spread Specifically designed for high gain at high temperatures



#### qualification testing

All units are thoroughly heat cycled from -65°C to + 175°C. This test consists of fourteen cycles, including four at 95% relative humidity (from -65°C to +75°C). In addition, the hermetic seal is checked by pressure testing. All units are completely tested for design characteristics and undergo a rigorous tumble test to check for mechanical reliability.

#### mechanical data

Welded case with glass-to-metal hermetic seal between case and leads. Approximate weight is 1.7 grams.

# ALL CONNECTIONS INSULATED FROM CASE 1 - COLLECTOR 0.382 MAX. -1.5 (± 0.032) 0.048 (± 0.005) — 3 LEADS 0.017 (+ 0.002, - 0.001) DIA. 0.190 MAX ALL DIMENSIONS IN INCHES

## absolute maximum ratings at 25°C ambient [except where advanced temperatures are indicated]

Collector Voltage Referred	d to	Ba	ase			٠								•		•	45	V
Emitter Voltage Referred	to	Bas	se														1	V
Collector Current .				100		•											25	mA
Collector Dissipation }				•			1.0		•		8 <b>4</b> 0 F						150	mW
at 100°C } .							,			•							100	mW
at 150°C }				•													50	mW
	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	Collector Voltage Referred to Base												

#### junction temperature

-65°C to +175°C Maximum Range

## common base design characteristics at $T_j = 25$ $^{\circ}$ C [except where advanced temperatures are indicated]

		test cond	ditions	min.	design center	max.	unit	
BV <sub>CBO</sub>	Collector Breakdown Voltage	$I_C = 50\mu A$	$I_E = 0$	45	_	_	Volt	
СВО	Collector Cutoff Current }	$V_{CB} = 30V$	$I_E = 0$	_		2	μΑ	
	at 100° C}	$V_{CB} = 5V$	$I_E = 0$	_	_	10	μΑ	
	at 150° C}	$V_{CB} = 5V$	$I_E = 0$	-		50	μΑ	
hib	Input Impedance	$V_{CB} = 5V$	$I_{E} = -1mA$	30	42	80	Ohm	
hob	Output Admittance	$V_{CB} = 5V$	$I_E = -1mA$	0.0	0.4	1.2	$\mu$ mho	
h <sub>rb</sub>	Feedback Voltage Ratio	$V_{CB} = 5V$	$I_{E} = -1mA$	50	400	1000	X10-6	
hfb	Current Transfer Ratio	$V_{CB} = 5V$	$I_{E} = -1mA$	-0.987	-0.99	-0.997		
PG <sub>e</sub>	Power Gain*†	$V_{CE} = 20V$	$I_E = -2mA$	_	42.5	*	db	
NF	Noise Figure*‡	$V_{CE} = 5V$	$I_{E} = -1mA$	_	20	_	db	
$f_{\alpha b}$	Frequency Cutoff	$V_{CB} = 5V$	$I_{E} = -1mA$	_	7		mc	
Cob	Output Capacitance (1mc)	$V_{CB} = 5V$	$I_{E} = -1 \text{mA}$	_	7	_	$\mu\mu$ f	
Rcs	Saturation Resistance*	$I_B = 2.2 \text{mA}$	$I_C = 5mA$	_	100	200	Ohm	


\*Common Emitter


 $\dagger Rg = 1k$ ;  $R_L = 20k$ 


‡Conventional Noise-Compared to 1000 ohm resistor, 1000 cps and 1 cycle band width


# **TYPE 2N120**


### TYPICAL CHARACTERISTICS














TEXAS INSTRUMENTS

POST OFFICE BOX 312 · DALLAS, TEXAS

TO SUPPLY THE BEST PRODUCTS POSSIBLE, TEXAS INSTRUMENTS RESERVES THE RIGHT TO MAKE CHANGES AT ANY TIME IN ORDER TO IMPROVE DESIGN.