



HP StorageWorks

Enterprise Backup Solution

Hardware/Software Compatibility Matrix

January 2004

Version 1.1

This matrix includes tape automation compatibility details for Direct Attach SCSI (DAS), Direct Attach Fibre (DAF or point-to-point fibre), and Storage Area Network (SAN) connection options. This matrix does not imply device availability.

Products that are scheduled for removal from the EBS Matrix next month will be highlighted in yellow. Automation products will then be moved to the Legacy Support Details page.

[start here](#)

For information about tape drive compatibility and support, go to <http://www.hp.com/go/connect>

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

Libraries Next>> | AutoLoaders | Operating Systems | RAID Arrays | Infrastructure | Servers | Fibre HBAs
 SCSI HBAs | Software | Disk Array Multipath | Firmware & Drivers | Backup App Details | Legacy Support

January 2004

DAS, DAF, and SAN Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Enterprise Libraries											
ESL 9595 (Ultrium 460)	✓			✓ ²	✓	✓	✓	✓	✓	✓	✓
ESL 9595 (Ultrium 230)	✓			✓	✓	✓	✓ ⁵	✓	✓	✓	✓
ESL 9595 S2	✓			✓	✓	✓	✓	✓	✓	✓	✓
ESL 9595 SL	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ESL 9326 SL	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ESL 9326 DX ⁶	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ESL 9322 (Ultrium 460)	✓			✓ ²	✓	✓	✓	✓	✓	✓	✓
ESL 9322 (Ultrium 230)	✓			✓	✓	✓	✓ ⁵	✓	✓	✓	✓
ESL 9322 S2	✓			✓	✓	✓	✓	✓	✓	✓	✓
ESL 9198 SL	✓	✓	✓	✓ ²	✓	✓	✓	✓	✓	✓	✓
ESL 9198 DLX ⁶	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ESL Multi-Unit Scalability ^{3,4}	✓				✓		✓	✓	✓ ⁸		✓
ESL Mixed Media Support	✓			✓						✓ ⁹	✓
Mid-Range Libraries											
MSL 6060 (Ultrium 460)	✓			✓	✓	✓	✓	✓	✓	✓	✓
MSL 5060 (Ultrium 230)	✓			✓	✓	✓	✓ ⁵	✓	✓	✓	✓
MSL 5052 S2	✓			✓	✓	✓	✓	✓	✓	✓	✓
MSL 5052 SL	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
MSL 6030 (Ultrium 460)	✓			✓	✓	✓	✓	✓	✓	✓	✓
MSL 5030 (Ultrium 230)	✓			✓	✓	✓	✓ ⁵	✓	✓	✓	✓
MSL 5026 S2	✓			✓	✓	✓	✓	✓	✓	✓	✓
MSL 5026 SL	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
MSL 5026 DLX ⁶	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
MSL Multi-Unit Scalability ^{3,4}	✓			✓		✓	✓			✓	✓
MSL Mixed Media Support	✓			✓						✓ ⁹	✓
SSL 2020 TL ⁶	✓	✓	✓	✓	✓ ⁷		✓ ¹	✓ ¹	✓ ¹	✓ ⁷	✓ ¹

NOTES:

1) Windows NT/2000 and Solaris support in homogeneous SAN environments only

2) Support is with CA BrightStor ARCserve for Windows NT/2000 v9.0 and CA BrightStor ARCserve for NetWare v7.0 in a homogeneous environment only

3) ESL multi-unit scalability is with a horizontal pass-through mechanism, and the MSL multi-unit scalability is with a vertical pass-through mechanism

4) Contact your ISV for scalability support

5) Ultrium 230 drives are not supported on Windows 2003

6) Not supported with IA-64 operating systems

7) Windows support only

8) Support is with IBM 6228 HBA only

9) Homogeneous Windows only

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

<<Previous Libraries | AutoLoaders | Operating Systems | RAID Arrays | Infrastructure | Servers | Fibre HBAs
 SCSI HBAs | Software | Disk Array Multipath | Firmware & Drivers | Backup App Details | Legacy Support

January 2004

DAF and SAN Support ¹	E2400-160 FC Interface Controller	NSR E1200-160	NSR E2400	NSR E1200	NSR M2402	NSR N1200	MDR
Enterprise Libraries							
ESL 9595 (Ultrium 460)	✓				✓		
ESL 9595 (Ultrium 230)	✓		✓		✓	✓	
ESL 9595 S2	✓		✓		✓	✓	
ESL 9595 SL	✓		✓		✓	✓	✓
ESL 9326 SL	✓		✓		✓	✓	✓
ESL 9326 DX					✓	✓	✓
ESL 9322 (Ultrium 460)	✓				✓		
ESL 9322 (Ultrium 230)	✓		✓		✓	✓	
ESL 9322 S2	✓		✓		✓	✓	
ESL 9198 SL	✓		✓		✓	✓	✓
ESL 9198 DLX	✓		✓		✓	✓	✓
ESL Multi-Unit Scalability	✓		✓		✓	✓	✓
Interface Manager	✓						
Mid-Range Libraries							
MSL 6060 (Ultrium 460)		✓			✓		
MSL 5060 (Ultrium 230)		✓		✓	✓	✓	
MSL 5052 S2		✓		✓	✓	✓	
MSL 5052 SL		✓		✓	✓	✓	✓
MSL 6030 (Ultrium 460)		✓			✓		
MSL 5030 (Ultrium 230)		✓		✓	✓	✓	
MSL 5026 S2		✓		✓	✓	✓	
MSL 5026 SL		✓		✓	✓	✓	✓
MSL 5026 DLX		✓		✓	✓	✓	✓
MSL Multi-Unit Scalability		✓		✓	✓	✓	✓
SSL 2020 TL					✓	✓	✓

NOTE:

1) For ISV compatibility information with the routers, refer to the second [Infrastructure](#) page within this document or [click here](#).

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders Next>>](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

DAS Support	Operating System Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	SyncoSort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup	Native
AutoLoaders¹													
SSL1016 Ultrium 460 Tape Autoloader	HP-UX 11.0	✓						✓		✓		✓	✓
	HP-UX 11.11	✓						✓		✓		✓	✓
	HP-UX 11.22	✓											
	HP-UX 11.23	✓						✓					✓
	Windows NT 4.0	✓			✓	✓			✓	✓	✓	✓	
	Windows 2000 Server/AS	✓			✓	✓		✓	✓	✓	✓	✓	✓
	Windows Server 2003 (32-bit)	✓			✓			✓		✓	✓	✓	✓
	Windows Server 2003 (64-bit)	✓						✓		✓			
	Tru64 5.1							✓					✓
	Tru64 5.1A							✓					✓
	Tru64 5.1B							✓					✓
	Linux Redhat Advanced Server 2.1 (32-bit)							✓				✓	✓
	Linux Redhat Advanced Server 2.1 (64-bit)	✓											
	United Linux 1.0 (32-bit)							✓					
	United Linux 1.0 (64-bit)	✓											
	NetWare 5.1	✓			✓						✓		
	NetWare 6.0	✓			✓						✓		
	Solaris 7	✓						✓		✓		✓	
	Solaris 8	✓						✓		✓		✓	
	Solaris 9	✓						✓					✓
	AIX 4.3.3 (32-bit)							✓		✓		✓	
	AIX 5.1L (32-bit)									✓			
	AIX 5.2 (32-bit)												
SSL1016 SDLT160/320 Tape Autoloader	HP-UX 11.0	✓						✓				✓	✓
	HP-UX 11.11	✓						✓				✓	✓
	HP-UX 11.22	✓											
	HP-UX 11.23	✓											✓
	Windows NT 4.0	✓			✓	✓	✓		✓		✓	✓	
	Windows 2000 Server/AS	✓			✓	✓	✓	✓	✓		✓	✓	✓
	Windows Server 2003 (32-bit)	✓			✓			✓			✓	✓	✓
	Windows Server 2003 (64-bit)	✓						✓					
	Tru64 5.1							✓					✓
	Tru64 5.1A	✓						✓					✓
	Tru64 5.1B	✓						✓					✓
	Linux Redhat Advanced Server 2.1 (32-bit)	✓											✓
	Linux Redhat Advanced Server 2.1 (64-bit)	✓											✓
	United Linux 1.0 (32-bit)	✓											
	United Linux 1.0 (64-bit)	✓											
	NetWare 5.1	✓			✓							✓	
	NetWare 6.0	✓			✓							✓	
	Solaris 7	✓						✓				✓	
	Solaris 8	✓						✓				✓	
	Solaris 9	✓						✓				✓	
	AIX 4.3.3 (32-bit)	✓						✓				✓	
	AIX 5.1L (32-bit)							✓					
	AIX 5.2 (32-bit)												

NOTES:

1) Autoloaders are only supported in Direct Attach SCSI configurations

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 <<Previous AutoLoaders [Next>>](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

DAS Support	Operating System Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Synsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup	Native
AutoLoaders¹													
1/8 Ultrium 460 Tape Autoloader	HP-UX 11.0	✓						✓				✓	✓
	HP-UX 11.11	✓						✓				✓	✓
	HP-UX 11.22												
	HP-UX 11.23	✓											✓
	Windows NT 4.0				✓						✓	✓	
	Windows 2000 Server/AS	✓			✓			✓		✓	✓	✓	✓
	Windows Server 2003 (32-bit)	✓			✓			✓		✓	✓	✓	✓
	Windows Server 2003 (64-bit)	✓						✓					✓
	Tru64 5.1	✓											✓
	Tru64 5.1A	✓											✓
	Tru64 5.1B	✓											✓
	Linux Redhat Advanced Server 2.1 (32-bit)	✓											✓
	Linux Redhat Advanced Server 2.1 (64-bit)	✓											✓
	United Linux 1.0 (32-bit)	✓											
	United Linux 1.0 (64-bit)	✓											✓
	NetWare 5.1	✓			✓						✓		
	NetWare 6.0	✓			✓						✓		
	Solaris 7												✓
	Solaris 8												✓
	Solaris 9												✓
	AIX 4.3.3 (32-bit)												
	AIX 5.1L (32-bit)												✓
	AIX 5.2 (32-bit)												✓
1/8 Ultrium 230 Tape Autoloader	HP-UX 11.0	✓								✓		✓	✓
	HP-UX 11.11	✓								✓		✓	✓
	HP-UX 11.22	✓											
	HP-UX 11.23	✓											✓
	Windows NT 4.0	✓			✓	✓	✓		✓	✓	✓	✓	✓
	Windows 2000 Server/AS	✓			✓	✓	✓	✓	✓	✓	✓	✓	✓
	Windows Server 2003 (32-bit)	✓							✓		✓		✓
	Windows Server 2003 (64-bit)	✓								✓			✓
	Tru64 5.1												
	Tru64 5.1A												
	Tru64 5.1B												
	Linux Redhat Advanced Server 2.1 (32-bit)							✓					✓
	Linux Redhat Advanced Server 2.1 (64-bit)	✓							✓				
	United Linux 1.0 (32-bit)								✓				
	United Linux 1.0 (64-bit)	✓							✓				
	NetWare 5.1	✓			✓								✓
	NetWare 6.0	✓			✓								✓

NOTES:

1) Autoloaders are only supported in Direct Attach SCSI configurations

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [<<Previous AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

DAS Support	Operating System Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup	Native
AutoLoaders¹													
	HP-UX 11.0	✓											✓
	HP-UX 11.11	✓											✓
	HP-UX 11.22	✓											
	HP-UX 11.23	✓											
	Windows NT 4.0	✓	✓	✓	✓	✓	✓		✓		✓		
	Windows 2000 Server/AS	✓	✓	✓	✓	✓	✓	✓	✓		✓		✓
	Windows Server 2003 (32-bit)	✓				✓			✓				✓
	Windows Server 2003 (64-bit)	✓											
	Tru64 5.1												
	Tru64 5.1A												
	Tru64 5.1B												
1/8 DLT vs80 Tape Autoloader	Linux Redhat Advanced Server 2.1 (32-bit)								✓				✓
	Linux Redhat Advanced Server 2.1 (64-bit)	✓							✓				
	United Linux 1.0 (32-bit)								✓				
	United Linux 1.0 (64-bit)	✓							✓				
	NetWare 5.1	✓			✓							✓	
	NetWare 6.0	✓			✓							✓	
	Solaris 7								✓				
	Solaris 8								✓				
	Solaris 9								✓				
	AIX 4.3.3 (32-bit)												
	AIX 5.1L (32-bit)												
	AIX 5.2 (32-bit)												
	HP-UX 11.0								✓		✓		
	HP-UX 11.11								✓		✓		
	HP-UX 11.22												
	HP-UX 11.23	✓											
SSL1016 DLT1 Tape Autoloader	Windows NT 4.0	✓	✓	✓	✓	✓	✓		✓	✓	✓	✓	✓
	Windows 2000 Server/AS	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Windows Server 2003 (32-bit)										✓		
	Windows Server 2003 (64-bit)	✓									✓		
	Tru64 5.1								✓				
	Tru64 5.1A								✓				
	Tru64 5.1B								✓				
	Linux Redhat Advanced Server 2.1 (32-bit)								✓				
	Linux Redhat Advanced Server 2.1 (64-bit)	✓							✓				
	United Linux 1.0 (32-bit)								✓				
	United Linux 1.0 (64-bit)	✓							✓				
	NetWare 5.1				✓								
	NetWare 6.0				✓								
	Solaris 7								✓		✓		
	Solaris 8								✓		✓		
	Solaris 9								✓				
	AIX 4.3.3 (32-bit)								✓		✓		
	AIX 5.1L (32-bit)										✓		
	AIX 5.2 (32-bit)												

NOTES:

1) Autoloaders are only supported in Direct Attach SCSI configurations

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) [Next>>](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

DAS, DAF, and SAN Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Operating Systems¹⁰											
HP-UX 11.0	✓		✓ ²		✓ ²	✓ ²	✓	✓ ²	✓		✓
HP-UX 11.11	✓	✓ ²			✓ ²	✓ ²	✓	✓ ²	✓		✓
HP-UX 11.22 ⁹	✓										
HP-UX 11.23	✓						✓				
Windows NT 4.0		✓	✓	✓ ⁷	✓	✓		✓	✓	✓	✓
Windows 2000 Server/AS	✓	✓	✓	✓ ⁷	✓	✓	✓	✓	✓	✓	✓
Windows Server 2003 (32-bit)	✓			✓ ⁷	✓	✓	✓	✓	✓	✓	✓
Windows Server 2003 (64-bit)	✓						✓	✓	✓		
Tru64 5.1 ³								✓			✓
Tru64 5.1A ³	✓	✓	✓		✓	✓	✓	✓			✓
Tru64 5.1B ³	✓					✓	✓	✓			✓
OpenVMS 7.3-1 ^{3, 11}	✓										
Linux Redhat Advanced Server 2.1 (32-bit)	✓						✓	✓			✓
Linux Redhat Advanced Server 2.1 (64-bit)	✓						✓				
United Linux 1.0 (32-bit)	✓						✓				
United Linux 1.0 (64-bit)	✓										
NetWare 5.1	✓		✓	✓ ⁷				✓		✓	
NetWare 6.0	✓			✓ ⁷		✓		✓		✓	
NetWare 6.5	✓									✓	
Solaris 7	✓					✓	✓		✓		✓
Solaris 8	✓	✓	✓		✓	✓	✓	✓	✓		✓
Solaris 9	✓				✓		✓	✓			✓
AIX 4.3.3 (32-bit)	✓ ⁵		✓			✓	✓		✓		✓
AIX 5.1L (32-bit)						✓	✓ ¹	✓	✓		✓
AIX 5.2 (32-bit and 64-bit)									✓		✓
High Availability⁸											
HP-UX (Service Guard) ⁴	✓ ⁶									✓ ⁶	
Windows (MSCS)	✓	✓	✓			✓	✓	✓	✓	✓	✓
Tru64 (TruCluster)		✓					✓	✓			✓
NetWare 5.1 (NWCS)										✓	
NetWare 6.0 (NWCS)								✓		✓	
Solaris											✓

NOTES:

- 1) DLT8000 products not supported
- 2) A-Class, L-Class, N-Class, and V-Class servers only
- 3) Ultrium 230 (LTO) not supported
- 4) Supported on XP and VA raid array products only
- 5) Robot control is performed on Windows platform
- 6) ATS is not supported

7) Supports ESL9000 libraries in a homogeneous environment only

8) Refer to the EBS Design Guide for details on failover configurations

9) Support for 32 bit emulation mode only

10) Other Operating Systems not listed above may be supported within EBS by the respective ISVs as LAN clients

11) Supported only with the original version 7.3-1 mk driver

OS Version Details >>

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 <<Previous Operating Systems |
 RAID Arrays |
 Infrastructure |
 Servers |
 Fibre HBAs
 SCSI HBAs |
 Software |
 Disk Array Multipath |
 Firmware & Drivers |
 Backup App Details |
 Legacy Support

January 2004

DAS, DAF, and SAN Support	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Operating Systems												
HP-UX 11.0	(HWE 1100) September 2003	(HWE 1100) September 2003		11.0		11.00 w/SP56 (HWE 11.0) PHKL_25769	11.0	(HWE 1100) September 2003	(HWE 1100) September 2003	(HWE 1100) September 2003		(HWE 1100) September 2003
HP-UX 11.11	(HWEnable11i) September 2003	(HWEnable11i) September 2003	11.11			11.11 w/SP56 (HWE 11.11) PHKL_22857	11.11	(HWEnable11i) September 2003	(HWEnable11i) September 2003	(HWEnable11i) September 2003		(HWEnable11i) September 2003
HP-UX 11.22	11.22	11.22										
HP-UX 11.23	11.23	11.23					11.23					
Windows NT 4.0	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a	sp6a
Windows 2000 Server/AS	sp4	sp4	sp2	sp2	sp4	sp4	sp3	sp4	sp4	sp4	sp4	sp4
Windows Server 2003 (32-bit)	✓	✓			✓	✓	✓	✓	✓	✓	✓	✓
Windows Server 2003 (64-bit)	✓	✓					✓		✓	✓	✓	
Tru64 5.1	5.1 pk6							5.1 pk6				5.1 pk6
Tru64 5.1A	5.1A pk4	5.1A pk4	5.1A	5.1A		5.1A pk4	5.1A pk4	5.1A pk4	5.1A pk4	5.1A pk4		5.1A pk4
Tru64 5.1B	5.1B pk1 (ipk)	5.1B pk1 (ipk)					5.1B pk1 (ipk)	5.1B pk1 (ipk)	5.1B pk1 (ipk)			5.1B pk1 (ipk)
OpenVMS 7.3-1 ¹	7.3-1	7.3-1										
Linux Redhat Advanced Server 2.1 (32-bit)	2.4.9-e24	2.4.9-e24						2.4.9-e24	2.4.9-e24			2.4.9-e24
Linux Redhat Advanced Server 2.1 (64-bit)	2.4.8.18-e31	2.4.8.18-e31						2.4.8.18-e31				
United Linux 1.0 (32-bit)	sp2a	sp2a						sp2a				
United Linux 1.0 (64-bit)	sp2a	sp2a										
NetWare 5.1	5.1 sp6	5.1 sp6		5.1 sp5	5.1 sp6				5.1 sp6		5.1 sp6	
NetWare 6.0	6.0 sp3	6.0 sp3			6.0 sp3		6.0 sp3		6.0 sp3		6.0 sp3	
NetWare 6.5	6.5	6.5									6.5	
Solaris 7	7	7					7	7		7		7
Solaris 8	8	8	8	8		8	8	8	8	8		8
Solaris 9	9	9				9		9	9			9
AIX 4.3.3 (32-bit)	4.3.3	4.3.3		4.3.3			4.3.3	4.3.3		4.3.3		4.3.3
AIX 5.1L (32-bit)	5.1L						5.1L	5.1L	5.1L	5.1L		5.1L
AIX 5.2 (32-bit and 64-bit)	5.2									5.2		5.2

NOTES:

1) Supported only with the original version 7.3-1 mk driver

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

SAN Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
RAID Arrays											
XP 1024/128 ¹	✓			✓	✓	HP-UX, NT/WIN 2000, WIN 2003, and Solaris only	✓	HP-UX, NT/WIN 2000, WIN 2003, and Solaris only	HP-UX and NT/WIN2K only	✓	✓
XP 48/512 ¹	✓			✓	✓	HP-UX, NT/WIN 2000, WIN 2003, and Solaris only	✓	HP-UX, NT/WIN 2000, WIN 2003, and Solaris only	HP-UX and NT/WIN2K only	✓	✓
Zero Downtime with XP	✓										
Instant Recovery with XP	✓										
Enterprise Virtual Array EVA 5000 ^{1,3}	Solaris, Tru64, NetWare, HP-UX, NT, W2000, and W2003	NT/WIN2K only	NT/WIN2K only	✓	✓	✓	✓	✓	✓	✓	✓
Enterprise Virtual Array EVA 3000 ^{1,3}	Solaris, Tru64, NetWare, HP-UX, NT, W2000, and W2003	NT/WIN2K only	NT/WIN2K only	✓	✓	✓	✓	✓	✓	✓	✓
VA 7410/7110 ¹	✓			✓			✓			✓	✓
VA 7400/7100 ¹	✓			✓			✓			✓	✓
EMA 16000 ¹	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
EMA 12000/8000 ¹	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
MSA1000 ^{2, 3}	✓	NT/WIN2K only	NT/WIN2K only	✓	✓	NT/WIN2K only	✓	NT/WIN2K and NetWare only	✓	✓	✓

NOTES:

- 1) Consult with your hp solutions provider for disk array SAN compatibility information
- 2) For compatibility information about the optional MSA SAN Switch, refer to the [Infrastructure](#) page within this document for support details
- 3) NetWare supported with FCA2210 HBA only

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure Next>>](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

SAN Support	E2400-160 FC Interface Controller	NSR E1200-160	NSR E2400	NSR E1200	NSR M2402	NSR N1200	MDR
Interconnects¹							
Director Switch 2/140	✓	✓	✓	✓	✓	✓	✓
Director Switch 2/64	✓	✓	✓	✓	✓	✓	✓
Edge Switch 2/32	✓	✓	✓	✓	✓	✓	✓
Edge Switch 2/24	✓	✓	✓	✓	✓	✓	✓
Edge Switch 2/16	✓	✓	✓	✓	✓	✓	✓
Core Switch 2/64	✓	✓	✓	✓	✓	✓	✓
SAN Switch 2/32	✓	✓	✓	✓	✓	✓	✓
SAN Switch 2/16	✓	✓	✓	✓	✓	✓	✓
SAN Switch 2/8	✓	✓	✓	✓	✓	✓	✓
SAN Switch 2/16-EL	✓	✓	✓	✓	✓	✓	✓
SAN Switch 2/8-EL	✓	✓	✓	✓	✓	✓	✓
SAN Switch 16	✓	✓	✓	✓	✓	✓	✓
SAN Switch 8	✓	✓	✓	✓	✓	✓	✓
SAN Switch16EL	✓	✓	✓	✓	✓	✓	✓
SAN Switch 8EL	✓	✓	✓	✓	✓	✓	✓
FC Switch 16B	✓	✓	✓	✓	✓	✓	✓
FC Switch 8B	✓	✓	✓	✓	✓	✓	✓
Cisco MDS 9506	✓	✓	✓	✓	✓	✓	✓
Cisco MDS 9509	✓	✓	✓	✓	✓	✓	✓
Cisco MDS 9216	✓	✓	✓	✓	✓	✓	✓
Cisco MDS 9120	✓	✓	✓	✓	✓	✓	✓
Cisco MDS 9140	✓	✓	✓	✓	✓	✓	✓
MSA SAN Switch 2/8	✓	✓	✓	✓	✓	✓	✓
FC-AL Switch							✓

NOTES:

- 1) Refer to [Heterogeneous Open SAN Design Reference Guide](#) for switch configuration rules and guidelines located at:
<http://h18000.www1.hp.com/products/storageworks/san/documentation.html> or consult with your hp solutions provider for assistance

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 <<Previous Infrastructure |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

DAF and SAN Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Channel Interface Controller											
Interface Manager	✓			✓			✓		✓	✓	✓
E2400-160 FC Interface Controller	✓			✓	✓		✓	✓	✓	✓	✓
NSR E1200-160	✓			✓	✓	✓	✓	✓	✓	✓	✓
NSR E2400	✓			✓	✓	✓	✓	✓	✓	✓	✓
NSR E1200	✓			✓	✓	✓	✓	✓	✓	✓	✓
NSR M2402	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
NSR N1200	✓			✓	✓	✓	✓	✓	✓	✓	✓
MDR ^{1,2}	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Serverless Backup (SAN Support Only)											
NSR E2400				✓ ³	✓ ³					✓ ⁴	✓ ⁵
NSR E1200				✓ ³	✓ ³					✓ ⁴	✓ ⁵
NSR M2402				✓ ³	✓ ³					✓ ⁴	✓ ⁵
NSR N1200				✓ ³	✓ ³					✓ ⁴	✓ ⁵

NOTES:

- 1) MDR does not support Ultrium 230, Ultrium 460, and SDLT 2 libraries
- 2) MDR does not support Direct Attach Fibre (DAF) configurations
- 3) Windows 2000 Serverless option with HSG only
- 4) Windows 2000 ServerFree opt with HSG, HSV, MSA1000 only
- 5) Solaris 8 VERITAS NetBackup 4.5 nbu_snap w/ HSG only (master router configuration not supported)

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

DAS, DAF, and SAN Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Servers											
HP Integrity Superdome (IA-64)	✓						✓				
HP SuperDome (pa-risc)	✓						✓				✓
HP rp series (pa-risc)	✓				✓		✓	✓	✓		✓
HP Integrity rx-series (IA-64)	✓ ²						✓	✓	✓		
HP A, L, N, and V Class (pa-risc)	✓	✓	✓		✓	✓	✓	✓	✓		✓
HP K, R, and D Class (pa-risc) ¹	✓										
HP ProLiant	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
HP ProLiant Blade Server	✓			✓		✓	✓	✓	✓	✓	✓
HP NetServer	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
HP AlphaServer	✓	✓	✓		✓	✓	✓	✓			✓
IBM RS/6000	✓		✓			✓	✓	✓	✓		✓
Sun UltraSPARC	✓	✓	✓		✓	✓	✓	✓	✓		✓
Sun Sun Fire	✓				✓	✓	✓	✓	✓		✓
Third Party X86	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Workstations											
HP xz series (IA) ²	✓										
HP B-Class B2000 (pa-risc)	✓										✓
HP C-Class C3600, C3700 (pa-risc)	✓										✓
HP J-Class J6700, J6750 (pa-risc)	✓										✓
NAS											
NAS 9000s	✓										
NAS 4000s	✓										
NAS 8000	✓							✓			
NAS e7000	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
NAS B3000	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
NAS B2000	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓

NOTES:

1) Ultrium 230 support only

2) Data Protector 5.0 support in 32-bit emulation mode

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[Next>>](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

SAN and DAF Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Host Bus Adapters¹											
HP-UX (IA-64)											
A6795A (2G)	✓ ²						✓				
A6826A (2G)	✓						✓ ²				✓
HP-UX (PA-RISC)											
A6826A (2G)	✓ ²						✓ ²		✓		✓
A6795A (2G)	✓				✓	✓	✓	✓	✓		✓
A6685A (1G)	✓						✓				✓
A5158A (1G)	✓	✓	✓		✓	✓	✓	✓	✓		✓
OpenVMS											
FCA2384 (2G - PCI-X)	✓										
Tru64											
FCA2354 (2G - PCI)	✓				✓	✓	✓	✓			✓
FCA2384 (2G - PCI-X)	✓						✓				✓
KGPSA -CA (1G - PCI)	✓	✓	✓		✓	✓	✓	✓			✓
Solaris											
FCA2257P (2G - PCI)	✓				✓	✓	✓	✓	✓		✓
FCA2257C (1G - cPCI)	✓				✓	✓	✓	✓	✓		✓
FCA2257S (1G - SBus)	✓				✓	✓	✓	✓	✓		✓
SWSA4-SC 64-bit (1G - SBus)	✓	✓	✓		✓	✓	✓	✓	✓		✓
SWSA4-PC 32-bit (1G - PCI)							✓		✓		✓
SG-XPCI2FC-QF2 (X6768A) (2G - PCI-X)											✓ ³
FCX-6562/FCX2-6562 (2G - PCI)											
JNI FCE6460 (2G - PCI)	✓				✓	✓	✓	✓	✓		✓
JNI FCC6460 (2G - cPCI)	✓				✓	✓	✓	✓	✓		✓
JNI FCE6410 (1G - PCI)	✓						✓				✓
AIX											
Cambex PC2000 (2G - PCI)											✓
IBM 6228 (2G)	✓					✓	✓	✓	✓		✓
PCI-to-FC HBA for AIX (1G) 197819-B21	✓		✓				✓		✓		✓

NOTES:

1) Refer to [Heterogeneous Open SAN Design Reference Guide](#) for configuration rules and guidelines located at:

<http://h18000.www1.hp.com/products/storageworks/san/documentation.html> or consult with your hp solutions provider for assistance

2) DAF support only

3) Solaris 9 support only

[Next Page >>](#)

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 << Previous Fibre HBAs
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

SAN and DAF Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Host Bus Adapters¹											
Windows - HP Branded											
FCA2355 (2G)	NT/2000/2003			NT/2000/2003	NT/2000/2003	NT/2000/2003	2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003
FCA2408 (2G)	2000/2003			2000/2003		2000/2003	2000/2003	2000/2003	2000/2003	2000/2003	2000/2003
ISP2312 (2G - BL20pG2 Blade Server)	2000/2003			2000/2003		2000/2003	2000/2003	2000/2003	2000/2003	2000/2003	2000/2003
FCA2101 (2G)	NT/2000/2003			NT/2000/2003	NT/2000/2003	NT/2000/2003	2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003
FCA2404 (2G)	2000/2003			2000/2003		2000/2003	2000/2003		2000/2003	2000/2003	2000/2003
FCA2404DC (2G)	2000/2003			2000/2003		2000/2003	2000/2003		2000/2003	2000/2003	2000/2003
FCA2214/2214DC (2G)	2000/2003			2000/2003		2000/2003	2000/2003	2000/2003	2000/2003	2000/2003	2000/2003
64-bit/33MHz PCI to FC (1G) KGPSA-CB	NT/2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003	2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003	NT/2000/2003
Windows - HP Branded (IA64)											
A7298A (2G)	✓						✓		✓		
AB232A (2G)	✓						✓		✓		
Windows - 3rd Party											
Emulex LP982 ⁶	✓										✓
LINUX											
FCA2214 (2G)	✓						✓	✓			✓
ISP2312 (2G - BL20pG2 Blade Server)	✓						✓	✓			✓
QLA2200 (1G)	✓						✓	✓			
LINUX (IA64)											
A6826A	✓						✓				
NetWare											
FCA2210 (2G) ³	✓			✓		✓		✓		✓	
64-bit / 66 MHz PCI to FC HBA (1G) ^{2, 4, 5}	✓		✓	✓				✓		✓	
32-bit / 33 MHz HBA (1G) ^{2, 4, 5}	✓			✓				✓		✓	

NOTES:

1) Refer to [Heterogeneous Open SAN Design Reference Guide](#) for configuration rules and guidelines located at:

<http://h18000.www1.hp.com/products/storageworks/san/documentation.html> or consult with your hp solutions provider for assistance

2) COMPAQ HBAs

3) Supports Enterprise Virtual Array and MSA1000.

4) Heterogeneous Windows and NetWare configurations require FCA-2210 HBA for access to shared tape. If the configuration includes NetWare 6, HSG80-based disk storage (MA8000, EMA16000) and shared tape, servers must be configured with Compaq HBA's for disk storage and FCA-2210 HBA's for tape storage (separate switch zones for disk and tape).

5) Not supported with CA ARCserve 9.0 for NetWare

6) Supported for tape connectivity only. Support is limited to full-port driver 2.21a0 and firmware 1.01a2

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs Next>>](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

HP Branded SCSI Host Bus Adapters

Windows	HP-UX	LINUX	Tru64	NetWare
268351-B21 Ultra320, LVD, Dual Channel	A6829A Ultra160, LVD, Dual Channel	268351-B21 Ultra320, LVD, Dual Channel	3X-KZPCA-AA Ultra80, LVD, Dual Channel	268351-B21 Ultra320, LVD, Dual Channel
129803-B21 Ultra160, LVD, Dual Channel	A6828A Ultra160, LVD, Single Channel	129803-B21 Ultra160, LVD, Dual Channel		129803-B21 Ultra160, LVD, Dual Channel
348757-B21 Ultra80, LVD, Dual Channel	A5149A Ultra80, LVD, Single Channel	348757-B21 Ultra80, LVD, Dual Channel		348757-B21 Ultra80, LVD, Dual Channel
154457-B21 Ultra160, LVD, Single Channel	A5150A Ultra80, LVD, Dual Channel	154457-B21 Ultra160, LVD, Single Channel		154457-B21 Ultra160, LVD, Single Channel
C7474A Ultra160, LVD, Single Channel	A4974A ¹ Ultra, Single Channel, SE	C7474A Ultra160, LVD, Single Channel		284688-B21 Ultra160, LVD, Dual Channel
A7059A ² Ultra160, LVD, Single Channel	A4999A ¹ Ultra80, LVD, Single Channel	A7059A ² Ultra160, LVD, Single Channel		C7474A Ultra160, LVD, Single Channel
A7060A ² Ultra160, LVD, Dual Channel	A5838A Ultra80, Dual Channel	A7060A ² Ultra160, LVD, Dual Channel		
	A2679A Ultra80, LVD, Single Channel, SE			

NOTES:

- 1) Supported on HP-UX Workstations only
- 2) Windows IA-64 support only

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[**<< Previous SCSI HBAs**](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

Third Party SCSI HBA and Integrated SCSI Controllers

Windows	Linux	NetWare	Solaris
Adaptec 29320 Ultra320, LVD, Single Channel	Adaptec 29320 Ultra320, LVD, Single Channel	Adaptec 29320 Ultra320, LVD, Single Channel	StorEdge 6603A LVD, Dual Channel
Adaptec 29160 Ultra160, LVD, Single Channel	Adaptec 29160 Ultra160, LVD, Single Channel	Adaptec 29160 Ultra160, LVD, Single Channel	StorEdge 6602A LVD, Single Channel
Adaptec 39160 Ultra160, LVD, Dual Channel	Adaptec 39160 Ultra160, LVD, Dual Channel	Adaptec 39160 Ultra160, LVD, Dual Channel	
Symbios/LSI 22915 Ultra160, LVD, Dual Channel			
Symbios/LSI 22903 Ultra160, LVD, Dual Channel			
Symbios/LSI 8951 Ultra80, LVD, Single Channel			
Integrated Smart Array 5i/5i Plus Ultra160, LVD, Single Channel			
Integrated SCSI Ultra160, LVD, Single and Dual Channel			

[**<< HP Branded SCSI HBAs**](#)

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

SAN Support	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Disk Array Multipath¹											
AutoPath for HP-UX ¹	✓						✓				✓
Secure Path for HP-UX ¹	EVA Only				✓	EVA Only	EVA Only	✓	✓		EVA Only
Secure Path for WIN NT ¹	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Secure Path for WIN 2000 ¹	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
AutoPath for Windows 2000 ¹	✓			✓			✓		✓	✓	✓
AutoPath for Windows 2003 ¹				✓			✓			✓	
Tru64 Multipath ²					✓	✓	✓	✓			✓
Secure Path for NetWare ¹				✓ ³				✓		✓ ³	
Secure Path for Solaris ¹	✓				✓	✓	✓	✓	✓		✓
Secure Path for AIX ¹						✓	✓	✓	✓		✓
IBM DPO									✓		

NOTES:

1) Refer to [Heterogeneous Open SAN Design Reference Guide](#) for configuration rules and guidelines located at:

<http://h18000.www1.hp.com/products/storageworks/san/documentation.html> or consult with your hp solutions provider for assistance

2) Multipath to tape supported

3) MSA1000 requires a minimum version of 3.0c with FCA-2210, HSG80's require 3.0b with COMPAQ HBAs

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 [Firmware & Drivers Next>>](#) |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Enterprise Libraries												
ESL 9595 (Ultirum 460)												
Robot FW	3.48	3.48			3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW Ultrium 460	F43W	F43W			F43W	F3CW	F3CW	F43W	F43W	F43W	F43W	F43W
ESL 9595 (Ultirum 230)												
Robot FW	3.48	3.48			3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW Ultrium 230	E38W	E38W			E38W	E33W	E33W	E38W	E38W	E38W	E38W	E38W
ESL 9595 S2												
Robot FW	3.48	3.48			3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW SDLT 160/320	v75	v75			v75	v52	v52	v75	v75	v75	v75	v75
ESL 9595 SL												
Robot FW	3.48	3.48	3.20p5	3.20p5	3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW SDLT 110/220	v75	v75	V35	V35	v75	v51	v51	v75	v75	v75	v75	v75
ESL 9326 SL												
Robot FW	3.48	3.48	3.20p5	3.20p5	3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW SDLT 110/220	v75	v75	V35	V35	v75	v51	v51	v75	v75	v75	v75	v75
ESL 9326 DX												
Robot FW	3.48	3.48	3.20p5	3.20p5	3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW 40/80	v86	v86	V80	V80	v86	V80	V80	v86	v80	v86	v86	v86
ESL 9322 (Ultirum 460)												
Robot FW	3.48	3.48			3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW Ultrium 460	F43W	F43W			F43W	F3CW	F3CW	F43W	F43W	F43W	F43W	F43W
ESL 9322 (Ultirum 230)												
Robot FW	3.48	3.48			3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW Ultrium 230	E38W	E38W			E38W	E33W	E33W	E38W	E38W	E38W	E38W	E38W
ESL 9322 S2												
Robot FW	3.48	3.48			3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW SDLT 160/320	v75	v75			v75	v52	v52	v75	v75	v75	v75	v75
ESL 9198 SL												
Robot FW	3.48	3.48	3.20p5	3.20p5	3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW SDLT 110/220	v75	v75	V35	V35	v75	v51	v51	v75	v75	v75	v75	v75
ESL 9198 DLX												
Robot FW	3.48	3.48	3.20p5	3.20p5	3.48	3.40	3.40	3.48	3.48	3.48	3.48	3.48
Drive FW 40/80	v86	v86	V80	V80	v86	v80	V80	v86	v80	v86	v86	v86

Next Page >>

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 <<Previous Firmware & Drivers Next>> |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Mid-Range Libraries												
MSL 6060 (Ultirum 460)					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21										
Drive FW Ultrium 460	F43W	F43W			F43W	F3CW	F3CW	F43W	F43W	F43W	F43W	F43W
MSL 5060 L1					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21										
Drive FW Ultrium 230	E38W	E38W			E38W	E33W	E33W	E38W	E38W	E38W	E38W	E38W
MSL 5052 S2					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21										
Drive FW SDLT 160/320	v75	v75			v75	v52	v52	v75	v75	v75	v75	v75
MSL 5052 SL					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21	3.11	3.11	4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Drive FW SDLT 110/220	v75	v75	V35	V35	v75	v51	v51	v75	v75	v75	v75	v75
MSL 6030 (Ultirum 460)					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21										
Drive FW Ultrium 460	F43W	F43W			F43W	F3CW	F3CW	F43W	F43W	F43W	F43W	F43W
MSL 5030 L1					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21										
Drive FW Ultrium 230	E38W	E38W			E38W	E33W	E33W	E38W	E38W	E38W	E38W	E38W
MSL 5026 S2					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21										
Drive FW SDLT 160/320	v75	v75			v75	v52	v52	v75	v75	v75	v75	v75
MSL 5026 SL					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21	3.11	3.11	4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
SDLT 110/220 FW	v75	v75	V35	V35	v75	v51	v51	v75	v75	v75	v75	v75
MSL 5026 DLX					4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Robot FW	4.21	4.21	3.11	3.11	4.21	4.14	4.14	4.21	4.14	4.21	4.21	4.21
Drive FW 40/80	v86	v86	V80	V80	v86	v80	v80	v86	v80	v86	v86	v86
SSL 2020 TL					4.16	4.16	4.16	4.16	4.16	4.16	4.16	4.16
Robot FW	4.16	4.16	4.15	4.15	4.16							
Drive FW AIT50	1.35	1.35	1.30	1.30	1.35			1.30	1.35	1.27	1.35	1.35

<< Previous Page

Next Page >>

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 <<Previous Firmware & Drivers Next>> |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Synsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Autoloaders												
SSL1016 Ultrium 460					v10	v10		v10	v10	v10	v10	v10
Robot FW	v10	v10										
Drive FW Ultrium 460	F43W	F43W			F43W	F43W		F43W	F43W	F43W	F43W	F43W
1/8 Ultrium 460												
Robot FW	N12r	N12r			N12r			N12r			N12r	N12r
Drive FW Ultrium 460	F78V	F78V			F78V			F78V			F78V	F78V
1/8 Ultrium 230												
Robot FW	H33R	H33R			H33R	H33R	H33R	H33R	H33R	H33R	H33R	H33R
Drive FW Ultrium 230	E00P	E00P			E00P	E00P	E00P	E00P	E00P	E00P	E00P	E00P
1/8 DLT vs80											0110	
Robot FW	0110	0110	0110	0110	0110	0110	0110	0110	0110			
Drive FW vs80	v56	v56	v56	v56	v56	v56	v56	v56	v56		v56	
SSL1016 SDLT160/320												
Robot FW	v31	v31			v31	v31	v31	v31	v31		v31	v31
Drive FW SDLT 160/320	v75	v75			v75	v52	v52	v75	v75		v75	v75
SSL1016 DLT1												
Robot FW	v31	v31	v31	v31	v31	v13	v13	v31	v31	v31	v31	v31
Drive FW DLT 1	v53	v53	v53	v53	v53	v46	v46	v53	v53	v53	v53	v53
Fibre Channel Interface Controllers												
Interface Manager	i100	i100			i100			i100		i100	i100	i100
NSR M2402	5.3.0b	5.3.0b	4.02	4.02	5.3.0b	5.3.0b	5.01.04	5.3.0b	5.3.0b	5.3.0b	5.3.0b	5.3.0b
NSR N1200	5.3.0b	5.3.0b			5.3.0b	5.3.0b	5.01.04	5.3.0b	5.3.0b	5.3.0b	5.3.0b	5.3.0b
NSR E2400	5.3.0b	5.3.0b			5.3.0b	5.3.0b	5.01.04	5.3.0b	5.3.0b	5.3.0b	5.3.0b	5.3.0b
NSR E2400-160	5.3.0b	5.3.0b			5.3.0b	5.3.0b		5.3.0b	5.3.0b	5.3.0b	5.3.0b	5.3.0b
NSR E1200-160	5.3.0b	5.3.0b			5.3.0b	5.3.0b	5.01.04	5.3.0b	5.3.0b	5.3.0b	5.3.0b	5.3.0b
NSR E1200	5.3.0b	5.3.0b			5.3.0b	5.3.0b	5.01.04	5.3.0b	5.3.0b	5.3.0b	5.3.0b	5.3.0b
MDR	v1187	v1187	v1186	v1186	v1187	v1187	v1187	v1187	v1187	V1187	v1187	v1187
Tools and Utilities												
Smart Start	6.40	6.40	5.30	5.30	6.40	6.40	6.40	6.40	6.40	6.40	6.40	6.40
Insight Manager	6.40	6.40			6.40	6.40	6.40	6.40	6.40	6.40	6.40	6.40
Disk Array Multipath Support												
AutoPath for HP-UX	2.01.02	2.01.02						2.01.02				2.01.02
Secure Path for HP-UX	3.0C	3.0C				3.0B	3.0A, SP1	3.0C	3.0B	3.0C		3.0C
Secure Path for WIN NT	4.0C	4.0C	v3.1A sp2	v3.1A sp2	4.0C	4.0B	4.0B	4.0C	4.0B	4.0C	4.0C	4.0C
Secure Path for WIN 2000	4.0C	4.0C	v3.1A sp2	v3.1A sp2	4.0C	4.0B	4.0B	4.0C	4.0B	4.0C	4.0C	4.0C
AutoPath for Windows 2000	2.01	2.01			2.01			2.01		2.01	2.01	2.01
AutoPath for Windows 2003	1.00				1.00			1.00			1.00	
Secure Path for LINUX	3.0A	3.0A										
Tru64 Multipath	Native					Native	Native	Native	Native			Native
Secure Path for NetWare	3.0C SP1				3.0C SP1				3.0C SP1		3.0C SP1	
Secure Path for Solaris	3.0C	3.0C				3.0B SP1	3.0A	3.0C	3.0B SP1	3.0C		3.0C
Secure Path for AIX	2.0D sp1					2.0D sp1	2.0B	2.0D sp1	2.0D sp1		2.0D sp1	2.0D sp1

<< Previous Page

Next Page >>

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 <<Previous Firmware & Drivers Next>> |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BalBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncof Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Interconnects												
Director Switch 2/140	05.01.00-24, HAFM 07.01.00 9											
Director Switch 2/64	05.01.00-24, HAFM 07.01.00 9											
Edge Switch 2/32	05.01.00-24, HAFM 07.01.00 9											
Edge Switch 2/24	05.01.00-24, HAFM 07.01.00 9											
Edge Switch 2/16	05.01.00-24, HAFM 07.01.00 9											
Core Switch 2/64	4.1.2b											
SAN Switch 2/32	4.1.2b											
SAN Switch 2/16	3.1.1c											
SAN Switch 2/8	3.1.1c											
SAN Switch 2/16-EL	3.1.1c											
SAN Switch 2/8-EL	3.1.1c											
SAN Switch 16	2.6.1c											
SAN Switch 8	2.6.1c											
SAN Switch 16EL	2.6.1c											
SAN Switch 8EL	2.6.1c											
FC Switch 16B	3.1.1c											
FC Switch 8B	3.1.1c											
Cisco MDS 9506	1.2.1a											
Cisco MDS 9509	1.2.1a											
Cisco MDS 9216	1.2.1a											
Cisco MDS 9120	1.2.1a											
Cisco MDS 9140	1.2.1a											
MSA SAN Switch 2/8	3.1.1c											
FC-AL Switch												
FC Loop Switch FW	1.20-g13	1.20-g13	1.20-g13	1.20-g13	1.20-g13		1.20-g13		1.20-g13		1.20-g13	
FC Loop Switch ROM	V1.2-b2	V1.2-b2	V1.2-b2	V1.2-b2	V1.2-b2		V1.2-b2		V1.2-b2		V1.2-b2	
HP OpenView Storage Software												
OpenView												
Storage Virtual Replicator	3.0b sp1				3.0b sp1			3.0b sp1		3.0b sp1	3.0b sp1	3.0b sp1
OV-SAM	3.1	3.1			3.1	3.0.2	3.0.2	3.1		3.1	3.1	3.1

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 <<Previous Firmware & Drivers Next>> |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Host Bus Adapters												
Windows - HP Branded												
FCA2355 (2G)												
FW	3.91a1	3.91a1			3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1
WIN NT 4.0 Driver	4-4.82a16	4-4.82a16			4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16
WIN 2000 Driver	5-4.82a16	5-4.82a16			5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
WIN 2003 Driver	5-4.82a16	5-4.82a16			5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
FCA2408 (2G)												
FW	1.01a2	1.01a2			1.01a2		1.01a2	1.01a2	1.01a2	1.01a2	1.01a2	1.01a2
WIN 2000 Driver	5-4.82a16	5-4.82a16			5-4.82a16		5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
WIN 2003 Driver	5-4.82a16	5-4.82a16			5-4.82a16		5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
ISP2312 (2G - BL20pG2 Blade Server)												
FW	1.34	1.34			1.34		1.33	1.34	1.33	1.34	1.34	1.34
WIN 2000 Driver	8.2.0.73	8.2.0.73			8.2.0.73		8.2.0.72	8.2.0.73	8.2.0.72	8.2.0.73	8.2.0.73	8.2.0.73
WIN 2003 Driver	8.2.0.73	8.2.0.73			8.2.0.73		8.2.0.72	8.2.0.73	8.2.0.72	8.2.0.73	8.2.0.73	8.2.0.73
FCA2101 (2G)												
FW	3.91a1	3.91a1			3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1
WIN NT 4.0 Driver	4-4.82a16	4-4.82a16			4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16
WIN 2000 Driver	5-4.82a16	5-4.82a16			5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
WIN 2003 Driver	5-4.82a16	5-4.82a16			5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
FCA2404 (2G)												
FW	1.01a2	1.01a2			1.01a2		1.01a2	1.01a2		1.01a2	1.01a2	1.01a2
WIN 2000 Driver	5-4.82a16	5-4.82a16			5-4.82a16		5-4.82a16	5-4.82a16		5-4.82a16	5-4.82a16	5-4.82a16
WIN 2003 Driver	5-4.82a16	5-4.82a16			5-4.82a16		5-4.82a16	5-4.82a16		5-4.82a16	5-4.82a16	5-4.82a16
FCA2404DC (2G)												
FW	1.01a2	1.01a2			1.01a2		1.01a2	1.01a2		1.01a2	1.01a2	1.01a2
WIN 2000 Driver	5-4.82a16	5-4.82a16			5-4.82a16		5-4.82a16	5-4.82a16		5-4.82a16	5-4.82a16	5-4.82a16
WIN 2003 Driver	5-4.82a16	5-4.82a16			5-4.82a16		5-4.82a16	5-4.82a16		5-4.82a16	5-4.82a16	5-4.82a16
FCA2214/2214DC (2G)												
FW	1.34	1.34			1.34		1.33	1.34	1.33	1.34	1.34	1.34
WIN 2000 Driver	8.2.0.73	8.2.0.73			8.2.0.73		8.2.0.72	8.2.0.73	8.2.0.72	8.2.0.73	8.2.0.73	8.2.0.73
WIN 2003 Driver	8.2.0.73	8.2.0.73			8.2.0.73		8.2.0.72	8.2.0.73	8.2.0.72	8.2.0.73	8.2.0.73	8.2.0.73
64-bit/33MHz PCI to FC (1G) KGPSA-CB												
FW	3.91a1	3.91a1	3.82a1	3.82a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1	3.91a1
WIN NT 4.0 Driver	4-4.82a16	4-4.82a16			4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16	4-4.82a16
WIN 2000 Driver	5-4.82a16	5-4.82a16	5-4.52a9	5-4.52a9	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16
WIN 2003 Driver	5-4.82a16	5-4.82a16			5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16	5-4.82a16

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 <<Previous Firmware & Drivers Next>> |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCserve	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Host Bus Adapters												
Windows - HP Branded (IA64)												
A7298A (2G)												
FW	1.01a2	1.01a2						1.01a2		1.01a2		
WIN 2003 Driver	6.50.0a11	6.50.0a11						6.50.0a11		6.50.0a11		
AB232A (2G)												
FW	1.01a2	1.01a2						1.01a2		1.01a2		
WIN 2003 Driver	6.50.0a11	6.50.0a11						6.50.0a11		6.50.0a11		
Windows - 3rd Party												
Emulex LP982												
FW	1.01a2	1.01a2										1.01a2
WIN 2000 Driver	2.21a0	2.21a0										2.21a0
WIN 2003 Driver	2.21a0	2.21a0										2.21a0
LINUX												
FCA2214 (2G)												
FW	1.34	1.34						1.34	1.29			1.34
Linux Driver (Intel)	6.04.00	6.04.00						6.04.00	6.04.00			6.04.00
ISP2312 (2G - BL20pG2 Blade Server)												
FW	1.34	1.34						1.34	1.29			1.34
Linux Driver (Intel)	6.04.00	6.04.00						6.04.00	6.04.00			6.04.00
QLA2200 (1G)												
FW	1.76	1.76						1.76	1.76			
Linux Driver (Intel)	6.0.1c	6.0.1c						6.0.1c	6.0.1			
LINUX (IA64)												
A6826A (2G)												
FW												
RedHat Advanced Server 2.1 Driver	6.06.50-14	6.06.50-14						6.06.50-14				
United Linux Driver	6.06.50-9	6.06.50-9										
NetWare												
FCA2210 (2G)												
FW	1.34	1.34			1.34		1.28		1.34		1.34	
NetWare Driver	6.50y	6.50y			6.50y		6.50s		6.50y		6.50y	
64 Bit / 66 MHz PCI to FC HBA (1G)												
NetWare Driver	2.52	2.52		2.52	2.52				2.52		2.52	
32-bit / 33 MHz HBA (1G)												
NetWare Driver	2.52	2.52			2.52				2.52		2.52	

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) |
 [AutoLoaders](#) |
 [Operating Systems](#) |
 [RAID Arrays](#) |
 [Infrastructure](#) |
 [Servers](#) |
 [Fibre HBAs](#)
[SCSI HBAs](#) |
 [Software](#) |
 [Disk Array Multipath](#) |
 <<Previous Firmware & Drivers Next>> |
 [Backup App Details](#) |
 [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncoart Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Host Bus Adapters												
HP-UX (IA-64)												
A6795A (2G)												
FW	1.10	1.10						1.10				
td Driver	Native	Native						Native				
A6826A (2G)												
FW	3.02.165	3.02.165									3.02.165	
fcd Driver	Native	Native									Native	
HP-UX (PA-RISC)												
A6826A (2G)												
fcd Driver	Native								Native		Native	
HP-UX 11.11 Driver	11.11.02								11.11.02		11.11.02	
FW	3.02.165								3.02.165		3.02.165	
A6795A (2G)												
HP-UX Driver	11.11.09 11.0.10	11.11.09 11.0.10				11.11.09 11.0.10	11.11.09 11.0.10	11.11.09 11.0.10	11.11.09 11.0.10	11.11.09 11.0.10		11.11.09 11.0.10
A6685A (1G)												
HP-UX Driver	11.11.09	11.11.09						11.11.09 11.0.10				11.11.09 11.0.10
A5158A (1G)												
HP-UX Driver	11.11.09 11.0.10	11.11.09 11.0.10	11.00.06	11.00.06		11.11.09 11.0.10	11.11.09 11.0.10	11.11.09 11.0.10	11.11.09 11.0.10	11.11.09 11.0.10		11.11.09 11.0.10
Tru64												
FCA2354												
FW	3.91a1	3.91a1				3.91a1	3.81a4	3.91a1	3.91a1			3.91a1
Tru64 Driver	2.06	2.06				2.06	1.32a	2.06	2.06			2.06
FCA2384 (2G - PCI-X)												
FW	1.00x6 w/LFU	1.00x6 w/LFU						1.00x6 w/LFU				1.00x6 w/LFU
Tru64 Driver												
KGPSA -CA												
FW	3.91a1	3.91a1	3.81a4	3.81a4		3.91a1	3.81a4	3.91a1	3.91a1			3.91a1
Tru64 Driver	2.06	2.06	1.32a	1.32a		2.06	1.32a	2.06	2.06			2.06
OpenVMS												
FCA2384 (2G - PCI-X)												
FW	3.91a1	3.91a1										
Driver	Native	Native										

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | <<Previous Firmware & Drivers | [Backup App Details](#) | [Legacy Support](#)

January 2004

Components & Firmware	Current Release	HP Data Protector	Atempo Time Navigator	BakBone NetVault	CA BrightStor ARCServe	CA BrightStor EB	CommVault Galaxy	Legato NetWorker	Syncsort Backup Express	Tivoli Storage Manager	VERITAS Backup Exec	VERITAS NetBackup
Fibre Host Bus Adapters												
AIX												
Cambex PC2000 (2G - PCI)												
AIX Driver w/o Secure Path	1.5.22.0											1.5.22.0
AIX Driver w/ Secure Path	1.5.24.1											1.5.24.1
IBM 6228 (2Gb)												
AIX 4.3.3 Driver	Maintenance Pack 10	Maintenance Pack 10					Maintenance Pack 10	Maintenance Pack 10		Maintenance Pack 10		Maintenance Pack 10
AIX 5.1L Driver	Native						Native	Native	Native	Native		Native
AIX 5.2 Driver	Native								Native			Native
PCI-to-FC HBA (PC1000) for AIX (1G) 197819-B21												
AIX Driver w/o Secure Path	1.5.22.0	1.5.19		1.5.11.1			1.5.22.0	1.5.22.0	1.5.22.0	1.5.22.0		1.5.22.0
AIX Driver w/ Secure Path	1.5.24.1						1.5.24.1	1.5.24.1	1.5.24.1	1.5.24.1		1.5.24.1
Solaris												
FCA2257P (2G - PCI)												
fw	3.1.2	3.1.2				3.1.2	3.1.2	3.1.2	3.1.2	3.1.2		3.1.2
Solaris Driver	4.11	4.11				3.26	3.26	4.11	3.26	4.11		4.11
FCA2257C (1G - PCI)												
fw	3.1.2	3.1.2				3.1.2	3.1.2	3.1.2	3.1.2	3.1.2		3.1.2
Solaris Driver	4.11	4.11				3.26	3.26	4.11	3.26	4.11		4.11
FCA2257S (1G - Sbus)												
fw	3.1.2	3.1.2				3.1.2	3.1.2	3.1.2	3.1.2	3.1.2		3.1.2
Solaris Driver	4.11	4.11				3.26	3.26	4.11	3.26	4.11		4.11
SWSA4-SC 64-bit Sbus												
Fcode	13.3.7	13.3.7	13.3.7	13.3.7		13.3.7	13.3.7	13.3.7	13.3.7	13.3.7		13.3.7
Solaris Driver	2.5.9	2.5.9	2.5.9	2.5.9		2.5.9	2.5.9	2.5.9	2.5.9	2.5.9		2.5.9
SWSA4-PC 32-bit PCI												
Fcode	3.0.3							3.0.3		3.0.3		3.0.3
Solaris Driver	2.5.9							2.5.9		2.5.9		2.5.9
SG-XPCI2FC:QF2 (X6768A) (2G - PCI-X)												
Solaris Driver	Native											Native
FCX-6562/FCX2-6562 (2G - PCI)												
Fcode												
Solaris Driver												
JNI FCE6460 (2G - PCI)												
Fcode	3.9	3.9				3.9	3.8.9	3.9	3.8.9	3.9		3.9
Solaris Driver	5.3	5.3				5.3	5.2.1	5.3	5.2.1	5.3		5.3
JNI FCC6460 (2G - cPCI)												
Fcode	3.9	3.9				3.9	3.8.9	3.9	3.8.9	3.9		3.9
Solaris Driver	5.3	5.3				5.3	5.2.1	5.3	5.2.1	5.3		5.3
JNI FCE6410 (1G - PCI)												
Fcode	3.9	3.9						3.9				3.9
Solaris Driver	4.1.5	4.1.5						4.1.5				4.1.5

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

ISV DETAILS

Name	Version	Date Last Tested	Recommended Tape Driver	Application Information/Support
HP OpenView Storage Data Protector	5.1.1, 5.1, and 5.0	Current	Use Native Drivers	Data Protector Product Information Data Protector Device Support Matrix
Atempo Time Navigator	3.6	Mar-02		www.atempo.com
BakBone NetVault	6.5.1	Mar-02		www.bakbone.com
Computer Associates BrightStor ARCServe for Windows NT/2000	ARCServe v9.0 build 2030	Current	CABA Driver for Windows	support.ca.com
Computer Associates BrightStor ARCServe for NetWare	9.0	Current	HP Driver for Netware	support.ca.com
Computer Associates BrightStor Enterprise Backup	BEB v10.5	Oct-03		support.ca.com/
CommVault Galaxy	4.2 sp2	Jul-03	HP Driver for Windows	www.commvault.com
Legato NetWorker	7.1, 7.0, 6.1.4, and 6.1.3	Current	HP Driver for Windows	www.legato.com
Syncsort Backup Express	2.1.5D	Oct-03	Use Native Drivers	www.syncsort.com
Tivoli Storage Manager	5.2.1.x	Current	Tivoli Driver for Windows	www.tivoli.com
VERITAS Backup Exec for Windows Servers	9.1.4691.42	Current	BE Driver for Windows	www.veritas.com
VERITAS Backup Exec for NetWare	9.1.306.11	Current	BE Driver for Netware	www.veritas.com
VERITAS NetBackup Windows	5.0 and 4.5 FP5/MP5	Current	HP Driver for Windows	www.veritas.com
VERITAS NetBackup UNIX	5.0 and 4.5 FP5/MP5	Current		www.veritas.com

NOTE: All ISV certifications have been completed with a minimum configuration of 16 servers by 16 drives.

This does not imply any limitations of the backup and restore application or HP StorageWorks SAN products.

Refer to the application vendor's website or representative for maximum configuration details.

STORAGE HARDWARE / SOFTWARE COMPATIBILITY MATRIX

[Libraries](#) | [AutoLoaders](#) | [Operating Systems](#) | [RAID Arrays](#) | [Infrastructure](#) | [Servers](#) | [Fibre HBAs](#)
[SCSI HBAs](#) | [Software](#) | [Disk Array Multipath](#) | [Firmware & Drivers](#) | [Backup App Details](#) | [Legacy Support](#)

January 2004

LEGACY PRODUCT SUPPORT DETAILS

Device Name	Last EBS Compatibility Matrix Where Device Was Listed ¹
TL895	December 2002
TL891DLX	December 2002
ESL9326D	April 2002
TL891D	April 2002
DLT 35/70	April 2002

1) Consult your HP Account Representative to obtain legacy EBS Compatibility Matrices