

HP StorageWorks Enterprise Backup Solution (EBS) Hardware/Software Compatibility Matrix

September 2007 Version 1.0

Start Here

Key Updates:

- LTO Ultrium 1840 FC support for ESL & EML E-series tape libraries
- New TAC partner for NetApp Filers with Data ONTAP v7.2.x
- New TAC partner FalconStor VTL
- Support for new VLS12000 Gateway Virtual Library System
- Added Tape Libraries Advisories
- Interoperability updates throughout



Enterprise Backup Solution Compatibility Matrix Index

(Click on topic to jump to that page)

The () icon indicates a hotlink. See [Sample Page Layout](#).

| Topic | Page |
|--|-------------|
| How To Use This Document | 3 |
| Sample Page Layout | 4 |
| Libraries/Autoloaders and Partner Products | 5 |
| Backup Application Details | 6 |
| Advanced Library Features | 7 |
| Libraries and Interface Controllers | 8 |
| Interface Controllers | 9 |
| HP-UX (PA-RISC) | 10 |
| HP-UX (Integrity) | 11 |
| Windows (x86) | 12 |
| Windows (Integrity) | 15 |
| Windows (x64) | 16 |
| Linux (x86) | 17 |
| Linux (Integrity) | 19 |
| Linux (x64) | 20 |
| Solaris | 21 |
| Tru64/OVMS | 23 |
| AIX | 24 |
| NetWare | 25 |
| RAID Arrays | 26 |
| Infrastructure | 27 |
| ProLiant Storage Servers (NAS) | 28 |
| ProLiant Data Protection Storage Servers | 28 |
| SCSI HBAs | 29 |
| Storage Software | 32 |
| Legacy Device Support | 33 |
| Useful Links | 34 |
| Advisories | 35 |

How To Use This Document

The **HP StorageWorks Enterprise Backup Solution (EBS) Compatibility Matrix** provides information for designing data protection solutions, including backup/restore and archiving, that scale from entry-level workgroups to enterprise-level datacenters. It includes support for Direct Attach SCSI (DAS), Direct Attach Fibre (DAF), and Storage Area Network (SAN). It does not imply product availability. Products **highlighted in yellow** will be removed from the EBS Compatibility Matrix in the next release. Previous versions of the EBS Compatibility Matrix are available on the web at www.hp.com/go/ebs.

HP partners with leading application and product vendors to provide backup/restore, archiving, and data security solutions. See below for information on the Extended Solution Interoperability (ESI) and Tape Automation Compatibility (TAC) categories:

Extended Solution Interoperability: HP performs on-going interoperability and extensive solution testing with these applications to provide fully certified and supported data protection solutions that include HP tape libraries, autoloaders, and virtual library systems. See the [Libraries and Partner Products](#) page for compatibility information. Extensive solution details including operating system details, host bus adapter and driver information, SAN infrastructure, and extended tape library feature support can be found throughout this document.

Tape Automation Compatibility: These products are verified for compatibility with HP tape libraries, autoloaders, and virtual library systems. See the [Libraries and Partner Products](#) page for compatibility information. Consult the product compatibility guide(s) for additional support details such as product version information, driver details, firmware revisions, patch levels, etc.

Additional technical information can be found in the Enterprise Backup Solution Design Guide and various Backup Application Implementation Guides located on the web at www.hp.com/go/ebs. For information on stand-alone tape products and compatibility, go to www.hp.com/go/connect.

Sample Page Layout

Index menu system, click to navigate to other pages

Yellow Box indicates current page selection

HP StorageWorks EBS Compatibility Matrix

Index Libraries/Autoloaders & Partner Products Backup App. Advanced Library Features Interface Controllers **HP-UX** Windows Linux
Solaris Tru64/OVMS AIX NetWare RAID Arrays Infrastructure NAS SCSI HBAs Storage Software Legacy Links Advisories

HP-UX (Integrity) ⁵

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|---|---|--|--|----------------------|--|
| Operating Systems ^{1, 2} | | | | | | |
| HP-UX 11.23 (11i v2) | HWE 11.23 March 2006 Quality Pack March 2006 | HWE 11.23 May 2005 Quality Pack May 2005 | HWE 11i v2 Sept 2006 Quality Pack Sept 2006 | HWE 11.23 June 2006 Quality Pack May 2005 | | HWE 11i v2 Sept 2006 Quality Pack Sept 2006 |
| Servers | | | | | | |
| HP Integrity Superdome and Mid-Range (rx7000-rx8000 Series, Integrity) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP Integrity Entry-Level (rx1000-rx6000 Series, Integrity) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ⁴ | | | | | | |
| AB379A / AB379B (4G, PCI-X 2.0) | | | | | | |
| FW | 4.00.70 | | 4.00.70 | 4.00.70 | | 4.00.70 |
| fcd Driver | Native | | Native | Native | | Native |
| AB378A / AB378B (4G, PCI-X 2.0) | | | | | | |
| FW | 4.00.70 | | 4.00.70 | 4.00.70 | | 4.00.70 |
| fcd Driver | Native | | Native | Native | | Native |
| AB465A (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A9782 (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A9784 (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A6795A (2G, PCI) | | | | | | |
| FW | 1.10 | 1.10 | 1.10 | 1.10 | | 1.10 |
| fd Driver | Native | Native | Native | Native | | Native |
| A6826A (2G, PCI-X) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| Disk Array Multipath Support ⁴ | | | | | | |
| Secure Path for HP-UX | | | | | | |
| | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | | 3.0F SP2 patch 2 |
| High Availability ⁶ | | | | | | |
| MC/ServiceGuard | | | | | | |
| | ✓ ³ | | ✓ ³ | | | |

NOTES:

1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
 3) ATS is not supported.
 4) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
 5) For Boot from Tape support, [click here](#), and select the type of tape for compatibility.
 6) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configuration.

September 2007, v1.0

Page 11 of 35

CLICK cell to navigate to the HP product webpage

CLICK cell to navigate to the firmware/driver download page

NOTES: section contains specific configuration details

Matrix Version

Darkened section indicates environment currently not supported by application

Navigation buttons

Libraries/Autoloaders and Partner Products

| DAF, SAN, and DAS Support ¹ | | Extended Solution Interoperability ¹ | | | | | | | | | | Tape Automation Compatibility ¹ | | | | | | | | | | | | | | | | |
|---|----------------------|--|-------------|---------------|----------------------------|----------------------|----------------------------|---------------------------|--------------------|-------------------------|------------------------|--|-------------------------|--------------------------|---------------------------------|----------------|----------------|--------------------------------|-----------------|--------------------------|--------------------------------------|-------------------------|----------------------------|------------------|--------------|-------------------------|------------------------|-----------------|
| | | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup | HP Data Protector Express | HP NonStop Servers | HP File System Extender | Attempo Time Navigator | BalBone NetVault | Bridgehead HT ISM Suite | Comm Vault OnNetx Galaxy | Decru DataFort ^{15,16} | EMC Retrospect | FalconStor VTL | Front Porch Digital DV Archive | IBM TSM Express | Intradyn ComplianceVault | NeoScale CryptoStar ^{14,15} | NetApp Data Ontap 7.2.x | QStar i3SM Data Director | Quantum StorNext | SQL FlashNet | Syncsort Backup Express | XenData Archive Series | Yosemite Backup |
| Enterprise Class Libraries | Firmware | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| ESL E-Series | 6.00 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 FC | H29W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 FC | L63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 460 | F6AW | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 460 FC | K48W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SDLT 600 | v41 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| EML E-Series | 1200 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 FC | H29S | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 FC | L63S | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 460 FC | K710 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| ESL 9000 Series ⁵ | 3.60 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 | G63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 460 | F6AW | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SDLT 600 | v41 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Virtual Library Systems | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| VLS 12000/300 EVA Gateway | 2.0.0 | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| EVA 4x00/6x00/8x00 | 6.xxx | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| EVA3000/5000 ² | 4.007 | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| VLS 6000 Series | 2.0.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| VLS 1000i Series ⁸ (iSCSI) | 2.6.0.228 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| HP StorageWorks D2D Backup System | | www.hp.com/go/connect | | | | | | | | | | www.hp.com/go/connect | | | | | | | | | | | | | | | | |
| Business Class Libraries | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| MSL 6000 Series | 5.20 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 ¹⁹ | B23W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 | G63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 460 | F6AW | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SDLT 600 | v41 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSL 8096 ¹⁰ | 8.20 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 FC ¹⁰ | H29W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 SCSI ¹⁹ | B23W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 4Gb FC | M63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 SCSI | G63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 920 SAS ³ | C24W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSL 4048 ¹⁰ | 5.70 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 FC ¹⁹ | H29W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 SCSI ¹⁹ | B23W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 4Gb FC | M63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 FC | L63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 SCSI | G63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 920 SCSI | D22W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 920 SAS ³ | C24W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 448 SCSI | S63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSL 2024 ¹⁰ | 3.30 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 FC ¹⁹ | H29W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 1840 SCSI ¹⁹ | B23W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 4Gb FC | M63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 FC | L63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 960 SCSI | G63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 920 SCSI | D22W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 920 SAS ³ | C24W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Ultrium 448 SCSI | S63W | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Autoloaders ^{4,6,10} | Robot (Drive) | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1/8 G2 Tape Autoloader (Ultrium 920) | 1.30 (D22W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 G2 Tape Autoloader (Ultrium 920 SAS) ³ | 1.30 (C24W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 G2 Tape Autoloader (Ultrium 448) | 1.30 (S63W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 G2 Tape Autoloader (Ultrium 232) | 1.30 (P63W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 Tape Autoloader (Ultrium 960) | 1.50 (G63W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 Tape Autoloader (Ultrium 448) | 1.50 (S63W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 Tape Autoloader (Ultrium 232) | 1.50 (P63W) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 1/8 DLT Tape Autoloader (v480) | 5E40 (v64) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Advanced Drive and Media Features | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| Ultrium WORM | | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SDLT 600 WORM | | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

NOTES:

- 1) See "How To Use This

Backup Application Details ¹

| | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec (Windows) | Symantec Backup Exec (NetWare) | Symantec Veritas NetBackup |
|---|------------------------------------|------------------------------|-------------------------------|--|-----------------------------------|-----------------------------------|-------------------------------|
| Partner Device Compatibility Pages | Data Protector HCL | ARCserve HCL | NetWorker HCL | Tivoli Storage Manager HCL | Backup Exec HCL | Backup Exec HCL | NetBackup HCL |
| Recommended Tape Driver | Native Drivers | CABA Drivers | HP Drivers | Tivoli Drivers | BE Drivers | BE Drivers | HP or NBU Drivers |

Latest and Minimum Application Version Support

| | HP Data Protector | | CA ARCserve | | EMC NetWorker | | IBM Tivoli Storage Manager | | Symantec Backup Exec (Windows) | | Symantec Backup Exec (NetWare) | | Symantec Veritas NetBackup | |
|--|----------------------|---------|-------------|---------|---------------|---------|-------------------------------|--------------------|-----------------------------------|--------------------|-----------------------------------|------------------|-------------------------------|---------|
| Enterprise Class Libraries | Latest | Minimum | Latest | Minimum | Latest | Minimum | Latest | Minimum | Latest | Minimum | Latest | Minimum | Latest | Minimum |
| ESL E-Series | 6.0 | 5.0 | 11.5 | 9.0 | 7.3 | 6.0 | 5.4 ⁴ | 5.2 ⁴ | 11d | 9.0 | 9.2 | 9.0 | 6.5 | 4.5 |
| EML E-Series | 6.0 | 5.1 | 11.5 | 9.0 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10.0 | | | 6.5 | 5.0 |
| ESL 9000 Series | 6.0 | 5.0 | 11.5 | 9.0 | 7.3 | 6.0 | 5.4 ⁴ | 5.1 | 11d | 9.0 | 9.2 | 9.0 | 6.5 | 4.5 |
| Virtual Library Systems | | | | | | | | | | | | | | |
| VLS 12000/300 EVA Gateway | 6.0 | 5.1 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10.0 | | | 6.5 | 5.0 |
| VLS 6000 Series | 6.0 | 5.1 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10.0 | | | 6.5 | 5.0 |
| VLS 1000i Series | 6.0 | 5.5 | 11.5 | 11.5 | 7.3 | 7.0 | 5.4 ^{4,7} | 5.3 ^{4,7} | 11d ⁷ | 10d ⁷ | | | 6.5 | 5.0 |
| Business Class Libraries | | | | | | | | | | | | | | |
| MSL 6000 Series | 6.0 | 5.0 | 11.5 | 9.0 | 7.3 | 6.0 | 5.4 ⁴ | 5.2 ⁴ | 11d | 9.0 | 9.2 | 9.0 | 6.5 | 4.5 |
| MSL 8096 | 6.0 | 5.5 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10d ^{2,6} | | | 6.5 | 6.0 |
| MSL 4048 | 6.0 | 5.1 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10d ^{2,6} | | | 6.5 | 6.0 |
| MSL 2024 | 6.0 | 5.1 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10d ^{2,6} | | | 6.5 | 6.0 |
| Autoloaders | | | | | | | | | | | | | | |
| 1/8 G2 Tape Autoloader (Ultrium 920) | 6.0 | 5.5 | 11.5 | 11.5 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10d ³ | 9.2 | 9.0 | 6.5 | 6.0 |
| 1/8 G2 Tape Autoloader (Ultrium 920 SAS) | 6.0 | 5.5 | 11.5 | 11.5 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 11d ⁶ | | | 6.5 | 6.0 |
| 1/8 G2 Tape Autoloader (Ultrium 448) | 6.0 | 5.5 | 11.5 | 11.5 | 7.3 | 7.0 | 5.4 | 5.3 | 11d | 10d ³ | 9.2 ⁸ | 9.0 ⁸ | 6.5 | 6.0 |
| 1/8 G2 Tape Autoloader (Ultrium 232) | 6.0 | 5.5 | 11.5 | 11.5 | 7.3 | 7.0 | 5.4 | 5.3 | 11d | 10d ³ | 9.2 ⁸ | 9.0 ⁸ | 6.5 | 6.0 |
| 1/8 Tape Autoloader (Ultrium 960) | 6.0 | 5.1 | 11.5 | 9.0 | 7.3 | 7.0 | 5.4 ⁴ | 5.3 ⁴ | 11d | 10.0 | 9.2 | 9.0 | 6.5 | 5.0 |
| 1/8 Tape Autoloader (Ultrium 448) | 6.0 | 5.1 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 | 5.3 | 11d | 10.0 | 9.2 | 9.0 | 6.5 | 5.0 |
| 1/8 Tape Autoloader (Ultrium 232) | 6.0 | 5.1 | 11.5 | 11.1 | 7.3 | 7.0 | 5.4 | 5.3 | 11d | 10.0 | 9.2 | 9.0 | 6.5 | 5.0 |
| 1/8 DLT Tape Autoloader (vs80) | 6.0 | 5.0 | 11.5 | 9.0 | 7.3 | 6.0 | 5.4 | 5.1 | 11d | 9.0 | 9.2 | 9.0 | 6.5 | 4.5 |

NOTES:

- 1) Use the latest backup application maintenance release unless otherwise noted. Refer to the backup application vendor for specific operating system support, patches, builds, and drivers required to support HP tape automation and virtual library products.
- 2) Backup Exec version 10d and Device Driver Installer (DDI) version 20060615 or later are required to support the HP StorageWorks MSL2024 and MSL4048 Tape Automation Libraries.
- 3) Backup Exec version 10d and Device Driver Installer (DDI) version 20061015 or later are required to support the HP StorageWorks 1/8 G2 Tape Autoloaders.
- 4) TSM version 5.2.4 (or later) or 5.3.4 (or later) are required to support HP Ultrium 920 and 960 drives.
- 5) Application versions listed in the table are not necessarily the current version supported, but indicate the required minimum to support the associated HP tape automation and virtual library products.
- 6) Backup Exec 11d and Device Driver Installer (DDI) version 20061215 or later are required to support HP StorageWorks Ultrium 920 SAS drives in HP libraries.
- 7) Configurations running an HP VLS1000i virtual tape library must use the "HP VLS1000i" emulation in order to function properly.
- 8) BENW 9.x Driver SET 2 is required for Ultrium 232 and 448 1/8 G2 Autoloader support. Also, multi-LUN support must be enabled on the SCSI HBA.

Advanced Library Features

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|---|----------------|---------------|-------------------------------|-------------------------|-------------------------------|
| Enterprise Libraries | IMPORTANT: See the Backup Application Details page for the latest supported versions of backup software. | | | | | |
| ESL E-Series 2 Unit Cross Link ¹ | ✓ | ✓ ³ | ✓ | ✓ | | ✓ |
| ESL E-Series 3-5 Unit Cross Link ¹ | ✓ | | | ✓ | | ✓ |
| ESL 9000 Multi-Unit Scalability ¹ | ✓ | ✓ ³ | ✓ | ✓ | | ✓ |
| ESL Mixed Media | ✓ | ✓ ³ | ✓ | ✓ | ✓ ⁴ | ✓ |
| ESL Partitioning | ✓ | ✓ ³ | ✓ | ✓ | ✓ ⁴ | ✓ |
| EML Partitioning | ✓ | | ✓ | ✓ | ✓ ⁴ | ✓ |
| Midrange Libraries | | | | | | |
| MSL 6000 Multi-Unit Scalability ^{1,2} | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSL 6000 Mixed Media Support | ✓ | ✓ | ✓ | ✓ | ✓ ⁴ | ✓ |

NOTES:

- 1) Contact your ISV for scalability support.
- 2) MSL multi-unit scalability is with a vertical pass-through mechanism.
- 3) NetWare is supported with ESL libraries in a homogeneous environment only.
- 4) Windows support only.

Interface Controllers

| Interface Manager Firmware Required Minimum Component | i160 | i161 | i170 | i171 | i180 | i182 | i200 | i220 |
|--|--------|--------|--------|--------|--------|------------------|--------|--------|
| e2400-FC 4Gb Interface Controller (FC-FC) | N/A | 5.7.06 | 5.7.18 | 5.7.1b | 5.7.1f | 5.9.28 | 5.9.28 | 5.9.29 |
| e2400-FC 2Gb Interface Controller (FC-FC) | 5.6.78 | 5.6.7a | 5.6.87 | 5.6.87 | 5.6.8c | 5.9.28 | 5.9.28 | 5.9.29 |
| e2400-160 Interface Controller (FC-SCSI) | 5.6.78 | 5.6.7a | 5.6.87 | 5.6.87 | 5.6.8c | 5.9.28 | 5.9.28 | 5.9.29 |
| NSR E2400 | 5.6.78 | 5.6.7a | 5.6.87 | 5.6.87 | 5.6.8c | 5.9.28 | 5.9.28 | 5.9.29 |
| NSR E1200-160 | 5.6.78 | 5.6.7a | 5.6.87 | 5.6.87 | 5.6.8c | 5.9.28 | 5.9.28 | 5.9.29 |
| ESL 9595/9322 | 3.60 | 3.60 | 3.60 | 3.60 | 3.60 | 3.60 | | |
| ESL 9198/9326 | 3.60 | 3.60 | 3.60 | 3.60 | 3.60 | 3.60 | | |
| ESL E-Series 712e/630e | 4.10 | 4.10 | 4.60 | 4.60 | 4.86 | | 5.10 | 6.00 |
| ESL E-Series 322e/286e | 4.10 | 4.10 | 4.60 | 4.60 | 4.86 | | 5.10 | 6.00 |
| EML E-Series | 1022 | 1022 | 1022 | 1022 | 1070 | | 1126 | 1200 |
| JAVA Run Time | 1.4.2 | 1.4.2 | 1.4.2 | 1.4.2 | 1.4.2 | 1.4.2 | 1.4.2 | 1.4.2 |
| Command View TL | 1.6.00 | 1.6.01 | 1.7 | 1.7 | 1.8.00 | 1.8.00 or 2.0.00 | 2.0.00 | 2.2.00 |

HP-UX (PA-RISC) ⁶

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|--|--|---|---|----------------------|--|
| Operating Systems ^{1, 2} | | | | | | |
| HP-UX 11.11 (11i v1) | HWE 11.11, June 2005 Quality Pack. June 2005 | HWE 11.11, Dec 2004 Gold Pack, Dec 2004 | HWE 11.11, June 2005 Quality Pack. June 2005 | HWE 11.11, Dec 2004 Gold Pack, Dec 2004 | | HWE 11.11, Dec 2006 Quality Pack. Dec 2006 |
| HP-UX 11.23 (11i v2) | HWE 11i v2 March 2006 Quality Pack March 2006 | | HWE 11i v2 Sept 2006 Quality Pack Sept 2006 | HWE 11i v2 June 2006 Quality Pack March 2006 | | HWE 11i v2 Sept 2006 Quality Pack Sept 2006 |
| Servers | | | | | | |
| HP 9000 Superdome and Mid-Range (rp7000-rp8000 Series, PA-RISC) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP 9000 Entry-Level (rp2000-rp5000 Series, PA-RISC) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP A, L, N, and V Class (PA-RISC) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP R Class (PA-RISC) ³ | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ⁵ | | | | | | |
| AB379A / AB379B (4G, PCI-X 2.0) | | | | | | |
| FW | 4.00.70 | | 4.00.70 | 4.00.70 | | 4.00.70 |
| fcd Driver | Native | | Native | Native | | Native |
| AB378A / AB378B (4G, PCI-X 2.0) | | | | | | |
| FW | 4.00.70 | | 4.00.70 | 4.00.70 | | 4.00.70 |
| fcd Driver | Native | | Native | Native | | Native |
| AB465A (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A9782 (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A9784 (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A6826A (2G, PCI-X) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A6795A (2G, PCI) | | | | | | |
| td Driver | Native | Native | Native | Native | | Native |
| Disk Array Multipath Support ⁵ | | | | | | |
| Secure Path for HP-UX | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | | 3.0F SP2 patch 2 |
| High Availability ⁴ | | | | | | |
| MC/ServiceGuard | ✓ ³ | | ✓ ³ | | | |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) ATS is not supported.

- 4) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.
- 5) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 6) For Boot from Tape support, [click here](#), and select the type of tape for compatibility.

HP-UX (Integrity) ⁵

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|---|---|--|--|----------------------|--|
| Operating Systems ^{1, 2} | | | | | | |
| HP-UX 11.23 (11i v2) | HWE 11.23 March 2006 Quality Pack March 2006 | HWE 11.23 May 2005 Quality Pack May 2005 | HWE 11i v2 Sept 2006 Quality Pack Sept 2006 | HWE 11.23 June 2006 Quality Pack May 2005 | | HWE 11i v2 Sept 2006 Quality Pack Sept 2006 |
| Servers | | | | | | |
| HP Integrity Superdome and Mid-Range (rx7000-rx8000 Series, Integrity) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP Integrity Entry-Level (rx1000-rx6000 Series, Integrity) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ⁴ | | | | | | |
| AB379A / AB379B (4G, PCI-X 2.0) | | | | | | |
| FW | 4.00.70 | | 4.00.70 | 4.00.70 | | 4.00.70 |
| fcd Driver | Native | | Native | Native | | Native |
| AB378A / AB378B (4G, PCI-X 2.0) | | | | | | |
| FW | 4.00.70 | | 4.00.70 | 4.00.70 | | 4.00.70 |
| fcd Driver | Native | | Native | Native | | Native |
| AB465A (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A9782 (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A9784 (2G, PCI-X, Combo Card) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| A6795A (2G, PCI) | | | | | | |
| FW | 1.10 | 1.10 | 1.10 | 1.10 | | 1.10 |
| td Driver | Native | Native | Native | Native | | Native |
| A6826A (2G, PCI-X) | | | | | | |
| FW | 3.003.154 | 3.003.154 | 3.003.154 | 3.003.154 | | 3.003.154 |
| fcd Driver | Native | Native | Native | Native | | Native |
| Disk Array Multipath Support ⁴ | | | | | | |
| Secure Path for HP-UX | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | 3.0F SP2 patch 2 | | 3.0F SP2 patch 2 |
| High Availability ⁶ | | | | | | |
| MC/ServiceGuard | ✓ ³ | | ✓ ³ | | | |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) ATS is not supported.

- 4) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 5) For Boot from Tape support, [click here](#), and select the type of tape for compatibility.
- 6) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.

Windows (x86)

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| Windows Server 2003 (32-bit) | sp2 | sp2 | sp2 | sp2 | sp2 | sp2 |
| Windows Server 2003 R2 (32-bit) | sp2 | sp2 | sp2 | sp2 | sp2 | sp2 |
| Servers | | | | | | |
| HP ProLiant | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| HP ProLiant c-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| HP ProLiant p-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Third Party X86 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Fibre Host Bus Adapters ^{5, 6} | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| FC2243 / Emulex LP11002 (4G, PCI-X 2.0) FC2143 / Emulex LP1150 (4G, PCI-X 2.0) | | | | | | |
| FW | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| FC1243 (4G, PCI-X 2.0) FC1143 (4G, PCI-X 2.0) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 |
| WIN 2003 SCSIport Driver | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 |
| WIN 2003 StorPort Driver ^{3,4} | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| FC1142SR / QLogic QLE2460 (4G, PCI-e) FC1242SR DC / QLogic QLE2462 (4G, PCI-e) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 |
| WIN 2003 SCSIport Driver | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 |
| WIN 2003 StorPort Driver ^{3,4} | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| FC2142SR / Emulex LPe1150 (4G, PCI-e) FC2242SR DC / Emulex LPe11002-M4 (4G, PCI-e) | | | | | | |
| FW | 2.50a2 | 2.50a2 | 2.50a2 | 2.50a2 | 2.50a2 | 2.50a2 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| A7388A / Emulex LP1050 (2G, PCI-X) A7387A / Emulex LP1050DC (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| A7560A / Emulex LP1050EX-F2 (2G, PCI-e) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) All non-sp2 systems running applications other than Tivoli require updated Storport.sys KB891793 (minimum) or KB916048 (recommended); systems running Tivoli require Storport.sys KB901371. All sp2 systems are required to run Storport.sys KB932755.

- 4) Please reference ISV application installation/support documents for specific driver and patch requirements.
- 5) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 6) 3rd Party adapters require HP drivers and firmware.

Windows (x86) - Continued

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Fibre Host Bus Adapters^{1, 2} | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| FCA2355 / Emulex LP9002DC (2G, PCI-X) | | | | | | |
| FW | 3.93a0 | 3.93a0 | 3.93a0 | 3.93a0 | 3.93a0 | 3.93a0 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| FCA2408 / Emulex LP982 (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| QMH2462 (4G, PCI-e) for HP c-Class BladeSystem | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 |
| WIN 2003 SCSIport Driver | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 |
| WIN 2003 StorPort Driver ^{3,4} | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| LPe1105 (4G, PCI-e) for HP c-Class BladeSystem | | | | | | |
| FW | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| Emulex Mezzanine Card for p-Class Blades (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| QLogic Balcony Card for p-Class Blades (2G, PCI-X) QLogic Mezzanine Card for p-Class Blades (2G, PCI-X) | | | | | | |
| FW (BL25p) | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 |
| FW (BL20p, BL30p, and BL35p) | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 |
| WIN 2003 SCSIport Driver | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 |
| WIN 2003 StorPort Driver ^{3,4} | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| FCA2404 / Emulex LP9802 (2G, PCI-X) FCA2404DC / Emulex LP9802DC (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| FCA2101 / Emulex LP952 (2G, PCI-X) | | | | | | |
| FW | 3.93a0 | 3.93a0 | 3.93a0 | 3.93a0 | 3.93a0 | 3.93a0 |
| WIN 2003 SCSIport Driver | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 | 5-5.30a2 |
| WIN 2003 StorPort Driver ^{3,4} | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 | 5-1.20a7 |
| FCA2214 / QLogic 2340 (2G, PCI-X) FCA2214DC / QLogic 2342 (2G, PCI-X) | | | | | | |
| FW | 1.45 | 1.45 | 1.45 | 1.45 | 1.45 | 1.45 |
| WIN 2003 SCSIport Driver | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 | 9.1.3.11 |
| WIN 2003 StorPort Driver ^{3,4} | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |

NOTES:

- 1) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 2) 3rd Party adapters require HP drivers and firmware.

- 3) All non-sp2 systems running applications other than Tivoli require updated Storport.sys KB891793 (minimum) or KB916048 (recommended); systems running Tivoli require Storport.sys KB901371. All sp2 systems are required to run Storport.sys KB932755
- 4) Please reference ISV application installation/support documents for specific driver and patch requirements

Windows (x86) - Continued

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Disk Array Multipath Support ¹ | | | | | | |
| Secure Path for Windows | 4.0C SP2-1 | 4.0C SP2-1 | 4.0C SP2-1 | 4.0C SP2-1 | 4.0C SP2-1 | 4.0C SP2-1 |
| Windows MPIO ⁵ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| High Availability ² | | | | | | |
| Windows (MSCS) | ✓ | ✓ | ✓ | ✓ ³ | ✓ ⁴ | ✓ |

NOTES:

1) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

2) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.

3) Not supported with TSM 5.3.x.

4) Support includes NAS9000 and NAS4000 platforms.

5) Windows Full-Feature MPIO failover support. Clusters sharing disk and tape on the same HBA require StorPort.

Windows (Integrity)

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| Windows Server 2003 (64-bit) | sp2 | sp2 | sp2 | sp2 | | sp2 |
| Servers | | | | | | |
| HP Integrity Superdome and Mid-Range (rx7000-rx8000 Series, Integrity) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP Integrity Entry-Level (rx1000-rx6000 Series, Integrity) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ^{4, 7} | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| AB379A / AB379B (4G, PCI-X 2.0) FC1143 (4G, PCI-X 2.0) | | | | | | |
| EFI | 1.09 | 1.09 | 1.09 | 1.09 | | 1.09 |
| WIN 2003 StorPort Driver ^{5, 8} | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | | 9.1.3.16 |
| FC2143 / Emulex LP1150 (4G, PCI-X 2.0) FC2243 / Emulex LP11002 (4G, PCI-X 2.0) | | | | | | |
| FW | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | | 2.10a10 |
| WIN 2003 SCSIport Driver | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | | 6-5.30a2 |
| WIN 2003 StorPort Driver ^{5, 8} | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | | 6-1.20a7 |
| AB467A / Emulex LP1050 (2G, PCI-X) AB466A / Emulex LP1050DC (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | | 1.91a5 |
| WIN 2003 SCSIport Driver | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | | 6-5.30a2 |
| WIN 2003 StorPort Driver ^{5, 8} | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | | 6-1.20a7 |
| A7298A / Emulex LP982 (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | | 1.91a5 |
| WIN 2003 SCSIport Driver | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | | 6-5.30a2 |
| WIN 2003 StorPort Driver ^{5, 8} | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | | 6-1.20a7 |
| AB232A / Emulex LP9802 (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | | 1.91a5 |
| WIN 2003 SCSIport Driver | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | 6-5.30a2 | | 6-5.30a2 |
| WIN 2003 StorPort Driver ^{5, 8} | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | 6-1.20a7 | | 6-1.20a7 |
| Disk Array Multipath Support ⁴ | | | | | | |
| Secure Path for Windows | 4.0C SP2-1 | 4.0C SP2-1 | 4.0C SP2-1 | 4.0C SP2-1 | | 4.0C SP2-1 |
| Windows MPIO ⁶ | ✓ | ✓ | ✓ | ✓ | | ✓ |
| High Availability ³ | | | | | | |
| Windows (MSCS) | ✓ | | | ✓ | | ✓ |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.
- 4) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 5) Please reference ISV application installation/support documents for specific driver and patch requirements.
- 6) Windows Full-Feature MPIO failover support. Clusters sharing disk and tape on the same HBA require StorPort.
- 7) 3rd Party adapters require HP drivers and firmware.
- 8) All non-sp2 systems running applications other than Tivoli require updated Storport.sys KB891793 (minimum) or KB916048 (recommended); systems running Tivoli require Storport.sys KB901371. All sp2 systems are required to run Storport.sys KB932755.

Windows (x64)

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems 1, 2 | | | | | | |
| Windows Server 2003 x64 Edition | sp2 | sp2 | sp2 | sp2 | sp2 | sp2 |
| Windows Server 2003 R2 x64 Edition | sp2 | sp2 | sp2 | sp2 | sp2 | sp2 |
| Servers | | | | | | |
| HP ProLiant | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| HP ProLiant c-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| HP ProLiant p-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Fibre Host Bus Adapters 4,5 | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| FC1243 (4G, PCI-X 2.0) | | | | | | |
| FC1143 (4G, PCI-X 2.0) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 |
| WIN 2003 StorPort Driver 6,7 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| FC2143 / Emulex LP1150 (4G, PCI-X 2.0) | | | | | | |
| FC2243 / Emulex LP11002 (4G, PCI-X 2.0) | | | | | | |
| FW | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 |
| WIN 2003 StorPort Driver 6,7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 |
| FC2142SR / Emulex LPe1150 (4G, PCIe) | | | | | | |
| FC2242SR DC / Emulex LPe11002-M4 (4G, PCIe) | | | | | | |
| FW | 2.50a6 | 2.50a6 | 2.50a6 | 2.50a6 | 2.50a6 | 2.50a6 |
| WIN 2003 StorPort Driver 6,7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 |
| FC1142SR / QLogic QLE2460 (4G, PCIe) | | | | | | |
| FC1242SR DC / QLogic QLE2462 (4G, PCIe) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 |
| WIN 2003 StorPort Driver 6,7 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| A7388A / Emulex LP1050 (2G, PCI-X) | | | | | | |
| A7387A / Emulex LP1050DC (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 StorPort Driver 6,7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 |
| FCA2408 / Emulex LP982 (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 StorPort Driver 6,7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 |
| QMH2462 (4G, PCIe) for HP c-Class BladeSystem | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 | 1.26 |
| WIN 2003 StorPort Driver 6,7 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| LPe1105 (4G, PCIe) for HP c-Class BladeSystem | | | | | | |
| FW | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 |
| WIN 2003 StorPort Driver 6,7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 |
| QLogic Balcony Card for p-Class Blades (2G, PCI-X) | | | | | | |
| QLogic Mezzanine Card for p-Class Blades (2G, PCI-X) | | | | | | |
| FW (BL25p) | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 |
| FW (BL20p, BL30p, and BL35p) | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 | 1.48 |
| WIN 2003 StorPort Driver 6,7 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 | 9.1.3.16 |
| FCA2404 / Emulex LP9802 (2G, PCI-X) | | | | | | |
| FCA2404DC / Emulex LP9802DC (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 |
| WIN 2003 StorPort Driver 6,7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 | 7-1.20a7 |
| Disk Array Multipath Support 4 | | | | | | |
| Windows MPIO | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| High Availability 3 | | | | | | |
| Windows (MSCS) | ✓ | ✓ | | ✓ | | |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.

- 4) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 5) 3rd Party adapters require HP drivers and firmware.
- 6) All non-sp2 systems running applications other than Tivoli require updated Storport.sys KB903081 (minimum) or KB916048 (recommended); systems running Tivoli require Storport.sys KB901371. All sp2 systems are required to run Storport.sys KB932755.
- 7) Please reference ISV application installation/support documents for specific driver and patch requirements.

LINUX (x86) 4,6

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems 1, 2 | | | | | | |
| Red Hat Enterprise Linux [AS/ES/WS] 3.0 (32-bit) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Red Hat Enterprise Linux [AS/ES/WS] 4.0 (32-bit) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| United Linux 1.0/SUSE SLES 8 (32-bit) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| SUSE SLES 9 (32-bit) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| SUSE SLES 10 (32-bit) | ✓ | | | | | ✓ |
| Servers | | | | | | |
| HP ProLiant | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP ProLiant c-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP ProLiant p-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Third Party X86 | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters 3, 5 | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| FC1243 (4G, PCI-X 2.0) | | | | | | |
| FC1143 (4G, PCI-X 2.0) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | | 1.26 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| FC2143 / Emulex LP1150 (4G, PCI-X 2.0) | | | | | | |
| FC2243 / Emulex LP11002 (4G, PCI-X 2.0) | | | | | | |
| FW | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | | 2.70a5 |
| Red Hat Enterprise Linux 3.0 driver | 7.3.6 | 7.3.6 | 7.3.6 | | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| FC2142SR / Emulex LPe1150 (4G, PCIe) | | | | | | |
| FC2242SR DC / Emulex LPe11002-M4 (4G, PCIe) | | | | | | |
| FW | 2.50a6 | 2.50a6 | 2.50a6 | 2.50a6 | | 2.70a5 |
| Red Hat Enterprise Linux 3.0 driver | 7.3.6 | 7.3.6 | 7.3.6 | | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| FC1142SR / QLogic QLE2460 (4G, PCIe) | | | | | | |
| FC1242SR DC / QLE2462 (4G, PCIe) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | | 1.26 |
| Red Hat Enterprise Linux 3.0 driver | 7.07.05 | 7.07.05 | 7.07.05 | | | 7.07.05 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| United Linux 1.0/SUSE SLES 8 driver | 7.07.05 | 7.07.05 | 7.07.05 | | | 7.07.05 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| FCA2214 / QLogic 2340 (2G, PCI-X) | | | | | | |
| FCA2214DC / QLogic 2342 (2G, PCI-X) | | | | | | |
| BIOS | 1.45 | 1.45 | 1.45 | 1.45 | | 1.45 |
| Red Hat Enterprise Linux 3.0 driver | 7.07.05 | 7.07.05 | 7.07.05 | 7.07.05 | | 7.07.05 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| United Linux 1.0/SUSE SLES 8 driver | 7.07.05 | 7.07.05 | 7.07.05 | 7.07.05 | | 7.07.05 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 4) EBS is not dependent on specific kernel errata levels. For required/supported kernel errata, refer to your online storage array and backup application support documentation.
- 5) 3rd Party adapters require HP drivers and firmware.
- 6) Due to tape device discovery issues, SP2 for SLES 9 is not supported.

LINUX (x86)^{4,6} - Continued

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Fibre Host Bus Adapters^{3, 5} | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| QMH2462 (4G, PCI-e) for HP c-Class BladeSystem | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | | 1.26 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| LPe1105 (4G, PCI-e) for HP c-Class BladeSystem | | | | | | |
| FW | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 | | 2.70a5 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| Emulex Mezzanine Card for p-Class Blades (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | | 1.91a5 |
| Red Hat Enterprise Linux 3.0 driver | 7.3.6 | 7.3.6 | 7.3.6 | 7.3.6 | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| QLogic Balcony Card for p-Class Blades (2G, PCI-X) QLogic Mezzanine Card for BL20p G2/G3 (2G, PCI-X) | | | | | | |
| FW (BL25p) | 1.48 | 1.48 | 1.48 | 1.48 | | 1.48 |
| FW (BL20p, BL30p, and BL35p) | 1.48 | 1.48 | 1.48 | 1.48 | | 1.48 |
| Red Hat Enterprise Linux 3.0 driver | 7.07.05 | 7.07.05 | 7.07.05 | 7.07.05 | | 7.07.05 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| United Linux 1.0/SUSE SLES 8 driver | 7.07.05 | 7.07.05 | 7.07.05 | 7.07.05 | | 7.07.05 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| Disk Array Multipath Support³ | | | | | | |
| Emulex Multipulse (2.6 kernels only) | 2.1.9 | 2.1.9 | 2.1.9 | 2.1.9 | | 2.2.20 |
| QLogic Native Multi-Path for Linux (2.4 kernel) | 7.07.05 | 7.07.05 | 7.07.05 | 7.07.05 | | 7.07.05 |
| QLogic Native Multi-Path for Linux (2.6 kernel) | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| Secure Path for Linux | 3.0C | | 3.0C SP2 | 3.0C SP1 | | 3.0C SP2 |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 4) EBS is not dependent on specific kernel errata levels. For required/supported kernel errata, refer to your online storage array and backup application support documentation.
- 5) 3rd Party adapters require HP drivers and firmware.
- 6) Due to tape device discovery issues, SP2 for SLES 9 is not supported.

LINUX (Integrity) ^{3,5}

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| Red Hat Enterprise Linux [AS/ES/WS] 3.0 (64-bit) | ✓ | | ✓ | | | ✓ |
| Red Hat Enterprise Linux [AS/ES/WS] 4.0 (64-bit) | ✓ | ✓ | ✓ | | | ✓ |
| United Linux 1.0/SUSE SLES 8 (64-bit) | ✓ | ✓ | ✓ | | | |
| SUSE SLES 9 (64-bit) | ✓ | ✓ | ✓ | | | ✓ |
| SUSE SLES 10 (64-bit) | ✓ | | | | | ✓ |
| Servers | | | | | | |
| HP Integrity Superdome and Mid-Range (rx7000-rx8000 Series, Integrity) | ✓ | ✓ | ✓ | | | ✓ |
| HP Integrity Entry-Level (rx1000-rx6000 Series, Integrity) | ✓ | ✓ | ✓ | | | ✓ |
| Fibre Host Bus Adapters ⁴ | | | | | | |
| AB379A / AB379B (4G, PCI-X 2.0) FC1143 (4G, PCI-X 2.0) | | | | | | |
| EFI | 1.09 | 1.09 | 1.09 | | | 1.09 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| FC2143 / Emulex LP1150 (4G, PCI-X 2.0) FC2243 / Emulex LP11002 (4G, PCI-X 2.0) | | | | | | |
| FW | 2.10a10 | 2.10a10 | 2.10a10 | | | 2.70a5 |
| Red Hat Enterprise Linux 3.0 driver | | | 7.3.6 | | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| A6826A (2G, PCI-X) | | | | | | |
| BIOS | 1.45 | 1.45 | 1.45 | | | 1.45 |
| Red Hat Enterprise Linux 3.0 driver | 7.07.05 | | 7.07.05 | | | 7.07.05 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| United Linux 1.0/SUSE SLES 8 driver | 7.07.05 | 7.07.05 | 7.07.05 | | | |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| A7538A (2G, PCI-X) | | | | | | |
| BIOS | 1.45 | 1.45 | 1.45 | | | 1.45 |
| Red Hat Enterprise Linux 3.0 driver | 7.07.05 | | 7.07.05 | | | 7.07.05 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| United Linux 1.0/SUSE SLES 8 driver | 7.07.05 | 7.07.05 | 7.07.05 | | | |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| Disk Array Multipath Support ⁴ | | | | | | |
| Emulex Multipulse (2.6 kernels only) | 2.1.9 | 2.1.9 | 2.1.9 | | | 2.2.20 |
| QLogic Native Multi-Path for Linux (2.4 kernel) | 7.07.05 | 7.07.05 | 7.07.05 | | | 7.07.05 |
| QLogic Native Multi-Path for Linux (2.6 kernel) | 8.01.06 | 8.01.06 | 8.01.06 | | | 8.01.06 |
| Secure Path for Linux | 3.0C | | 3.0C | | | 3.0C SP2 |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.

- 3) EBS is not dependent on specific kernel errata levels. For required/supported kernel errata, refer to your online storage array and backup application support documentation.
- 4) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 5) Due to tape device discovery issues, SP2 for SLES 9 is not supported.

LINUX (x64) ^{4,6}

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| Red Hat Enterprise Linux [AS/ES/WS] 4.0 (x64) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| SUSE SLES 9 (x64) | ✓ | ✓ | ✓ | ✓ | | ✓ |
| SUSE SLES 10 (x64) | ✓ | | | | | ✓ |
| Servers | | | | | | |
| HP ProLiant | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP ProLiant c-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP ProLiant p-Class BladeSystem | ✓ | ✓ | ✓ | ✓ | | ✓ |
| HP NetServer | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Third Party X86 | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ^{3, 5} | | | | | | |
| HP Branded / 3rd Party | | | | | | |
| FC1243 (4G, PCI-X 2.0) | | | | | | |
| FC1143 (4G, PCI-X 2.0) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | | 1.26 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| FC2143 / Emulex LP1150 (4G, PCI-X 2.0) | | | | | | |
| FC2243 / Emulex LP11002 (4G, PCI-X 2.0) | | | | | | |
| FW | 2.10a10 | 2.10a10 | 2.10a10 | 2.10a10 | | 2.70a5 |
| Red Hat Enterprise Linux 3.0 driver | 7.3.6 | 7.3.6 | 7.3.6 | 7.3.6 | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| FC2142SR / Emulex LPe1150 (4G, PCIe) | | | | | | |
| FC2242SR DC / Emulex LPe11002-M4 (4G, PCIe) | | | | | | |
| FW | 2.50a6 | 2.50a6 | 2.50a6 | 2.50a6 | | 2.70a5 |
| Red Hat Enterprise Linux 3.0 driver | 7.3.6 | 7.3.6 | 7.3.6 | 7.3.6 | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| FC1142SR / QLogic QLE2460 (4G, PCIe) | | | | | | |
| FC1242SR DC / QLE2462 (4G, PCIe) | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | | 1.26 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| FCA2214 / QLogic 2340 (2G, PCI-X) | | | | | | |
| FCA2214DC / QLogic 2342 (2G, PCI-X) | | | | | | |
| BIOS | 1.45 | 1.45 | 1.45 | 1.45 | | 1.45 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| QMH2462 (4G, PCIe) for HP c-Class BladeSystem | | | | | | |
| BIOS | 1.26 | 1.26 | 1.26 | 1.26 | | 1.26 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| LPe1105 (4G, PCIe) for HP c-Class BladeSystem | | | | | | |
| FW | 2.50a8 | 2.50a8 | 2.50a8 | 2.50a8 | | 2.70a5 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| Emulex Mezzanine Card for p-Class Blades (2G, PCI-X) | | | | | | |
| FW | 1.91a5 | 1.91a5 | 1.91a5 | 1.91a5 | | 1.91a5 |
| Red Hat Enterprise Linux 3.0 driver | 7.3.6 | 7.3.6 | 7.3.6 | 7.3.6 | | 7.3.6 |
| Red Hat Enterprise Linux 4.0 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 9 driver | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | 8.0.16.27 | | 8.0.16.32 |
| SUSE SLES 10 driver | 8.1.6.7 | | | | | 8.1.6.7 |
| QLogic Balcony Card for p-Class Blades (2G, PCI-X) | | | | | | |
| QLogic Mezzanine Card for p-Class Blades G2/G3 (2G, PCI-X) | | | | | | |
| BIOS (BL25p) | 1.48 | 1.48 | 1.48 | 1.48 | | 1.48 |
| BIOS (BL20p, BL30p, and BL35p) | 1.48 | 1.48 | 1.48 | 1.48 | | 1.48 |
| Red Hat Enterprise Linux 4.0 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 9 driver | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |
| SUSE SLES 10 driver | 8.01.06 | | | | | 8.01.06 |
| Disk Array Multipath Support ³ | | | | | | |
| Emulex Multipulse (2.6 kernels only) | 2.1.9 | 2.1.9 | 2.1.9 | 2.1.9 | | 2.2.20 |
| QLogic Native Multi-Path for Linux (2.6 kernel) | 8.01.06 | 8.01.06 | 8.01.06 | 8.01.06 | | 8.01.06 |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 4) EBS is not dependent on specific kernel errata levels. For required/supported kernel errata, refer to your online storage array and backup application support documentation.
- 5) 3rd Party adapters require HP drivers and firmware.
- 6) Due to tape device discovery issues, SP2 for SLES 9 is not supported.

Solaris

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|---|-------------------|-------------|--------------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| Solaris 8 | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Solaris 9 | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Solaris 10 SPARC | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Solaris 10 x86/x64 | | | | | | ✓ |
| Servers | | | | | | |
| Sun UltraSPARC | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Sun Sun Fire | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ³ | | | | | | |
| SG-XPCI1FC-QF4 (4G, PCI-X 2.0) SG-XPCI2FC-QF4 (4G, PCI-X 2.0) Sun Native Driver | | | ✓ | ✓ | | ✓ |
| QLogic QLA2460 (4G, PCI-X 2.0) QLogic QLA2462 (4G, PCI-X 2.0) Sun Native Driver | | | ✓ | ✓ | | ✓ |
| SG-XPCI1FC-QF2 (X6767A) (2G, PCI-X) SG-XPCI2FC-QF2 (X6768A) (2G, PCI-X) Sun Native Driver | ✓ | ✓ | ✓ | ✓ | | ✓ |
| SG-XPCI1FC-QL2 (2G, PCI-X) SG-XPCI2FC-QF2-Z (2G, PCI-X) Sun Native Driver | ✓ | ✓ | ✓ | ✓ | | ✓ |
| SG-XPCI1FC-EM2 (2G, PCI-X) SG-XPCI2FC-EM2 (2G, PCI-X) Sun Native Driver | ✓ | | | ✓ | | |
| QLogic QLA2340 (2G, PCI-X) QLogic QLA2342 (2G, PCI-X) Fcode | | | 2.00.09 | 2.00.09 | | |
| QLogic Driver | | | 4.20 | 4.20 | | |
| Sun Native Driver | | | ✓ | ✓ | | |
| FCA2257P (2G, PCI-X) Fcode | 2.00.09 | 2.00.09 | 2.00.09 | 2.00.09 | | 2.00.09 |
| Driver | 4.20 | 4.20 | 4.20 | 4.20 | | 4.20 |
| FCA2684/Emulex LP10000 (2G, PCI-X) FCA2684DC/Emulex LP10000DC (2G, PCI-X) FW | 1.91a1 | 1.91a1 | 1.91a1 | 1.91a1 | | 1.91a1 |
| Emulex Driver | 6.02h | 6.02h | 6.02h ⁴ | 6.02h ⁴ | | 6.02h |
| Sun Native Driver | | ✓ | ✓ | ✓ | | ✓ |
| Emulex LP9002L (2G, PCI-X) FW | | | 3.92a2 | | | 3.92a2 |
| Emulex Driver | | | 6.01f | | | 5.01E ⁵ |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
September 2007, v1.0

- 4) Supported with Solaris 9 only.
- 5) Solaris 8 support only.

Solaris - Continued

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|----------------|----------------------------|----------------------|----------------------------|
| Disk Array Multipath Support ¹ | | | | | | |
| Secure Path for Solaris | 3.0D SP1-2 | 3.0D SP1-2 | 3.0D SP1-2 | 3.0D SP1-2 | | 3.0D SP1-2 |
| Solaris MPxIO | | | ✓ ⁴ | ✓ ⁴ | | ✓ ³ |
| VERITAS DMP | | | ✓ ⁵ | | | ✓ ⁵ |
| High Availability ² | | | | | | |
| VERITAS Cluster Server | | | | | | ✓ |

NOTES:

- 1) Refer to [EBS Design Guide](#) for configuration rules and guidelines.
- 2) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.
- 3) Supported with Solaris 9 only.
- 4) Supported with Solaris 9 and 10.
- 5) Supported with Solaris 10.

Tru64

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-----------------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| Tru64 5.1A ⁸ | 5.1A pk6 | 5.1A pk6 ⁷ | 5.1A pk6 | | | 5.1A pk6 |
| Tru64 5.1B ⁸ | 5.1B-3 | | 5.1B-4 | | | 5.1B-4 |
| Servers | | | | | | |
| HP AlphaServer | ✓ | ✓ | ✓ | | | ✓ |
| Fibre Host Bus Adapters ⁵ | | | | | | |
| FCA2684 (2G, PCI-X) | | | | | | |
| FCA2684 DC (2G, PCI-X) | | | | | | |
| FW | 1.91x6 | | 1.91x6 | | | 1.91x6 |
| Tru64 Driver | 2.17 | | 2.17 | | | 2.17 |
| FCA2354 (2G, PCI-X) | | | | | | |
| FW | 3.93a0 | 3.93a0 | 3.93a0 | | | 3.93a0 |
| Tru64 Driver | 2.17 | 2.14 | 2.17 | | | 2.17 |
| FCA2384 (2G, PCI-X) | | | | | | |
| FW | 1.91x6 | | 1.91x6 | | | 1.91x6 |
| Tru64 Driver | 2.17 | | 2.17 | | | 2.17 |
| Disk Array Multipath Support ⁵ | | | | | | |
| Tru64 Multipath | | Native | Native | | | Native |
| High Availability ⁴ | | | | | | |
| Tru64 (TruCluster) | | | ✓ | | | ✓ |

OVMS

| | | | | | | |
|---|--------|--|--|--|--|--|
| Operating Systems ^{1, 2} | | | | | | |
| OpenVMS 8.2 ^{3, 6, 8} | ✓ | | | | | |
| OpenVMS 8.2-1 ^{3, 6, 8} | ✓ | | | | | |
| OpenVMS 8.3 ^{3, 6, 8} | ✓ | | | | | |
| Servers | | | | | | |
| HP AlphaServer | ✓ | | | | | |
| HP Integrity | ✓ | | | | | |
| Fibre Host Bus Adapters ⁵ | | | | | | |
| FCA2684 (2G, PCI-X) | | | | | | |
| FCA2684 DC (2G, PCI-X) | | | | | | |
| FW | 1.91x6 | | | | | |
| OVMS Driver | Native | | | | | |
| FCA2354 (2G, PCI-X) | | | | | | |
| FW | 3.93a0 | | | | | |
| OVMS Driver | Native | | | | | |
| FCA2384 (2G, PCI-X) | | | | | | |
| FW | 1.91x6 | | | | | |
| OVMS Driver | Native | | | | | |
| A6826A (2G, PCI-X) | | | | | | |
| EFI | 1.47 | | | | | |
| OVMS Driver | Native | | | | | |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) OpenVMS supported in switched fabric configurations only.
- 4) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations
- 5) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 6) [Click here](#) for additional data protection applications and solution information for OpenVMS, which includes HP and 3rd Party Heterogeneous Backup Solutions, as well as OpenVMS-specific solutions including ABS (Archive Backup Systems) and SLS (Storage Library System)
- 7) Support is with BEB v10.5 only
- 8) Ultrium 230 (LTO) not supported

AIX

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|---------------------|---------------------|---------------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| AIX 5.2 | ✓ ³ | ✓ | ✓ | ✓ | | ✓ |
| AIX 5.3 | ✓ ³ | ✓ | ✓ | ✓ | | ✓ |
| Servers | | | | | | |
| IBM RS/6000 | ✓ | ✓ | ✓ | ✓ | | ✓ |
| IBM pSeries | ✓ | ✓ | ✓ | ✓ | | ✓ |
| Fibre Host Bus Adapters ⁴ | | | | | | |
| A7539A (Cambex PC2000) (2G, PCI-X) | | | | | | |
| AIX Driver w/o Secure Path | 1.5.26.0 | 1.5.26.0 | 1.5.26.0 | | | 1.5.26.0 |
| AIX Driver w/ Secure Path | 1.6.5.1 | 1.6.5.1 | 1.6.5.1 | | | 1.6.5.1 |
| IBM 6228 (2G, PCI-X) | | | | | | |
| AIX Driver | Native | Native | Native | Native | | Native |
| IBM 6239 (2G, PCI-X) | | | | | | |
| AIX Driver | Native ⁸ | Native ⁸ | Native ⁸ | Native ⁸ | | Native ⁸ |
| IBM 5716 (2G, PCI-X) | | | | | | |
| AIX Driver | Native ⁹ | Native ⁸ | Native ⁸ | Native ⁸ | | Native ⁸ |
| IBM 5758 (4G, PCI-X 2.0) IBM 5759 (4G, PCI-X 2.0) | | | | | | |
| AIX Driver | | | Native ⁹ | | | |
| Disk Array Multipath Support ⁴ | | | | | | |
| Secure Path for AIX | 2.0D SP3 | 2.0D SP3 | 2.0D SP3 | 2.0D SP3 | | 2.0D SP3 |
| AIX MPIO | ✓ ⁶ | | ✓ | ✓ | | ✓ |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) Robot control is not supported
- 4) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 5) DLT8000 products not supported
- 6) Disk and tape require dedicated HBA's.
- 7) Supported with AIX 5.2 only.
- 8) Supported with AIX 5.2 and 5.3 only.
- 9) Supported with AIX 5.3 only.

NetWare

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|----------------------|---------------|----------------------------|----------------------|----------------------------|
| Operating Systems ^{1, 2} | | | | | | |
| NetWare 6.0 | 6.0 sp5 | 6.0 sp5 ³ | | | 6.0 sp5 | |
| NetWare 6.5 | 6.5 sp5 | 6.5 sp2 ³ | | | 6.5 sp6 | |
| Servers | | | | | | |
| HP ProLiant ⁵ | ✓ | ✓ | | | ✓ | |
| HP ProLiant p-Class Blade Server ⁵ | ✓ | ✓ | | | ✓ | |
| Third Party X86 | ✓ | ✓ | | | ✓ | |
| Fibre Host Bus Adapters ^{3, 5} | | | | | | |
| FCA2214 (FCA2210) / QLA2340 (2G, PCI-X) FCA2214DC / QLA2342 (2G, PCI-X) | | | | | | |
| FW | 1.45 | 1.45 | | | 1.45 | |
| NetWare Driver | 6.90m | 6.51b | | | 6.90m | |
| Disk Array Multipath Support ⁵ | | | | | | |
| Secure Path for NetWare ⁹ | 3.0c SP2.1 | 3.0c SP2 | | | 3.0c SP2.1 | |
| MPIO | ✓ | | | | ✓ | |
| High Availability ⁴ | | | | | | |
| NetWare 6.0 (NWCS) | ✓ | | | | ✓ | |
| NetWare 6.5 (NWCS) | ✓ | | | | ✓ | |

NOTES:

- 1) Other Operating Systems may be supported within EBS by the respective ISVs as LAN clients.
- 2) Please reference your ISV support matrices for supported application and operating system version compatibility.
- 3) NetWare is supported with ESL libraries in a homogeneous environment only.
- 4) Refer to the [EBS Design Guide](#) for details on failover configurations. For Operating Systems not listed, please refer to the ISV's web page for supported High Availability configurations.
- 5) Refer to [EBS Design Guide](#) for configuration rules and guidelines.

- 6) COMPAQ HBAs
- 7) NetWare 5.1 and 6.0 support only.
- 8) Heterogeneous Windows and NetWare configurations require FCA-2210 HBA for access to shared tape.
- 9) MSA1000 and EVA require FCA-2210 HBA with a minimum Secure Path version of 3.0c. HSG80 arrays with FCA-2210 HBA require a minimum Secure Path version of 3.0c SP2.

RAID Arrays

| SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|----------------|---------------|----------------------------|----------------------|----------------------------|
| RAID Arrays | | | | | | |
| XP 24000 ¹ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| XP 12000 ¹ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| XP 10000 ¹ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| XP 1024/128 ¹ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| XP 48/512 ¹ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Zero Downtime with XP ⁷ | ✓ | | | | | |
| Instant Recovery with XP ⁷ | ✓ | | | | | |
| Enterprise Virtual Array ¹ EVA 4x00/6x00/8x00 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Enterprise Virtual Array ^{1, 3, 6} EVA 3000/5000 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSA1500 ¹ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSA1000 Small Business SAN Kit | ✓ ⁴ | ✓ ⁵ | | | ✓ ⁵ | |
| MSA1000 ² | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

NOTES:

- 1) Consult with your hp solutions provider for disk array SAN compatibility information
- 2) For compatibility information about the optional MSA SAN Switch, refer to the [Infrastructure](#) page within this document for support details
- 3) Supported with Fibre Channel and FATA disk drives.

- 4) LINUX and Windows support only
- 5) Windows support only
- 6) Supported with VCS 3.X and 4.X.
- 7) XP24000 currently not supported.

Infrastructure

| SAN Support | Supported Release | Native Fibre Channel Drives | | | Virtual Library Systems | | Interface Controllers | | | | | | | | | | |
|--|-------------------|-----------------------------|----------------------------|----------------------------|---------------------------|-----------------|-----------------------|--------------|-----------|---------------|---------------|-----------|-----------|-----------|-------------------|-----------|---|
| | | Ultrium 1840 FC Drive (4Gb) | Ultrium 960 FC Drive (4Gb) | Ultrium 960 FC Drive (2Gb) | VLS 12000/300 EVA Gateway | VLS 6000 Series | e2400-FC 4Gb | e2400-FC 2Gb | e2400-160 | e1200-320 4Gb | NSR E1200-160 | NSR E2400 | NSR E1200 | NSR M2402 | NSR N1200-320 4Gb | NSR N1200 | |
| SAN Switches¹ | | | | | | | | | | | | | | | | | |
| M-Series | | | | | | | | | | | | | | | | | |
| McData 4Gb SAN Switch for HP p-Class BladeSystem | 6.4.0.10.00 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| McData Sphereon 4700, 4400 | 09.03.00 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Director Switch 2/140, 2/64 | 09.03.00 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Edge Switch 2/32, 2/24, 2/16, 2/12 | 09.03.00 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| B-Series | | | | | | | | | | | | | | | | | |
| SAN Director 4/256 | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SAN Switch 4/64, 4/32B, 4/32, 4/16, 4/8 | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Brocade 4Gb SAN Switch for HP c-Class BladeSystem (4/12 and 4/24) | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Brocade 4Gb SAN Switch for HP p-Class BladeSystem | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SAN Director 2/128 | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Core Switch 2/64 | 5.0.5d | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SAN Switch 2/32, 2/8V, 2/16V, 2/16N | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| SAN Switch 2/16, 2/8, 2/8-EL, 2/16-EL | 3.2.1c | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| FC Switch 16B, 8B | 3.2.1c | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSA SAN Switch 2/8 | 3.2.1c | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| C-Series | | | | | | | | | | | | | | | | | |
| Cisco MDS 9513, 9506, 9509, 9216 9216a, 9216i, 9120, 9124, 9124e, 9140 | 3.1(3a) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Cisco MDS 9020 | 2.1(3) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Multi-Protocol Routers and Gateways¹ | | | | | | | | | | | | | | | | | |
| StorageWorks 400 Multi-Protocol Router ^{2,5} | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| StorageWorks Multi-Protocol Router Blade ^{2,5} | 5.3.0 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Multi-Protocol Router ^{2,3} | 7.4.1d | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| IP Storage Router 2122-2 ⁴ | 3.4.5c | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

NOTES:

- 1) Refer to [HP StorageWorks SAN Design Reference Guide](#) for configuration rules and guidelines
- 2) Supported with all backup application/operating system combinations.
- 3) Supported as a SAN-to-SAN interconnect only. Direct connection of libraries or hosts to the MP Router is not supported.

- 4) Supported for FC/IP SAN-to-SAN interconnect only.
- 5) Tape pipelining not supported.

ProLiant Storage Servers (NAS) and ProLiant Data Protection Storage Servers

| DAS, DAF, and SAN Support | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|--|-------------------|-------------|---------------|----------------------------|----------------------|----------------------------|
| EFS Clustered Gateway / Polyserve | √ ³ | | | | | |
| DL380 G5 Data Protection Storage Server | √ | | | | √ | √ ¹ |
| DL380 G4 Data Protection Storage Server | √ | | | | √ | √ ¹ |
| ML310 G2 Data Protection Storage Server | √ | | | | √ | √ ¹ |
| DL100G2 Storage Server ² | √ | | | | √ | √ ¹ |
| DL100 G2 Data Protection Storage Server ² | √ | | | | √ | √ ¹ |
| DL585G2 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| DL585 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| DL380 G5 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| DL380 G4 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML370 G4 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML350 G5 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML350 G4p Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML350 G4 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML310 G4 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML310 G3 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML310 G2 Storage Server | √ | √ | √ | √ | √ | √ ¹ |
| ML110 G2 Storage Server ² | √ | √ | | | √ | |
| AiO600 ² | √ | | | | √ | |
| AiO400 ² | √ | | | | √ | |
| NAS 9000s | √ | √ | √ | | √ | √ ¹ |
| NAS 4000s | √ | √ | √ | | √ | √ ¹ |
| NAS 8000 | √ | | | | | |
| NAS e7000 | √ | √ | √ | √ | √ | √ |
| NAS 1500s ² | √ | √ | | | √ | |
| NAS 500s ² | √ | √ | | | √ | |
| NAS 2000s ² | √ | √ | | | √ | |
| NAS 1200s ² | √ | √ | | | √ | |
| NAS B3000 | √ | √ | √ | √ | √ | √ |
| NAS B2000 | √ | √ | √ | √ | √ | √ |

NOTES:

- 1) Requires NetBackup 5.0 MP2 or later.
- 2) Tape connectivity via direct-attach SCSI only.
- 3) Supported with Data Protector v5.5 for Linux and v6.0 for windows.

SCSI Host Bus Adapters

HP Branded ProLiant, HP-9000, and HP Alpha SCSI Host Bus Adapters ^{2, 3, 4}

| Windows | | | | | |
|------------------|------------|---------------|--------------------|------------------|----------------|
| Product # (-B21) | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| 416096 (SAS) | PCI-e | 3Gb | 4 | SAS | SFF-8470 |
| AH627A | PCI-e | Ultra320 | 2 | SCSHLVD | VHDCI |
| 412911 | PCI-e | Ultra320 | 1 | SCSHLVD | VHDCI |
| 374654 | PCI-X | Ultra320 | 1 | SCSHLVD | VHDCI |
| 268351 | PCI-X | Ultra320 | 2 | SCSHLVD | VHDCI |
| 284688 | PCI | Ultra160 | 2 | SCSHLVD | VHDCI |
| 129803 | PCI-X | Ultra160 | 2 | SCSHLVD | VHDCI |
| 154457 | PCI-X | Ultra160 | 1 | SCSHLVD | HD68 |

| Linux | | | | | |
|------------------|------------|---------------|--------------------|------------------|----------------|
| Product # (-B21) | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| 416096 (SAS) | PCI-e | 3Gb | 4 | SAS | SFF-8470 |
| AH627A | PCI-e | Ultra320 | 2 | SCSHLVD | VHDCI |
| 412911 | PCI-e | Ultra320 | 1 | SCSHLVD | VHDCI |
| 374654 | PCI-X | Ultra320 | 1 | SCSHLVD | VHDCI |
| 268351 | PCI-X | Ultra320 | 2 | SCSHLVD | VHDCI |
| 284688 | PCI | Ultra160 | 2 | SCSHLVD | VHDCI |
| 129803 | PCI-X | Ultra160 | 2 | SCSHLVD | VHDCI |
| 154457 | PCI-X | Ultra160 | 1 | SCSHLVD | HD68 |

| Netware | | | | | |
|------------------|------------|---------------|--------------------|------------------|----------------|
| Product # (-B21) | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| 374654 | PCI-X | Ultra320 | 1 | SCSHLVD | VHDCI |
| 284688 | PCI | Ultra160 | 2 | SCSHLVD | VHDCI |
| 129803 | PCI-X | Ultra160 | 2 | SCSHLVD | VHDCI |
| 154457 | PCI-X | Ultra160 | 1 | SCSHLVD | HD68 |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |

| HP-UX | | | | | |
|---------------------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| A7173A | PCI-X | Ultra320 | 2 | SCSHLVD | VHDCI |
| AB290A | PCI-X | Ultra320 | 2 | SCSHLVD | VHDCI |
| A6829A | PCI-X | Ultra160 | 2 | SCSHLVD | VHDCI |
| A6828A | PCI-X | Ultra160 | 1 | SCSHLVD | VHDCI |
| A4999A ¹ | PCI | Ultra80 | 1 | SCSHLVD | HD68 |

| Tru64 | | | | | |
|-------------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| 3X-KXPEA-DB | PCI-X | Ultra160 | 2 | SCSHLVD | VHDCI |
| 3X-KXPCA-AA | PCI-X | Ultra80 | 1 | SCSHLVD | HD68 |
| | | | | | |
| | | | | | |
| | | | | | |

NOTES:

- 1) Supported on HP-UX Workstations only
- 2) Refer to the Server QuickSpecs to determine which SCSI HBAs are supported
- 3) Third party X86 servers supported with HP-Branded adapters only.
- 4) SMART Array Controllers do not support attachment to tape automation products.

SCSI Host Bus Adapters - Continued

HP Branded Integrity SCSI Host Bus Adapters, Integrity 64-bit ¹

| Windows | | | | | |
|-----------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| A7173A | PCI-X | Ultra320 | 2 | SCSI-LVD | VHDCI |
| A7060A | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| A7059A | PCI-X | Ultra160 | 1 | SCSI-LVD | VHDCI |
| | | | | | |

| Linux | | | | | |
|-----------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| A7173A | PCI-X | Ultra320 | 2 | SCSI-LVD | VHDCI |
| A7060A | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| A7059A | PCI-X | Ultra160 | 1 | SCSI-LVD | VHDCI |
| | | | | | |

| HP-UX | | | | | |
|-----------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| A7173A | PCI-X | Ultra320 | 2 | SCSI-LVD | VHDCI |
| AB290A | PCI-X | Ultra320 | 2 | SCSI-LVD | VHDCI |
| A6829A | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| A6828A | PCI-X | Ultra160 | 1 | SCSI-LVD | VHDCI |

NOTES:

1) Refer to the Server QuickSpecs to determine which SCSI HBAs are supported

SCSI Host Bus Adapters - Continued

Third Party SCSI HBA and Integrated SCSI Controllers ^{1,2,3}

| Windows | | | | | |
|---------------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| Adaptec 29320 | PCI-X | Ultra320 | 1 | SCSI-LVD | HD68 |
| Adaptec 29160 | PCI-X | Ultra160 | 1 | SCSI-LVD | VHDCI |
| Adaptec 39160 | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| LSI 22915 | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| ATTOTech UL4D | PCI-X | Ultra320 | 2 | SCSI-LVD | VHDCI |
| ATTOTech UL5D | PCI-e | Ultra320 | 2 | SCSI-LVD | VHDCI |

| Linux | | | | | |
|---------------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| Adaptec 29320 | PCI-X | Ultra320 | 1 | SCSI-LVD | HD68 |
| Adaptec 29160 | PCI-X | Ultra160 | 1 | SCSI-LVD | VHDCI |
| Adaptec 39160 | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| ATTOTech UL4D | PCI-X | Ultra320 | 2 | SCSI-LVD | VHDCI |
| ATTOTech UL5D | PCI-e | Ultra320 | 2 | SCSI-LVD | VHDCI |
| | | | | | |

| Netware | | | | | |
|---------------|------------|---------------|--------------------|------------------|----------------|
| Product # | System Bus | Data Transfer | Number of Channels | Signal Interface | Connector Type |
| Adaptec 29320 | PCI-X | Ultra320 | 1 | SCSI-LVD | HD68 |
| Adaptec 29160 | PCI-X | Ultra160 | 1 | SCSI-LVD | VHDCI |
| Adaptec 39160 | PCI-X | Ultra160 | 2 | SCSI-LVD | VHDCI |
| | | | | | |
| | | | | | |

NOTES:

- 1) For Solaris and AIX configurations, HP supports all SCSI HBA's supported by the server hardware manufacturer. Refer to the server manufacturer's web site for supported HBA/server platform/operating system combinations.
- 2) Third Party SCSI HBA support is for HP servers only
- 3) See vendor website for additional details:
<http://www.adaptec.com/>
<http://www.attotech.com/hp.html>
<http://www.lsilogic.com/>

Storage Software

| | HP Data Protector | CA ARCserve | EMC NetWorker | IBM Tivoli Storage Manager | Symantec Backup Exec | Symantec Veritas NetBackup |
|-------------------------------|----------------------|-------------|---------------|-------------------------------|-------------------------|-------------------------------|
| Command View TL | 2.2.00 | 2.2.00 | 2.2.00 | 2.2.00 | 2.2.00 | 2.2.00 |
| Continuous Access | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Business Copy EVA | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Business Copy XP | ✓ | | | | | |
| Storage Essentials | 5.1.0 SP1 | 5.1.0 SP1 | 5.1.0 SP1 | 5.1.0 SP1 | 5.1.0 SP1 | 5.1.0 SP1 |
| Systems Insight Manager (SIM) | 5.0 SP5 | 5.0 SP5 | 5.0 SP5 | 5.0 SP5 | 5.0 SP5 | 5.0 SP5 |
| Insight Manager Agents | 7.70 | 7.70 | 7.70 | 7.70 | 7.70 | 7.70 |
| Smart Start | 7.70 | 7.70 | 7.70 | 7.70 | 7.70 | 7.70 |

Legacy Device Support

| Device Name | Last EBS Compatibility Matrix Where Device Was Listed ¹ |
|--|--|
| ESL9000 series libraries | September 2007 |
| ESL E-Series SDLT 160/320 | July 2007 |
| ESL 9000 Series SDLT 160/320 | July 2007 |
| 1/8 Tape Autoloader (SDLT 160/320) | July 2007 |
| MSL5000 Series | March 2006 |
| SSL1016 Tape Autoloaders | March 2006 |
| ESL9000 Series (Ultrium 230 and SDLT 110/220) | March 2006 |
| 1/8 Tape Autoloaders (Ultrium 230 and Ultrium 460) | March 2006 |
| ESL 9326 DX | March 2005 |
| ESL 9198 DLX | March 2005 |
| MSL 5026 DLX | March 2005 |
| SSL 2020 TL | March 2005 |
| DLT 40/80 | March 2005 |
| Modular Data Router (MDR) | February 2004 |
| TL895 | December 2002 |
| TL891DLX | December 2002 |
| ESL9326D | April 2002 |
| TL891D | April 2002 |
| DLT 35/70 | April 2002 |
| | |

NOTES:

1) EBS Compatibility Matrices from the last year can be found on <http://www.hp.com/go/ebs>.
For matrices older than one year, consult your HP Account Representative.

Useful Links

| Product Family | URL |
|--|---|
| EBS Home Webpage | http://www.hp.com/go/ebs |
| EBS Design Guide | http://h200001.www2.hp.com/bc/docs/support/SupportManual/c00190922/c00190922.pdf |
| EBS 1-2-3 | http://h18000.www1.hp.com/products/storageworks/ebs/ebs123.html |
| EBS Example Configurations | http://h200005.www2.hp.com/bc/docs/support/SupportManual/c00375285/c00375285.pdf |
| Library and Tape Tools (LTT) | http://h18006.www1.hp.com/products/storageworks/ltt/index.html |
| Interconnects | http://h18006.www1.hp.com/storage/saninfrastructure.html |
| RAID Arrays | http://h18006.www1.hp.com/storage/arrayssystems.html |
| OpenView Storage | http://h18006.www1.hp.com/storage/software.html |
| Data Protector | http://www.hp.com/go/dataprotector |
| Storage Media | http://h18006.www1.hp.com/storage/storagemedia.html |
| Firmware & Driver Downloads | http://welcome.hp.com/country/us/en/support.html |
| Windows OS/ProLiant Server Support Matrix | http://h10018.www1.hp.com/wwsolutions/windows/index-all.html |
| Linux OS/ProLiant Server Support Matrix | http://h18004.www1.hp.com/products/servers/linux/hpLinuxcert.html |
| NetWare OS/ProLiant Server Support Matrix | http://h10018.www1.hp.com/wwsolutions/novell/index-all.html |
| IT Resource Center Website | http://itrc.hp.com |
| Performance and Troubleshooting Support | http://www.hp.com/support/pat |
| Network Services - Backup and Recovery | http://h20219.www2.hp.com/services/cache/10819-0-0-225-121.aspx |
| Tape Systems | http://www.hp.com/go/tape |
| HP StorageWorks SAN Design Reference Guide | http://h20000.www2.hp.com/bizsupport/TechSupport/DocumentIndex.jsp?contentType=SupportManual&locale=en_US&docIndexId=179911&taskId=101&prodTypeld=12169&prodSeriesId=406734 |

Advisories

| Date | Problem Description | Number |
|------------------------------------|--|-------------------------------|
| Tape Libraries Advisories | | |
| 09/01/07 | NetApp Filers - Unable to Access Tape Devices Mapped Behind Port 1 of Interface Controllers in ESL E-Series and EML E-Series Enterprise Tape Libraries | c01154679 |
| 06/14/07 | HP StorageWorks Ultrium 230/460/960 Tape Drives - tape unload instructions for tapes stuck in Ultrium 230/460/960 tape drives | c00795203 |
| 05/31/07 | HP StorageWorks MSL5000 and MSL6000 Libraries - potential for CRC or Parity Errors when SCSI Termination is on the Controller | c00659626 |
| 06/16/06 | Interface Controller/NSR and Storport Drivers - Library and Tape Tools Hardware Scan Unresponsive When Using Storport Drivers and Interface Controller/NSR with Fibre LUN Target/Active Fabric Enabled. | c00683746 |
| 05/09/06 | Network Storage Router (NSR) or Interface Controller (IFC) have a Maximum Limit for the Number of Initiators That Can Be Seen Through One or Two External Fibre Channel Port Routers | c00492083 |
| 10/29/05 | 1/8 Autoloaders Ultrium 232, 448 and 960 - Tapes automatically labeled as slots with chance of duplicates | OT050930_CW02 |
| 07/11/05 | ESL-e Library Firmware v3.40 Recommended for Robot 24-Day Unresponsive Issue | c00891572 |
| Application Advisories | | |
| 08/23/06 | Data Protector Express Version 3.1 may generate a tape mount request (alert message number 1401) when using two drive versions of HP StorageWorks MSL 2024. | c00743086 |
| 07/06/06 | EMC Legato NetWorker backup jobs failing with 10 second timeout may occur while running on either Redhat Linux v2.1 or v3.0 and any tape library or tape drive | c00707628 |
| 12/12/05 | Symantec Backup Exec May Report "Drive Serialization" for HP EML and ESL E Tape Libraries Configured for SCSI-over-Internet Protocol (SIPP) - Requires HP Secure Manager Partitioning | c00571560 |
| 08/29/05 | Tivoli Storage Manager (TSM) 5.3.0.0 to 5.3.1.1 May Not Access All Tape Load Ports on ESL E-Series With Cross Link Kit | OT050822_CW01 |
| 06/20/05 | Tivoli Storage Manager (TSM) Server 5.3.0.0 to 5.3.1.1, Linux IA32 RHEL3 or SLES 8/9, and HP tape libraries with Ultrium 460 at 59W firmware fail on labeling, backup, and restore | OT050526_CW02 |
| Operating System Advisories | | |
| 06/21/07 | Solaris - ESL E-Series and EML E-Series Library Reboots Causing Device Access Issues on Servers Running Sun Native HBA Drivers | c00965686 |
| 05/31/07 | Microsoft Windows Server 2003 - Interoperability Issues with Persistent Binding of Symbolic Tape Names in an Enterprise Backup Solution (EBS) Configuration | c01064312 |
| 03/26/07 | Emulex StorPort Driver - Targets Cannot be Persistently Bound when Running with the Emulex StorPort Driver | c00871551 |
| 03/07/07 | Microsoft Windows SAN - How to Disable Tape Drive Polling on Microsoft Windows SAN-Attached Servers Running hplto.sys | c00718488 |
| 03/01/07 | HP-UX 11.11 - Running Get All Elements Details on HP-UX 11.11 Hosts Can Cause Tape Backups to Abort | c00869191 |
| 12/21/06 | Linux - Tape Drives in an HP StorageWorks Enterprise Backup Solution (EBS) Shared Tape Configuration are being Issued Rewind Commands by Rebooted Linux Hosts | c00823270 |
| 10/11/06 | Linux - Driver Kit Installation Procedures for HP StorageWorks Enterprise Backup Solution Shared Tape Configurations | c00788781 |
| 09/26/05 | Linux Red Hat - Tape Devices Not Discovered and Configured Across Server Reboots on Linux Red Hat | OT050715_CW01 |
| Miscellaneous Advisories | | |
| 06/08/05 | Change Media Notification - HP SDLT and DLT Tape Drive Change Media Notification. | OT050606_CW01 |

To view these advisories do the following:

- 1) Click on the advisory number above or go to the IT Resource Center at <http://itrc.hp.com> (NOTE: To review these documents, you must register to use this website.)
- 2) Select "search technical knowledge base" (located at the top of the page under "maintenance and support (hp products)")
- 3) To search the technical knowledge base, enter a search word like "EBS" or an advisory number listed above.

NOTE: There may be other important advisories that may effect your EBS environment that are not listed on this page. Refer to the technical knowledge base or contact your local support representative for additional information.