# CONTROL DATA® 9776 FIXED MODULE DRIVE

**Designed for OEM Original Equipment Manufacturers** 





The Control Data 9776 Fixed Module Drive (FMD) (A2, B2 and C2 configurations) is a mass-storage device containing two spindles of random-access disk memory. Each spindle has a capacity of 400 megabytes. Using the A2 version of this drive assures compatibility with the IBM 3350. Optional fixed-head capability (Models F) provides 1.24 million bytes for increased system flexibility.

Each CDC® 9776 consists of a cabinet and frame containing two decks with two Head Disk Assemblies (HDA), a dc power supply, logic chassis assembly, air circulation system and ac distribution assembly. Front and rear doors and a hinged cabinet cover allow access for all maintenance functions. HDA installation and removal is achieved via a hinged top cover by qualified field service personnel. Installation and removal of the HDA have been facilitated by ramped guides and a docking port.

#### **FEATURES**

- Sealed Head Disk Assembly module design improves reliability
- Customer Engineering movable data module can be exchanged in approximately 15 minutes
- A2/B2/C2 configuration
- Diagnostics micro programs for maintenance
- Error detection/correction code provided for up to four bits
- Defect skipping reduces alternate track assignment
- Rotational Positioning Sensing (RPS) saves latency time
- Read-Only Switch provides write inhibit

#### **OPTIONS**

- · Dual access to all 9776 models
- 1.24 million bytes of fixed-head, zero seek-time capability
- String-switch

# Deck Assembly


Each deck assembly consists of a drive motor with a fail-safe brake, head disk assembly, voice coil linear motor and read/write electronics.


# Air Circulation System

Each Fixed Module Drive has two air flow systems supplied by two impellers driven from a common blower motor. One system provides filtered air to each HDA and the rate of air flow is a minimum of 40 cubic feet per minute (12.2 m³/minute); the air temperature will not exceed 133°F (54°C). Air flow in this system is monitored by a pressure switch.

This system also contains a replaceable absolute filter and a second permanent absolute filter to reduce contaminants. The allowable contamination level of the filtered air to each HDA will not exceed 100 particles per cubic foot (3.5 x 10<sup>3</sup> P/m) of 0.5 micron and larger.

The second system provides air flow for the logic chassis and both power supplies. A temperature limit switch in the top of the logic chassis will cut ac power if that limit is exceeded.





**HEAD DISK ASSEMBLY (HDA)** 

# AC Power Distribution Assembly


The 9776 ac power distribution assembly provides primary power protection, phase rotation sensing, power sequencing, control and distribution functions associated with each FMD.


# DC Power Supply Assembly

A self-contained dc power supply assembly provides all of the dc power required for drive operation. In the 2X configuration, a switch allows dc power to be removed from the electronics for either spindle for independent on-line operation of one spindle while the other is being serviced.

# Logic Chassis Assembly

The logic chassis assembly consists of a wire-wrapped back-panel with pluggable circuit card assemblies, plus card guiding and support hardware. The assembly is cooled by forced air. A single-port device contains 67 cards, including a four-increases to 73 for an optional string-switch device.





#### **SPECIFICATIONS**

# Data Organization:

	IBM Emulation Mode		
	2 X 3330-1	2 X 3330-11	1 X 3350
Cylinders/Volume:	404	808	555
Tracks/Cylinder:	19	19	30
Tracks/Volume:	7,676	15,353	16,650
Track Capacity (Bytes):	13,030	13,030	19,069
Cylinder Capacity (Bytes):	247,570	247,570	572,070
Volume Capacity (Mbyte):	100	200	317.5
Spindle Capacity			
Moving head (Mbyte):	200	400	635
Fixed Head:	N/A	N/A	1.24

### Performance-

Data Transfer Rate: 1198K bps (9.6-MHz)

Spindle Speed: 3600 rpm Average Latency: 8.3 ms

Seek Time

Minimum: 10 ms Average: 25 ms Maximum: 50 ms

#### Power Requirements -

The 9776-A2 FMD requires threephase power obtained from either a wye or a delta source as noted below. A line filter is provided and filtered power is then daisy-chained to the other FMDs.

# 60 Hz (59.0 to 60.6 Hz)

Nominal	Range
200 V ac	180-220 V ac
208 V ac	187-229 V ac
230 V ac	207-253 V ac

# 50 Hz (49.0 to 50.5 Hz)

Nominal	Range
200/208 V ac delta	170-220 V ac
220 V ac delta	187-242 V ac
230/235/240 V ac	
delta	195-259 V ac
380 V ac wye	323-426 V ac
398/400/408/415	
V ac wyo	340 - 449 V ac

The FMD is delivered prewired for 208 V ac, 60 Hz or 380 V ac, 50 Hz line voltages and frequencies. Conversion to the other line voltages within a frequency is achieved by rewiring terminal strips within each FMD as outlined in the Equipment Maintenance Manual.

# Physical Characteristics (single drive basis) -

	A2/A2F/C2/C2F	B2/B2F
Height:	50.0 in (1270 mm)	same
Width:	42.0 in (1067 mm)	same
Depth:	33.3 in (844 mm)	same
Weight:	1100 lb (410 kg)	900 lb (344 kg)
Heat:	6000 Btu/h (1740 W)	4875 Btu/h (1413 W)
Power:	2.0 kVA	1.7 kVA

Environmental-

A2/A2F/B2/B2F/C2/C2F

Operating Temperature: 60°F to 90°F

(16°C to 32°C) 10% to 80% R.H. Specifications subject to change without notice

CONTROL DATA SALES OFFICES ARE LOCATED IN PRINCIPAL CITIES THROUGHOUT THE WORLD

OEM PRODUCT SALES BOX, 0, MINNEAPOLIS, MINNESOTA 55440 TELEPHONE: (612) 853-3111 TWX: 910-576-2978

Operating Humidity: