
# READ

Real-time Electronic Access and Display system



#### WHAT IT IS . . .

The modern digital computer is truly a remarkable device. However, with its growing capacity for storage of information (billions of characters) and its lightning fast internal speeds (measured in nanoseconds), the computer is already far ahead of man's ability to utilize its information retrieval capabilities.

Paper tapes, punch cards and high speed printers are continuously being improved but remain woefully slow compared with the internal access speeds of the computer. They are significantly slow when equated with the Real-Time requirements of the user.


Philco's READ (Real-time Electronic Access and Display system) provides a giant step in information retrieval techniques by offering <u>instant</u> visual communication with stored computer information. READ is essentially an electronic display system which converts digital data to a visual display on a cathode ray tube. The displayed data can be generated in textual, tabular and annotated graphical formats. Retrieved information can be viewed directly on the face of the cathode ray tube, optically displayed on a wall screen, recorded onto 16mm or 35mm film or transposed through a Xerox recorder into hard copy.

READ's format versatility, display variations and ultra-fast speed, make it particularly well suited for use in automated teaching, computer-aided design, command and control systems, computer program checkout, satellite tracking and other applications where dynamic and plotting capabilities are required.


### WHAT IT DOES . . .

The READ system is composed of a format controller, a character generator, a vector generator, a control logic module, a typewriter keyboard input device, a cursor, a cathode ray tube-optical display module and a custom engineered interface for mating with your computer system.


The READ system will accept data from the typewriter keyboard, or directly from the data processor. READ will accept data at rates up to 950,000 characters per second. Preprogrammed command codes which establish the format to be displayed are interpreted by the systems control logic and routed to the format controller, character generator or vector generator. Map overlays, X-Y plots, dynamic tracking, block diagrams and alpha-numeric information are instantly displayed to the user. Dynamic information such as the position of an orbiting satellite can be projected onto a wall screen map as an overlay so that its exact position can be visually monitored in real-time. In addition to direct viewing, hard copy records of static plots, block diagrams, and textual and tabular information can be made on film or Xerox.



Light Pen being used for display correction



Transistorized printed circuit cards are used throughout the system



Air traffic control display on CRT

#### READ is fast

READ can display over 4000 characters and 2000 lines at a repetition rate of thirty cycles per second, without flicker. Film records can be made with printing speeds of 36,000 lines per minute and graphic records at a rate of six graphs per second. This total capability is unobtainable today on electro-mechanical equipment.

### READ is versatile

The combination of the cathode ray display and optical and film attachments coupled with its ability to present data in textual, tabular and graphic forms make READ the most versatile information retrieval device available.

# READ is compatible

Any digital computer system can utilize READ when connected through a custom designed, relatively simple interface. READ can be connected on-line to a central processor or can be provided with its own internal storage unit which requires minimal interface.

## READ is programmable

Software for the optimum utilization of READ has already been investigated and basic routines have been devised. User software packages will be available shortly.

#### READ is reliable

Reliability has been engineered into the READ system with extended testing indicating a Mean Time Between Failure of 200 hours. Experience with the system indicates a Mean Time To Repair of 30 minutes.

#### READ is available


READ has already been built and is in operation. A complete system including 12 remote consoles and the necessary interface can be delivered within five months.

#### ENGINEERED COMPATIBILITY . . .


With the exception of the monitor, the READ system is completely transistorized, resulting in a compact and easily maintained installation. Modularization of READ subsystems permits simplified variation in console configuration. Thus READ can be customized to your system installation with a minimum of disruption.

Remote consoles greatly enhance and extend the scope of the READ system and can be used for internetwork communications. READ utilizes the central computer processor as the automatic data source but is independent of the processor once the information has been transferred. READ can be operated manually for data insertion and can also be utilized when the central processor is not available.


This advanced design peripheral computer equipment will give your information storage and retrieval system a true real-time capability with the many added advantages of unique display and hard copy presentation.



Tracking display projected on map overlay



Textual message generated on CRT



Block diagram generated on CRT

The Philco Real-time Electronic Access Display system (READ) is composed of modular units providing adaptability to various system configurations. A basic system consists of a Common Display Logic (CDL) unit with a

maximum of fifteen (15) remote units. The design of the CDL provides various options for on-line/off-line operation with various degrees of capability. The following are general specifications for a typical system:

- a. Power Requirements
  CDL 115V 1 phase 2000 watts
  Remote
  Units 115V 1 phase 500 watts
- b. Physical Characteristics
  CDL 24"x60"x72" 700 lb.
  Console 31"x26"x36" 150 lb.
  Console Power Supply
  24"x24"x28" 175 lb.

24"x24"x28" 175 lb. CDL can be located a maximum of 75 ft. from the digital data source. The console and the console power supply which are colocated can be located a maximum of 75 ft. from the CDL.

- Nominal Internal Storage
   A core memory with 4096 (36 bit) word capacity.
- d. Symbol/Character Generator
  Wired integrated line stroke method
  with a maximum of twenty-four
  (24) line segments. Maximum of
  seven character sizes—8:1 ratio.

64K characters when K=1 to 8. 64 key keyboard.

- e. CRT Size
  Console: 16" round, 19" round, 24" rectangular.
  Direct Projection: 10" or 12" high intensity, optically flat faced tube with simple refractive optic lens.
- f. Refresh Rate 30 frames per second Nominal.
- g. Vector Generator
  Vector length up to ½ screen diameter. Vector specified to interconnect point of 1024 x 1024 x-Y grid. Vector initial and terminal point accuracy of 1/512 screen diameter. Solid and dashed vectors.
- h. Type of Circuit Transistorized printed circuit cards.
- i. Absolute Position Accuracy  $\pm 0.2\%$

- Character Transfer Rate Max, 950,000 characters per second asynchronous. 200,000 characters per second synchronous.
- k. Major Position Change (Major Screen Diameter) 12.5  $\mu$ sec on 16" CRT
- I. Average Character Drawing Time 4.5  $\mu$ sec.
- m. Average Vector Drawing Time 6  $\mu$ sec.
- n. Succession Character Position Time 1.6 μsec with 16 character per line.
- o. Options
  - 1. High intensity direct projection
  - 2. Hard copy printer (multiple)
  - 3. Microfilm
  - 4. Light pen/cursor control
  - 5. Off-line operation
  - 6. Format control/stunt box
  - 7. Vector generator



# PHILCO. A SUBSIDIARY OF FORD MOTOR COMPANY, COMMUNICATIONS AND ELECTRONICS DIVISION

#### FOR MORE COMPLETE INFORMATION CONTACT:

LEXINGTON, MASSACHUSETTS 594 Marrett Road Lexington, Massachusetts Area Code 617 862-6000

ROME, NEW YORK 1333 East Dominick Street Rome, New York Area Code 513 336-8200

COLORADO SPRINGS, COLORADO Medallion Building, Suite 1040 Bijou at Union Boulevard Colorado Springs, Colorado Area Code 303 632-3559 LOS ANGELES, CALIFORNIA 999 N. Sepulveda Blvd. Airport Imperial Building Room 410-416 El Segundo, California Area Code 213 772-3554

COCOA BEACH, FLORIDA Cape Kennedy Office 1325 N. Atlantic Avenue Suite 222 Cocoa Beach, Florida Area Code 305 783-1380

HOUSTON, TEXAS 7015 Gulf Freeway Houston, Texas Area Code 713 MI 4-5439 DAYTON, OHIO Talbott Tower, Suite 1406 Dayton, Ohio

Area Code 513 223-7215

PALO ALTO, CALIFORNIA Western Development Lab. 3875 Fabian Way Palo Alto, California Area Code 415 DA 6-4350

RED BANK, NEW JERSEY 103 E. Front Street Tuller Building Red Bank, New Jersey Area Code 201 747-0016 WASHINGTON, D. C. 808 17th Street, N. W. Washington, D. C.

Area Code 202 298-7800

WILLOW GROVE, PENNSYLVANIA 3900 Welsh Road Willow Grove, Pennsylvania Area Code 215 OL 9-7700

HUNTSVILLE, ALABAMA Holiday Office Center Suite 16 3322 Memorial Parkway Huntsville, Ala. Area Code 205 881-1515