# SYNERGISTIC PRODUCTS, INC.

SANTA ANA, CALIF. 92705 • (714) 540-7755

NEWER MACHINE Model # 1405-0003

N/c Type 1800

SPI Serial # 1049 N/c .. # 1053

110 volis 22 amps 60 ts 1 place

Multimatic
SYNERGISTIC PRODUCTS, INC. Dulling Machiel

1800 CONTROLLER

OLDERMACHIUMIS

MODEL # 1500

N/c TypE 1800-511

SPI SERIAL # 1043

NC " # 1024

115 wells GONL Stanges

1 placese.

# TABLE OF CONTENTS SPI 1800 CONTROLLER

## GENERAL DESCRIPTION

# DOCUMENTATION CONVENTIONS

# MANUAL CONTROLS

## THEORY OF OPERATION

- 1. System Clock
- 2. Input Logic
- 3. Function Registers
- 4. X & Y Functions
- 5. Motor Control
- 6. Motor Inhibit

# ADJUSTMENTS

- A. DAC Balance Procedure
- B. Servo Adjustment Procedure
- C. JOG Speed Adjustments

## PREVENTIVE MAINTENANCE

# GENERAL DESCRIPTION

The SPI 1800 is a two-axis point-to-point positioning system. The positioning is performed by closed loop servo systems using DC motors which are driven by SCR power amplifiers. The position of the device being controlled is sensed by incremental encoders which are attached to the lead screws of the machine being positioned. Some machines have been equipped with linear incremental encoders which measure the linear motion of the moving table. The motion of the moving part is measured with a resolution of .0001 inches per pulse.

The positioning system is absolute rather than incremental. That is, each positioning command is executed relative to a single 0 point rather than relative to the previous position of the machine. Incorporated into the 1800 are the capabilities to recognize, respond to and display numerous control codes which are necessary for the control of wire wrapping machines, drilling machines or I/C insertion machines. These features are the result of this controller's having been designed specifically for this type of usage.

The general logical configuration of the controller is shown in the block diagram (Fig. 1). At the top of the page are the input circuits. These circuits provide for taking information either from the paper tape reader or from the thumbwheel switches on the front panel of the controller, modifying that information and depositing it in one of the registers shown in the upper right-hand side of the diagram. Display register provides the capability to drive a 6-digit decimal display. The S register provides the capability to drive lamps used to control routing of wire in a wrapping machine. The M register provides the capability




FIG 1

to recognize M functions which are used for control of automatic spindle wrapping machines and for control of the paper tape reader. The N register is used to drive lighted bin boxes for wrapping machines. The X desired and Y desired registers are used to store the position to which it is desired to move the machine. The input control circuits consist of control flip-flops for controlling the motion of the paper tape reader, sequencing circuitry, circuitry for checking the parity of incoming data and detecting particular control characters.

At the bottom of the page is shown the servo system which may be considered the output circuitry of the controller. The current position of the machine relative to the machine zero position is carried at all times in the X actual register and the Y actual register. The X and Y encoders cause these registers to be incremented or decremented as the table moves. The comparator compares the X desired position with the X actual position, feeds the difference between the two to a digital-to-analog converter which converts the position error into a DC voltage suitable to drive an SCR power amplifier which in turn drives the DC positioning motor. The encoder is mechanically coupled into the positioning motor so that the loop is closed. An identical loop is used for the Y position.

The general sequencing of operations is as follows: The completion of an operation, or a manual function by the tool operator, generates an index pulse to the controller to cause it to initiate a cycle. The tape reader is started, then it reads in tape until an end-of-block code is detected. When the tape reader starts, the servo system is disabled. While data is being read in, it is checked for parity and routed to the proper registers. An end-of-block code is detected -- then the inputting operation is complete, the paper tape reader

is stopped and the servo system is enabled. The servo system starts to move one or both motors as necessary to decrease the difference between the actual and desired positions. When the difference has been reduced to zero, the motors are turned off and an "in position" signal is sent to the tool being controlled, which allows that tool to complete its function.

All logic for the 1800 controller, with the exception of the Digital-to-Analog converter, is mounted on a single matrix board. This is located in the processor drawer. The DAC board, plugs into J17 inside the processor drawer.

Throughout this system logic 1 (true or high) is +3.0 volts or greater, and logic 0 (false or low) is +0.6 volts or less.

## DOCUMENTATION CONVENTIONS

1800 logic is documented on approximately 120 8-1/2 x 11 drawings. Several means have been provided to assist in locating the proper drawing:

- A. An index of drawing titles has been provided (Dwg. #100).
- B. A diagram depicting the flow of information through the system is provided in Fig. 2. The drawing numbers of each major function have been noted.
- C. A block diagram showing all machine functions and the numbers of the drawings which detail each function is provided in Fig. 3.

To assist in following signals from one drawing to another, signal traceability data has been included on all drawings. A page number contained in parentheses indicates the source of the signal.

Note that in some cases, drawing numbers differ only by a dash-number, for example, 115-2. The traceability data does not contain the dash-number.

Use the index to verify that the drawing you are using is applicable to your system.

#### MANUAL CONTROLS

(a) Power (Dwg. 195, sheet 2)

Two lighted, momentary pushbutton switches are provided.

POWER OFF is pushed to drop unit power and when illuminated indicates AC power is applied to the controller but it is not powered up. POWER ON is pushed to apply system power and when illuminated indicates DC power is applied to the controller. This switch is also a unit reset; it may be pushed to reset the unit at any time. If pushed while the unit is moving, motion stops but zero is not lost.

The only way zero can be lost is to press POWER OFF (see SET ZERO, below).

- (b) MODE SELECTOR (Dwg. 195, sheet 2) four position rotary switch.

  Selects unit mode of operation.
  - (1) SLOW JOG enables machine to jog at 1.5 ipm when JOG CONTROL switch is activated (see JOG CONTROL, below).
  - (2) MANUAL Causes the Data Entry switches to be the sole source of input data.
  - (3) TAPE Causes the tape reader to be the source of input data.
  - (4) EXT Transfers operation of control functions to an external control panel.
- (c) INDEX (Dwg. 195, sheet 1) Starts system operation active only in MANUAL or TAPE mode. Push to read in data from either tape reader or manual data switches. INDEX light is on when machine is in position and off when machine is moving.
- (d) SET ZERO (Dwg. 195, sheet 1) Active in any mode but should be set in MANUAL mode. When pressed this switch causes the

- present location of the machine to become the zero point to which all X and Y coordinate data are referred.
- (e) RETURN TO ZERO (Dwg. 195, sheet 1). Active only in MANUAL mode; causes the machine to move to its zero point. The XD and YD registers are reset; this is equivalent to reading in X and Y coordinates of 0, 0.
- (f) RETURN TO LAST POINT (Dwg. 195, sheet 1) Active in MANUAL or TAPE modes. Used to return to a point after the operator has had to jog off a point (see JOG CONTROL, below).
- (g) BACKSPACE (Dwg. 195, sheet 1) Active only in tape mode; backs tape up one block each time it is pressed. No data is read in.
- (h) REWIND (Dwg. 195, sheet 1) Causes tape to rewind until beginning-of-tape character is detected. Rewind is automatically started when an end-of-tape character is detected. Unit must be in TAPE mode.
- (i) EMERGENCY STOP (Dwg. 195, sheet 1). Causes all machine motion to cease. POWER ON reset must then be pressed. Inputs from limit switches (Dwg. 148) will automatically apply a reverse drive to the limited axis, then bring up emergency stop.
- (j) JOG CONTROL (Dwg. 195, sheet 2). Active in any mode. In MANUAL or TAPE fast jog ensues (60 ipm). In SLOW JOG the rate is 1.5 ipm. When a jog switch is engaged the DAC's are held at zero and voltages are generated past them (see Dwgs. 147, 164, 165). While jogging the actual position registors follow the machine motion but the Desired Position registers are unaltered. Thus RETURN TO LAST POINT may be pressed and operation resumed.

(k) MANUAL DATA ENTRY (Dwg. 195, sheet 3)

These are two sets of thumbwheel switches. In MANUAL MODE, pressing the INDEX will cause the machine to move to the coordinates selected by these switches. The Digit Time Counter (Dwg. 183) scans these switches serially (Dwg. 187) and the data is gated into the desired registers in the same manner as tape data (Dwg. 113).

#### THEORY OF OPERATION

# (1). SYSTEM CLOCK (Dwgs. 177 and 144)

The system clock provides all necessary synchronizing and clocking signals for the system. The basic oscillator is a three-gate ring circuit which oscillates at approximately 10 MHz (Dwg. 177). The exact frequency is not critical but must be somewhere between 6 and 12 MHz. The 10 MHz is divided down to 5 MHz.

The 5 MHz signal is fed into a 5-bit serial shift register with only one flip-flop set at a time. Two 1 MHz pulse trains, CK03 and CK05, are taken from this register. The pulses are approximately 200 nanoseconds wide and there is approximately a 400 nanosecond difference between the trailing edge of CK03 and the trailing edge of CK05. These signals are fed to buffer amplifiers and distributed throughout the system.

The Control Time Counter (Dwg. 144) can also be considered part of the system clock, since it is always running and the operations it controls are always being performed (see discussion under (4b), Tachometer Input and Control Time Counter).

The Control Time Counter is a four-bit, serial shift register with only one flip-flop set at a time. All flip-flop outputs, CT1 thru CT4, are used.

(2) INPUT LOGIC (Dwgs. 104 thru 113, 149, 185)

The input logic receives all eight tape channels (Dwg. 104). Either EIA or ASCII codes may be received and are selected by the ASCII/EIA switch (S4) located on the rear panel of the processor drawer. This switch also selects odd or even parity check (Dwgs. 105, 149). Since ASCII uses even parity and EIA uses odd parity, a two-pole switch performs both functions.

Sets of X and Y coordinates and other numeric data are punched on tape in groups called blocks. Each block is terminated by an end-of-block (EOB) character. Blocks are composed of fields of numeric data. Each field is preceded by a control character. The input logic determines whether a character is a number or a control character (Dwg. 112), and decodes (i. e. provides a single line output) the characters EOB, RWSTOP (rewind stop), RWCON (rewind control or end of tape), and the control characters M, N, S, X and Y (Dwgs. 109, 110); other characters are decoded but not used. To indicate polarity of X and Y coordinates, the minus character is also decoded (Dwg. 109); in the absence of this character, a number is assumed to be positive; hence no plus character is decoded and may be omitted from the tape.

Tape tracks 1, 2, 3 and 4 contain the numeric data in Binary Coded Decimal (BCD) form. This data is not decoded but is sent unchanged to the Display, M N, S and desired input registers, each of which is enabled by its corresponding control character.

#### (3) FUNCTION REGISTERS

# (a) M Register

The M function flip-flop (Dwg. 185 ) is set by the M control character and generates clock pulses MCK, - one pulse is generated for each numeric character received. The M register (Dwg. 114 ) holds a two-digit BCD number, Most Significant Digit (MSD) first. If the M field contains more than two digits, only the last two digits will be preserved in the M register. The outputs from the M register are fed to eight relays (Dwg. 192 ) which are used to perform special display or other functions.

#### (b) N Register

The processing of the N field for energizing bin lights is almost identical to the M field processing. The N function flip-flop (Dwg. 185 ) is set by the N control character and generates clock pulses NCK; one pulse is generated for each character received. The N register (Dwg. 118 ) holds a two-digit BCD number, MSD first; thus, only the last two digits of the N field will be preserved in it. The outputs from this register drive eight relays (Dwg. 193) which are encoded to energize the bin lights.

# (c) Display Register

The display register is operated by the N field and is actually a second register for it. The N function flip-flop (Dwg. 185) generates clock pulses which are used to shift the N-field digits into the display register. This register is six digits long; each digit is represented by seven flip-flops. Each digit passes through

a BCD-to-seven-segment decoder (Dwg. 167) before entering the display register. Data enters MSD first from the Least Significant Digit (LSD) end of the register. The N control character sets this register to all zeros; thus the register is completely reset before new data starts shifting in. This makes the register automatically right justified if the N field is fewer than six characters. Each flip-flop in the register feeds a high current driver which goes to the display connector J06. This connector mates with a six digit, seven-segment mosaic indicator panel.

# (d) S Register

The S function clock (Dwg. 103) is set by the S control character; this develops a single pulse to enter the following numeric character into the S function register. The output of this single-digit, four -bit register is decoded, sent to display connector J06, and used to energize the wire route lights.

# (4) X AND Y FUNCTIONS

(a) Input, Conversion, and Desired Registers

The X and Y fields are each processed in an identical manner.

Data are read from the tape one digit at a time, MSD first. If the Dial Offset Switch (DOS) on the rear panel is on, the data from the manual entry switches is added to each coordinate after it is read from the tape.

Four registers are involved:

Input Register (Dwg. 121),

Conversion Register (Dwg. 122, 123, 124),

X Desired Register (XD) (Dwg. 127, 128, 131),

Y Desired Register (YD) (Dwg. 129, 130, 131).

Although tape and manual data are in BCD, all internal data processing is in binary. Therefore, BCD to binary conversion is necessary. This conversion is controlled by the Digit Time

Counter (Dwg. 186 ) a six-bit flip-flop ring (DT1-DT6) that indicates which digit is being processed. It is usually held to all zeros. An X or Y control character sets DT1; at the same time, a sign flip-flop, IR5,(Dwg. 126 ) is set to indicate PLUS. If the next character on tape is a minus sign, IR5 is reset to indicate MINUS: if the character following the X or Y control character is a plus sign or a number character (the plus sign may be omitted) the flip-flop remains set. When a number character is received, a modulo 24 binary counter (the Bit Time Counter, Dwg. 184 ) is allowed to count. When it reaches 24

(BC24) it causes DT1 to be reset and DT2 to be set. This condition remains static until the next digit is read (approximately 6.6 milliseconds for a typical tape reader), at which time BC24 is again allowed to count. Al count 24, DT2 is reset and DT3 is set. This repeats down through DT6. At count 24 of DT6, the entire X or Y coordinate field has been processed. The X- or Y- Data Bits Tape flip-flop (Dwg. 186), which was set by the X or Y control character, is reset by the combination of DT6 and BC 24. This combination also sets the X- or Y- Dials Time flip-flop (Dwg. 186 ) and causes the Bit and Digit Time counters to repeat the above process. This time the appropriate X or Y set of manual data switches is read. The DT ring counts but does not stop at each BC24 count, since the data from all switches are immediately available. If the DOS switch is on, the data will be read as indicated by the switch settings; if DOS is off the logic will go through the motions and read as if all switches were set to zero.

The BCD to binary conversion is done serially, MSD first. As a number character is read, it is parallel loaded into the Input Register (IR) (Dwg. 121). IR is a four-bit parallel-in, serial-out shift register. The Bit Time Counter (Dwg. 184) causes IR and the Conversion Register (CR) (Dwg.124, 123, 122) to start shifting (CR is initially set to zero). The output of IR (IR1) is added to the output of CR (CR01) in a serial binary adder (Dwg. 125). Each BCD digit from IR is added to the binary output of CR as though it

were a binary number. The answer is multiplied by ten in binary by passing the output of the adder through a three-bit shift register. Each flip-flop of the register delays the data by one clock time. It is the property of serial binary numbers that a stage of delay doubles the number; hence the output of the first stage (2X) is two times the sum and the output of the third stage (8X) is eight times the sum. The terms 2X and 8X are added together in a second serial binary adder. The output of this adder (SUM2) is then ten times the output of the first adder and is shifted back into CR. When the second BCD character is received, the above process is repeated and continues until DT6 time. At DT6 time the output of the first adder is gated to the input of the X Desired Register (XD), (Dwg. 127, 128, 131), if an X field is being processed, or to the Y Desired Register (YD) if a Y field is being processed (Dwg. 129, 130, 131).

When the input data contains a MINUS sign, the first adder's input becomes the inverse of IR (IR) plus 1. This produces the two's complement of the input number and is the way negative binary numbers are processed in this system.

If trailing zeros are omitted from a tape coordinate (which is permitted) it is detected by the recognition of a control character before DT6 has been processed. When this happens the Digit Time and Bit Time counters continue to cycle without stopping until BC24 count of DT6. The worst case is five trailing zeros

omitted and the total time to cycle out is 120 microseconds while the time to read one character from tape is approximately 6.6 milliseconds. Therefore, no data will be lost. Once XD and YD are loaded, they cannot be altered until a new data block is read.

(b) Tachometer Input and Control Time Counter

Signal pulses from optical tachometers (encoders, actually)

mounted on the X and Y motor shafts are sent to the Logic Section

and synchronized to the system clock (Dwg. 119, 120). Four possible

control pulses are generated: JXUP, JXDN, JYUP and JYDN.

These pulses are sent to the Motor Control and Power Amplifier

circuits (Dwgs. 115, 116,117) to provide a motor feedback voltage

proportional to machine velocity. These pulses are also synchronized

and gated with four Control Time Counter signals (Dwg. 143).

These timing signals, CT1 thru CT4, are generated by a cyclic

modulo 4 counter, and select which of four operations are to be

performed by the actual position registers (XA and YA) and their

associated summing logic:

CT1: XA is incremented + 1 if JXUP is true,

- 1 if JXDN is true,

0 if JXUP and JXDN
 are both false or both
 true.

CT2: YA is incremented + 1 if JXUP is true,

- 1 if JXDN is true,

0 is JXUP and JXDN are both false or both true.

CT3:  $XD-XA = \Delta X$  is calculated.

CT4:  $YD-YA = \Delta Y$  is calculated.

(c) Actual Registers and Adder Logic

The XA and YA registers (Dwgs. 137 thru 142) are each 24 bits long (23 magnitude bits and one sign bit). These registers are gated into the B- inputs of a 24-bit parallel binary adder/subtractor (Dwgs. 137 thru 142). The outputs of the desired registers are gated with CT3 and CT4 (Dwgs. 132 thru 135) and gated into the A- inputs of the adder, along with the DOWN pulses from the tachometers (AGG Dwg. 143). The UP pulses from the tachometers are fed to the carry input of the adder (Dwg. 142). Since the Control Time Counter is always running, the operations controlled by it (Para. (b) above) are always current. At CT3 and CT4 the output of the parallel adder represents the values of  $\Delta X$  and  $\Delta Y$  respectively, which indicate the distance left to travel to the desired stopping point.

(d) Digital-To-Analog Converters

One Digital-to-Analog Converter (DAC) is used for each axis

(Dwgs. 155 thru 165). The AX and AY values are each 24-bit

numbers but only ten bits are fed to the DAC's: 1 thru 5 (LSBs)

9 thru 12 (MSBs) and the 24th, or sign bit.

When the distance to travel is between 0.0031 and 0.4095 inch, the MSB's decrement each 0.0256 inch of travel while the LSB's are held full scale. From 0.0031 inch to the stopping point, the

LSB's decrement each 0.0001 inch of travel. Treating the DAC's in this fashion generates a non-linear decelleration profile. If the machine overshoots the stopping point, the \( \Delta \text{value will change} \) signs, causing the sign of the DAC to change, resulting in a reverse motor drive signal.

Due to the non-linear input and the fact that there are various manually controlled digital inputs to the system, the DAC's require some gating and timing (Dwgs. 147, 153, 154, 175) to control these functions. The MSB's and LSB's are clocked into the DAC's separately (Dwg. 154).

A ten-bit input storage register is used on each DAC (Dwgs. 155 thru 158). The output of each register is fed to a precision summing network through transistor switches. These switches are NPN transistors and are deliberately installed upside-down (i. e. emitter to + and collector grounded). This results in a very low gain factor (2 to 3-1/2 typically) but also a very low saturation voltage (60 millivolts or less). This greatly reduces errors caused by differences in saturation voltages between transistors. Since the summing points are fed to high input impedance amplifiers, gain of switching stages is not important here.

# (5) MOTOR CONTROL

The DAC outputs are fed to motor control amplifier circuits (Dwg. 115; one required for each axis) where the DAC signal is combined with the tachometer pulses to provide the proper firing angle to SCR's on the power amplifiers (Dwg. 116 & 117). A Motor Inhibit Circuit (Dwg. 148, 199) is provided to prevent machine motion under specified conditions: e.g. if the spindle is down and data is being shifted in.

# (6) MOTOR INHIBIT

In order to prevent an annoying audible buzz from the motors due to the power line frequency supplied to them by the SCR drive, the motors are turned off whenever they are not needed. This is referred to as inhibiting the motors. (Refer to Page 148). The two signals leaving the right of the page, INHY and INHX, inhibit the motors at all times, except when the move flop is set, which causes the servo to be enabled and the signal DACZ is not true, which means that the servo system has not gotten into position, or a jog switch right - left or in-out has been depressed or the signal AMS is true. AMS stands for any microswitch but could be better expressed as any limit switch. These are the three conditions which can keep the motors on. Note that depressing the leftright jog switch enables only the X motor and does not disturb the inhibit signal which is applied to the Y motor. Following these two signals to Page 199, they are further processed. S5 shown on this page and physically located at the back of the processor is labeled "inhibit override". Actuating this switch completely defeats the inhibiting system and causes the servo to remain active at all times. The input signal to the OR gates located at 14R called Z-SAFE comes indirectly from the machine being controlled by the processor. This signal inhibits both motors whenever the Z axis, normally the up and down spindle motion of a tool, is such that it would not be safe for the table to move. In the case of most machines, the Z axis is not safe at any time the tool is not in the uppermost position. Also, on Page 199, the RC network, comprised of C14 and R105 and the two gates and one transistor associated with those

components, provide a signal stretching network which delays the application of the inhibit signal for approximately 100 milliseconds without delaying the removal of the inhibit signal. Delay is necessary because the signal DACZ goes true as soon as the servo system comes into the error zone. It is necessary to delay the application of the inhibit signal a sufficient length of time to allow the servo system to completely settle within the error zone before inhibit is applied.

It should be noted that should the inhibit signal be applied to the motors while the table is moving by the failure of the Z safe signal, no dynamic breaking is applied to the motors and the table will coast to a stop.

#### ADJUSTMENTS

This procedure is applicable to controllers using motor amp board, Part

Number

#### A. DAC BALANCING PROCEDURE

This is a simple procedure which is used to correct small drifts which occur within the DAC system.

- 1. Turn on system, allow to warm up for 1/2 hour, preferably longer. Open the back door, over-ride the interlock by pulling on the plunger.
- 2. Place the INHIBIT OVERRIDE switch UP.
- 3. Jog the machine to the approximate center of the available travel.
- 4. Adjust the X DAC BALANCE and Y DAC BALANCE potentiometers which are located on the DAC board and identified by screening on the chassis for either of the following balance criteria:
  - Deserving the table or the head is not good enough. If necessary, use two people, one observing the pulley, and the other turning the pot. If the pot can be turned more than a few degrees between the points where the motor moves in opposite directions, set the pot approximately half way between these two points. If you can turn the pot 1/2 turn without the motor moving, something is wrong.

- b. Balance indicated by zero volts on a meter connected
  between the RED and BLACK test jacks (current test, ground)
  on the back of the motor drive chassis (not on DAC board).

  Any meter with a sensitivity of approximately 1 volt full
  scale will do fine. It need not be a zero-center meter,
  although that is a convenience. The procedure is straight
  forward. Adjust the appropriate balance pot for zero reading
  on the meter. With some controllers, there is a tendency for
  the meter to "pop" from one polarity to the other, rather
  than passing through zero smoothly.
- 5. When both axes have been balanced, place the INHIBIT OVERRIDE switch in the DOWN position and verify proper operation of the servo by setting move distance into the X and Y manual entry switches and exercising the servo by use of the INDEX and RETURN to ZERO switches. Exercise the servo with moves of 10 inches, 1 inch, 0.1 inch, 0.01 inch. The servo should settle smoothly without buzzing, hunting or hesitation for all moves. The servo is "in position" when the light in the index switch comes on.

#### B. SERVO ADJUSTMENT PROCEDURE

This procedure adjusts the balance, overlap and speed of the servo system. It is intended to be used whenever parts are replaced on the DAC board or the motor control boards or the power supplies associated with either, and as a PM procedure, approximately monthly.

- 1. Open the back door, defeat the interlock, turn the system on and allow it to warm up for at least 1/2 hour, preferably longer.
- 2. Place the INHIBIT OVERRIDE switch UP.
- 3. Jog the machine to the approximate center of its available travel.
- 4. Open the MOTOR ARMATURE BREAKERS, CB 2 and CB 5.
- 5. Connect a sensitive meter between the RED and BLACK test points on the DAC board (REPEAT -- DAC BOARD). A voltmeter with a full scale indication of 0.6 volts or a current 250 micro amps

  FS or less will be suitable.
- 6. Adjust the X DAC BALANCE or Y DAC BALANCE pot on the DAC board near the center to bring the meter to zero. Balance both X and Y using the appropriate test points and pot.
- 7. If the meter will not quite zero, back the pot away from the end of its travel by two turns and leave it there. Some DAC boards gradually acquire so much offset that they will not balance. This can be compensated for in the motor amp board, however.
- 8. Connect a dual trace oscilloscope using 10 to 1 probes to the YELLOW BALANCE/OVERLAP test jacks for the X axis. Ground the scope to the black test jack (Fig. 1). Do not use 3 rd wire ground on scope. Adjust the scope for a presentation like Fig. 3; use line synchronization. If unable to get at least one ramp,

- as shown in Fig. 3, verify that INHIBIT OVERRIDE is up and momentarily depress any jog switch.
- 9. Adjust the balance potentiometer on the motor control board (Fig. 1) to bring the firing time on the two waveforms into coincidence.
- 10. Adjust the OVERLAP potentiometer (Fig. 1) for overlap = 0.4 millisecond ± 0.1 millisecond. If necessary, touch up the balance.
- 11. Repeat steps 8 through 10 for the Y axis.
- 12. Return the inhibit override switch to the down position. Return the circuit breakers to their normal position.
- 13. Exercise the system in one axis at a time, using alternate INDEX and RETURN'TO ZERO commands and 16 inch moves. The move should be completed within 3 seconds. The overshoot should not exceed 0.1 inch. Note that this is 1/2 revolution of the motor pulley.
- 14. If the speed is not satisfactory, it may be adjusted using the VELOCITY FEEDBACK pot (Fig. 1). This adjustment is a compromise between speed and overshoot. If the VELOCITY FEEDBACK is moved, check steps 9 and 10. This completes the adjustment procedure.

# C. JOG SPEED ADJUSTMENTS


The machine provides two independent jog speeds; FAST JOG with the rotary selectro switch in MANUAL, SLOW JOG with the selector switch in SLOW JOG.

These speeds may be adjusted over a wide range to suit the needs or preferences of the individual user. There are a total of 8 potentiometers on the DAC board which control these speeds. Each axis, speed, direction has its own pot.

- X slow -
- X slow +
- X fast -
- X fast +
- Y slow -
- Y slow +
- Y fast -
- Y fast +

Adjustment of the jog speeds will not affect the servo positioning speeds.

Adjustment of the servo positioning speed will affect the jog speeds.



# PREVENTIVE MAINTENANCE

The 1800 controller requires little preventive maintenance. It is our experience however, that regular performance of the following checks and adjustments will materially reduce the occurrence of field failures.

# Weekly perform the following:


- Perform the DAC balancing procedures. Note that this procedure should not be performed until the machine has warmed up for 1/2 hr., preferably longer.
- 2. While the rear door is open, check to see that the fans in the bottom of the controller and the fan which blows air on the processor logic panel and the fan which cools the motor control drawer are all operating.
- 3. Check front panel control switches for normal operation.
- 4. Check lamps and indicators for normal operation.

# Monthly:

1. Check the five volt logic supply voltage on the logic panel. Use a meter with a working accuracy of 1% at 5 volts on the scale which you are using. The supply voltage is required to be 5.0 volts ± 0.1 volt. If the voltage is found to be outside of this range, before adjusting the power supply, check the connections

in the supply lines to the logic panel: The screws in the terminal boards in the bottom of the processor, the connectors at the back of the processor, and the screws on the terminal board of the power supply. A surprising number of field calls have resulted from improper supply voltages due to poor connections at these points. If you don't find the problem at one of these points, then readjust the power supply voltage to provide 5 volts at the logic panel. Approximately 5.4 volts will be required at the power supply to provide 5.0 volts at the logic panel. There is approximately 0.2 volt drop in the supply line to the logic panel and the same in the return line.

- 2. While the logic drawer is open, inspect the IC's for excessive dirt build-up underneath the fan. If significant dirt is present, remove it with a soft brush and a vacuum cleaner.
- 3. With a soft brush, clean the dirt from around the read head of the paper tape reader.
- 4. Perform the Servo Adjustment Procedure.



# Toggle Switches

All switches, except ASC11/E1A, are active in the up position.
ASC11/E1A is active in both positions.




Fig. 2

PROCESSOR DRAWER - REAR VIEW








Fig. 3








_				*		
1750-0101	(16)	1800-0159	ACTUAL REGISTER AND ADDER BITS 13-16	0-0177	SYSTEM CLOCK GENERATION	planting in the second
0102	I'm.	0140	ACTUAL REGISTER AND ADDER BITS 9-12	0178	MANUAL SWITCH INFUT NO. 1	
0103	S FUNCTION REGISTER WIRE ROUTE DISPLAY	0141	ACTUAL REGISTER AND ADDER BITS 5-8	0179	MANUAL SWITCH INPUT NO. 2	
6104	READER TRACK GATING AND ASCIILEIA CONV.	. 0142	ACTUAL REGISTER AND ADDER BITS 1-4	0180	MANUAL SWITCH INPUT NO. 3	
0105	READER TRACK PARITY DECOCER	0143	TACH PULSE SYNCHONIZATION	0181	INDEX, AXIS SAFE, SSI AND SS2 F/F	
0106	TRANSLATOR NO. 1-3 TO 1 OUT OF 8	0144	CONTROL TIME COUNTER	0182	RESET PULSE GENERATION	
0107	TRANSLATOR NO. 2.3 TO 1 OUT OF 8	0145	ACTUAL REGISTER CLOCKING	0183	DIGIT TIME COUNTER	
0108	CONTROL CHARACTER DECOLER NO. 1	0146	ACTUAL REGISTER CLEAR	0184	BIT TIME COUNTER	
0100	CONTROL CHARACTER DECOUER NO. 2	0147	JOG SWITCH GATING	0185	M AND N FUNCTION AND READER STROBE F/F	
0110	CONTROL CHARACTER DECODER NO. 3	0148	JOG OR MOVE SYNC, AND MOTOR INHIBIT	0186	DIALS AND TAPE DATA TIME F/F	
0111	TAPE READER DATA TRACK VERIFICATION	0149	START MOVE OR PARITY FAILURE	0187	DIALS INTERROCATION GATING	
0112	ALPHA AND NUMERIC CHARACTER DECODER	0150	INDEX, REWIND AND STOP INDICATOR DRIVERS	0188	RETURN TO REF. AND STOP F/F SWITCH SING	Œ
0113	TRANSLATOR NO. 3-9 TO 1 OUT OF 4	0151	COARSE RANGE DECODER	0189	TEST AND XY STOPPED F/F	
0114	M FUNCTION REGISTER	0152	FINE RANGE DECODER	0190	SHIFT F/F AND LOAD	
0115	MOTOR CONTROL (2 SHEETS)	0153	DAC INPUT DIRECT SET_RESET ENABLE	0191	READER CONTROL T/F	
0116-2	X-AXIS MTR. DR.	0154	DAC INPUT CLOCKING	0192	PROCESSOR M RELAYS	
0117-2	Y_AXIS MTR. DR.	0155	DAC INPUT REGISTER X SIGN AND MSB	0193	PROCESSOR N RELAYS	
orra	TORESTON REGISTER	0156	DAC IMPUT REGISTER X LSB	0194	FOWER CONTROL	
6119	TACH PULSE DECODING X.AXIS	0157	DAC INPUT REGISTER Y SIGN AND MSB	0195	CONTROL PANEL (3 SHEETS)	
0150	TACH POLSE NECODING YEARTS	0158	DAC INPUT REGISTER Y LSB	0196	(NOT USED)	
0121	4-BIY DESIRED THEOT REGISTER	0159	DAC INPUT ZERO DECODER	0197	(NOT USED)	
0122	CONVERSION REGISTER BITS 1-4	0160	DAC REFERENCE VOLTAGES .	0198	(NOT USED)	
0153	CONVERSION REGISTER BITS 5-14	0161	DAC NEGATIVE REFERENCE SUPPLY	0199	NOTOR INHIBIT DELAY	
0124	CONVERSION REGISTER BITS 15-24	0152	DAC X AXIS AMPLIFIER			
0125	BCD TO BLINARY AND DESTRED ARTHHETIC	0163	DAC Y AXIS AMPLIFIER			
0126	URSINFO REGISTER SIGN	0164	DAC X AXIS JOG CIRCUIT			
0127	X-DESTREO PEGISTER BITS 15-24	0165	DAC Y AXIS JOG CIRCUIT	<del> </del>		
0128	X_DESTRED REGISTER BITS 5-14	0166	(NOT USED)			
0129	Y-DESTRED REGISTER BITS 15-24	0167	BCD TO 7 SECHENT DECODER			
0130	Y-DESTHED REGISTER BITS 5-14	0168	DISPLAY REGISTER SEGMENT 3			
0131	X AND Y LESTRED REGISTER BITS 1-4	0169	DISPLAY REGISTER SEGMENT 4			
0132	DESIRED REGISTER OUTPUT CATING BITS 1-6	0170	DISPLAY REGISTER SEGMENT 5			
0133	DESTREO PEGISTER OUTPUT CATING BITS 7-12	0171	DISPLAY REGISTER SEGMENT 6			
0134	DESTRED REGISTER OUTPUT GATING BITS 13-18	0172	DISPLAY REGISTER SEGMENT 7			
0135	DESTRED REGISTER OUTPUT CATING BITS 19-24	0173	DISPLAY REGISTER SEGMENT 8	<del></del>		
0136	X AND Y DESIRED REGISTER CLOCKING	0174	DISPLAY REGISTER SEGMENT 9	<u> </u>		
	ACTUAL REGISTER AND ADDER BITS 21-24	0175	DAC INPUT DIRECT SET_RESET CATING			
0138	ACTUAL REGISTER AND ADDER BITS 17-20	0176	TIME DELAY COUNTER			
						1
		1			REF.	DESCRIPTION GIV. PER PART NUMBER ASSY. MACH.
•					THIS DOCUMENT CO	NTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED ON THANSPORTED TO
				<b>I</b> ———	TOLERANCES UNLES	OR DISCLOSED TO DITIENS ON DEED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT MISSION OF EVENERALISTIC PRODUCTS.
	· ·	•			INTERNATE SERVICE CONTROL IN THE CON	Chickey of Cavitron Corporation
					CONCENTAICITY AND CONCENTAICITY AND CO.	DATE TITLE
					AEMOVE BURRS AN BREAK ALL SHARP EUR	
			<u> </u>	NEXT ASSY	USED ON	11160-0100-
IL/73 DIETE	PRICHPORT DURAFFRINT MONTHS			•		



















5	IGNAL TR	ACEABILITY
SIGNAL	SOURCE	ADDITIONAL LOADS
BDOOL	104	105, 113
BDOOT	104	105
BD002	104	105, 113
BD004	104	105
80008	104	105, 113
BD00B	104	105
BDXXO		108, 109,0111
BDXXOA		112
BOXXI		108, 109, 112
BDXXIA		110
BDXX2		109, 110
BOXX3	-	108, 110
BOXX4	. —	-109, 110
BDXX5		108, 109
BDXX6		109, 110
BDXX7		109, 110, 111


NOTES: UNIESS OTHERWISE SPECIFIED.


- L 1.C.'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.
- 2. BDOO1, BDOO2 & BDOO4 REPRESENT TAPE READER TRACKS 1, 2, AND 3 RESPECTIVELY


		MEP.	DESCRIPTION	ASS.	GTY. PT 4 MACH.	PART NUMBER
		DTHER DOCUMENT		A ULCO FOR		BE REPRODUCED OR TRANSFERRED TO ING OR ANY CINER PURPOSE WITHOUT
		TOLEMANCES UNL		17 mg, 21	A	SYNERGISTIC PRODUCTS, INC.
	•	1.00 1.005 10	OFE CHECKED	DATE		A Subridiary of Cavitron Corporation 1902 McGray, Santa Ana, Culifornia
		OF BOUND T.I R.		DATE		C DIAGRAM -
		PREAK ALL SHAAP				NSLATOR NO. 1
		FINISH			SCALE -	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
NEXT ASSY	USED ON		1		I	1 1500-0106











NOTE: UNLESS OTHERWISE SPECIFIED 1. I.C.'S ARE BIGNETICS UTILOGIC II. SP SERIES OR EQUIV.

, ner.	O.E.	SCHIPTION	ASSY.	MACH.	FAR: ROMBER
OTHER DOCUM	KENTS OR	INS PROPRIETARY INFORM DISCLOSED TO OTHERS DR LION OF SYNERGISTIC PRO	USED FO	MCH SHALL R MANUPAC	NOT BE REPRODUCED ON TRANSFERRED T TURING OR ANY OTHER PURPOSE WITHOU
TOLERANCES OTHERWISE SI	OWELL TO E	W Keller	:/ .DA		SYNERGISTIC PRODUCTS, IN


OTHERWISE SPECIFIED


.KX .KXX ANDLE

1.61 J.605 10-20\*

CONCENTRICITY AND OUT

OF ROUND T.I.R., 605 A Substitute of Cavitron Corporation 1907 M. Gelv, Santa Ane, California LOBIC DIACHAM-CONTROL CHARACTER DECODER NO 2 REMOVE BURRS AND 1800-0109 NEXT ASSY USED ON







STMSCL	सुराय है था, उस		DATE & ALTER V
	REV PER ECO 412	209/2	

S	IGNAL TRA	ACEABILITY
SIGNAL	SOURCE	ADDITIONAL LOADS
ACON		0
ASCSTB	108	109
BCON		0
BDXXIA	106	
BDX2X	106	· 109
воххз	106	108
BDXX4	106	109
BDXX6	106	109
BDXX7	106	109, 111
BDXOXA	107	0
BDX2X	107	109
BDX2XA	107	115 .
BDX3X	107 -	109
BDX6X	107	112
CCON		0
EIASTB	108	109
SCON		103, 112
TCON		112
WCON ·		0
ZCON		112

1. I.C.'S ARE BIGNETICS UTILOGIC II, BP BERIES OR EQUIV.

' <b>~</b>							
		ner.	D	ESCRIPTION	ASSY.	PER MACH	PANT NUMBER
		OTH	ER DOCUMENTS OR		USED FOR		L NOT BE REPRODUCED OR TRANSPERRED TO ACTURING OR ANY OTHER PURPOSE WITHOUT
		01111	ERANCES UNLESS ERWISE SPECIFIED X XXX ANGLE 1 1.000 1 0 30° ENTPICITY AND OUT	CHECKED CHECKED	DATE	⁄ اد	SYNERGISTIC PRODUCTS, INC. A Subsidiery of Cevitron Corporation 1902 McGew. Santa Ana, California
**		NEM.	ROUND T.L.R., 695 HOVE BURRS AND RALLSHARP EDGES	MATERIAL		1111.8	LOGIC DIACHAM— CONTROL CHARACTER DECODER NO 3
NEXT ASSY	USED ON	PINIE				KALI	1800-0110







s	SIGNAL TRACEABILITY											
SIGNAL	SOURCE	ADDITIONAL LOADS										
BOXXO	106	108, 109										
BOXX7	106	109, 110										
вохох	107	108, 109, 112										
BDX7X	. 107	112										
BDI28	104	105										
BD128	104	105										
BD064	104	105, 108										
80064	104	105, 108, 112										
ENAB		185										
RSPK	185	1760										
RUN	191	176, 185										
TAPEA	189	191 .										
SPKER		149										

NOTE: UNLESS OTHERWISE SPECIFIED

- I. CAPACITORS ARE RATED IN MICROFARADS 20% AND ARE 100 VOLTS
- 2. RESISTORS ARE RATED IN OHMS ±5% AND ARE 1/4 WATT
- 3. I.C.'S ARE BIGNETICS UTILOGIC II, SP. SERIES OR EQUIV.

	• .						
•		MEP.	pt	SCRIPTION	P1 P	ATY FIR VACH.	PART HUMBER
		ОТИ	ER DECUMENTS OR		USED FOR		E REPRODUCED OR TRANSFERRED TO TOURTW JECARD REPORT VAR NO DI
		T OTHI	BJONA XXX.	MONTA GUEL CHECKED	6-25% eat.	1	YNERGISTIC PRODUCTS, INC. A Subudiary of Contron Corporation 1802 McCine, Sonte Are, Childenia
		ACM	IQVE BURRS AND CALL SHARP EUGES	MAYERIAL .		TAP TRA	IC CHASHAM - E READER DATA CK VERIFICATION
NEXT ASSY	USED ON	-				***	1110-0081






NEXT ASSY


, S	SIGNAL TRACEABILITY											
SIGNAL	SOURCE	ADDITIONAL LOADS										
воххо	106	108, 109										
BDXX7	106	109, 110										
врхох	107	108, 109, 112										
BDX7X	. 107	112										
BDI28	104	105										
BDI28	104	105										
BD0G4	104	105, 108										
80064	104	.105, 108, 112										
ENAB		185										
RSPK	185	176										
RUN	191	176, 185										
TAPEA	189 .	191										
SPKER		149										


## NOTE: UNLESS OTHERWISE SPECIFIED


- 1. CAPACITORS ARE RATED IN MICROFARADS 20% AND ARE 100 VOLTS
- 2. RESISTORS ARE RATED IN OHMS ±5% AND ARE I/4 WATT
- 3. I.C.'S ARE SIGNETICS UTILOGIC II, 1 COM SP SERIES OR EQUIV.


	REP.	0	ESCAIPTION	ASSY.	MACH.	PART NUMBER	
,	OTH	ER DOCUMENTS OR		USED FO		LL NOT BE REPRODUCED OR TRANSPERSED TO PACTURING OR ABY OTHER PURPOSE WITHOUT	
	0,14 (X. 0,1	3.10MA NRK. 1	MONTA GUE	6-233. 0A	_1 /	SYNERGISTIC PRODUCTS, INC. A Subudiary of Cavition Corporation 1902 Median, Smith Ana, California	
	CONC	INTRICITY AND OUT	APPROVED	DAT	1111.1		
	BREAL	GVE BURRS AND ALLSHARF EDGES	MATERIAL		1	TAPE READER DATA	
USED ON	PIMISI				144.5	1800-01112	














































NOTE UNLESS OTHERWISE SPECIFIED

1. IC'S ARE SIGNETICS UTILOGIC II, SP
SERIES OR EQUIV.

		ner.	Di	SCRIPTION	ASSY.	GTY. FLP MACH		PAR	T PUMBER		]
	,	OTH	ER DOCUMENTS OR	INS PROPRIETARY INFORMA DISCLOSED TO OTHERS OR I SION OF SYNERGISTIC PROD	ILEO FOR						
		OTH IX	ERWISE SPECIFIED  BLOOM TOTAL  TOTAL	CHECKED CHECKED	7~47/	1 /	/ A . A	Subsid ary	of Cavitron Cores, Senta Are,	poration	
		HE!	ENTRICITY AND OUT ROUND TIR., 1885 WOVE BURRS AND KALLSHARP EDGES	MATERIAL	6A11	******	LOGI 4 B	C DIAG	HAM -		
S NEXT ASSY	USED ON	FINIS	*			SEALS		31.	300-0	121	Α






NOTES: UNLESS OTHERWISE SPECIFIED.

1. IC'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.

•		REP.	DESCRIPTION	PER I	OTV. ICR MACH.	PART NUMBER		
		DTHER DOCU	THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OF TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSES TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE MISHOUT PRIOR MISTITES PERMISSION OF STREAMSTEE FOR DISCLOSES.					
				7-17-71		SYNERGISTIC PRODUCTS, INC. A Subsidiary of Cavitron Corporation		
		CONCENTRICIT OF ROUND T	YAND OUT APPROVED	DATI	<u></u>	1902 NeGaw, Santa Anu, Galiforna OGIC DIAGRAM =		
		BREAK ALLSH				NVERSION REGISTER		
NEXT ASSY	USED ON	PINISH			BEALE	1800-0122		

6-76 BIETERICH-POST CLEARPHINT MINIS




3 CRO6 14

BZIA

29F

►CRO5 122

► CRO5 122



NOTE: UNLESS OTHERWISE SPECIFIED 1. IC'S ARE SIGNETICS UTILOGIC IT, SP SERIES OR EQUIV.

		HEF.	DESCRIPTION		PT H	PART NUMBER	
		OTHER	CUMENT CONTAINS PROPRIETARY I DOCUMENTS OR DISCLOSED TO OTH RITTEN PERMISSION OF SYNERUIST	EP3 OR USFD FOR	M SHALL NO MANUPACTI	OT BE REPRODUCED OR TRANSPERRED TO URING OR ANY DINTR PURPOSE WITHOUT	
		OTHERW	NCES UNLESS BY A CLECKED CHECKED CHECKED	DATE	1/	SYNERGISTIC PRODUCTS, INC. A Subsidiary of Cariffon Corporation	
			CITY AND OUT APPROVED	DATE	1902 by Gen, Santa Ana, California		
			L SURRE AND MATERIAL LSMAPP EDGES		CC!	NVERSICN MEGISTER 'S 5-14	
NEXT ASSY	USED ON	PINISH			MALE	1800-0123	

12 CR09 7

9 321A 1

24F

9 521A I

23F


3 CRO8 14

321A


24 F

12 CR07 7

9 29F




- CRIS 123




NOTE: UNLESS OTHERWISE SPECIFIED

- 1. 7404N ARE SIGNETICS TTL OR EQUIV.
- 2. 321A & 356A ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV

			AEF.	DC	SCRIPTION	PYR ASSY.	MACH.	PAR' NUMBER
			074	ER DOCUMENTS OR		USED FOR		ALL NOT BE REPRODUCED OR TRANSPERRED TO FACLURING OR ANY DIMER PUPPOSE WITHOUT
Γ				EMANCES UNI ESS	"Collin	DAT	1	SYNERGISTIC PRODUCTS, INC.
			i	X .XXX ANGLE	CHECKED	DAT	3/	A Sub-diery of Ceritron Corporation 1002 No Gaily, Santa Ana, California
			CONC	ENTRICITY AT DOUT	APPROVED	DAT	1	
				MOVE BURRS AND	MATERIAL		7	୍ଷ୍ଟ୍ରେପ୍ ଅକ୍ତ୍ୟନ୍ତ ପୁରୁଷ୍ଟନ୍ତୁ ପୁରୁ କଥିବାହ୍ୟନ
			711118	-			SCAL	1 DWG 7
•	NEXT ASSY	USED ON					1_	- 10 1c0-0!24 1 1






NEX'T ASSY

REMOVE BURPS AND

USED ON

A Subsidiary of Centron Connection
1907 Metros, Santa Ass, Celefornia
LOGIC OFFICE ARA
DESIRE\* TEGISTER
SIGN

1:00-0126





NOTE: UNLESS OTHERWISE SPECIFIED

1. IC'S ARE SIGNETICS UTILOGIC II: SP SERIES
OR EQUIV.

		•	REP.	DESCRIPTION		PACH.	PART NUMBER
	DRILLING N	MACHINE	0140		THERS OR USED FOR I		T SE PEPRODUCTO OR TRANSPERED TO RING OR ANY OTHER PURPOSE WITHOUT
			CONCE	ERANCPS UNLESS  I. REVA ANOLE  I. Z. OOS 10-10* INTRICITY AND DUT  APPROVED  OUND T.1.0009	DATE DATE		SYNERGISTIC PRODUCTS, INC. A Sub-idury of Certorin Cerporotion 1912 McGov, Santa Ana, California 1G RA M
ŀ	NEST ABOV	Volto ON		OVE BURRS AND I ALL SHARP SHOPS		7.3	REGISTER

AS. FFF 4-2713







NOTE: UNLESS OTHERWISE SPECIFIED

1. IC'S ARE SIGNETICS UTILOGIC II
SP SERIES OR EQUIVALENT

			467,	DI	ESCRIPTION	ASSY.	PER MACH	PANT NUMBER
			1000	ER DOCUMENTS OR	INS PROPRIETARY INFO DISCLOSED TO OTHER SION OF SYMERGISTIC P	OR 1/10 PO	CH THAI	L NOT BE REPRUDUCED IN TRANSFERRED 19 ACTURING OR KNY DIMER PURPISE RITHOUT
Γ	T			LAWISE SPECIFIED	"Kchen	I APP T		SYNERGISTIC PRODUCTS, INC.
				# .KRE ANGLE	CHECKED	DAT		A Subsidiary of Certifon Corporation
Г		····	CONC	ENTRICITY AND OUT	APPROVED	DAI	1174	. 1902 McGare, Senta Aria, Cal forme
Г				ADVE BURRE AND K ALL SHARP EDGES	MATERIAL		7	· Kinggog PERSTER
			FINID				FEAL	3174
$\overline{}$	NEXT ASSY	USED ON	<b>一</b>					1900-017







NOTE: UNLESS OTHERWISE SPECIFIED

1. FLIP-FLOPS ARE LU32IA OR EQUY.

	•	REF.	D	ESCRIPTION	ASSV.	MACH.	PART NUMBER	1
		014	CR DOCUMENTS OR		DA LIZE FOR		LE NOT BE REPRODUCED OR THUSPER BLOOT TO PROTURING OR ANY DYNER PURPOSE WITHOUT	
			ERANCES UNLESS	"Kelan	14 400 7		SYNERGISTIC PRODUCTS, INC.	1
		1.0	T.AUS TO'S	CHECKED	DAT	3/	A Subsidiery of Cariffon Corporation 1907 McGam, Santa Ana, Califforna	
			ENTRICITY AND OUT	APPROVED	DAT	1174		ł
1.0			KOVE BURRS AND	MATERIAL		7	x ให้เกรียนที่ มีกระห	
1.		FINIS	H			ICALI	Pre* 1: 00 1= 00'8	1
 NEXT ASSY	USCD ON	مسية		1			1=1111	P







NOTE: UNLESS OTHERWISE SPECIFIED

L FLIP-FLOPS ARE LU32IA OR EQUIV.

		ACF.	DESCRIPTION	I FER !	VACH.	PART NUMBER
		OTHER DOCUM		5 00 USED FOR		CT DERRESSÉMANT RC DISSICIORSER BUTC TVÖHTIM BEDGRUG KENEG VAA RG BRIRL TVÖHTIM BEDGRUG KENEG VAA RG BRIRL
		TOLERANCES OTHERWISE SP		I PATE	$\Delta$	SYNERGISTIC PRODUCTS, INC.
		1.51 1.00b	10-10.	DATE	1//	A Subsidiary of Cavitrin Corporation  1902 VoGew, Santa Ana, California
		OF BOUND T.	AND OUT APPROVED	DATE	11114	Etiolic (14 may)
		REMOVE BUR				Y DESIRED FEGISTER
		FINIDA			ICALE _	- I DAR C
NEXT ASSY	USED ON		1			ISCO-0i29






NOTE: UNLESS OTHERWISE SPECIFIED


1. FLIP-FLOPS ARE LU32IA OR EQUIV


			REP.	DESCRIPTION		CTV. PTR MACH.	PART NUMBER
		• .	OTHER DOCUMENTS OF		USED FOR		E REPRODUCED OR TRANSPERSED TO O DR AME OLHER PURPOSE WITHOUT
			TOLERANCES UNLESS OTHERWISE SPECIFIED .AX .AXX ANGLE 1 01 1,003 10-10*	excelu checkeo	DATE IS APC TI DATE		NERGISTIC PRODUCTS, INC. Subsidiary of Carifron Co. porstion
ı			OF ROUND T.I R 609	APPHOVED	UATE		1902 McGrw, Sarte Ara, California
l	4 ,		REMOVE SURRS AND BPEAK ALLSHARP EDGE	MATERIAL		YOU	SIRED REGISTER
I			PINISH		٠.	SCALE	**********
ı	NEXT ASSY	USED ON	1				1800-0100 ]



I. I.C.'S ARE SIGNETICS UTILOGIC II,
SP BERIES OR EQUIV.


			REF.	01	ESCRIPTION	GTY. PER ASSY.	MACH		PART NUMBER	_
			ОТН	ER DOCUMENTS OR		R USED FOR			BE REPRODUCED OR TRANSFERRED TO	
Ī					W Kelle	/4//0; Y	1 /	<u> </u>	SYNERGISTIC PRODUCTS, INC. A Subjectory of Caristian Corporation	7
1			- cont	1 1,001 10 JO'		DAT	$\mathcal{L} \mathcal{L} \mathcal{L}$	anie de la	N. 1902 M. Griv, Fanta Ana, California	_} .
1			ner	MOVE BURRS AND IX ALL SHARP EDGES	MATERIAL		7111.8	X	GIC DIACG/M S AND Y OFSIRED- GISTER, DIES 1-4	]
Ţ	NEXT ASSY	USED ON	PINIS		-		SCALE		1900-0131	コロ







NOTE: UNLESS OTHERWISE SPECIFIED


SP SERIES OR EQUIV.











NEXT ASSY


































NOTE: UNLESS OTHERWISE SPECIFIED

1. I.C.'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV. . . .

•	REF. D	ESCRIPTION		MACH.	PART NUMBER	
	OTHER DOCUMENTS OR		USED FOR		OT BE REPRODUCED OR TRANSPEASED TO IRING OR ANY OTHER PURPOSE WITHCUT	
	OTHERWISE SPECIFIED	CHECKED	7 414777 DATE	1		
	RENOVE BURRS AND BREAK ALL SHARP EDGES	MATERIAL		Ā	DGIC DIAGRAM— CTUAL REGISTER LOCKING	
NEXT ASSY USED ON	PINISH		•	KAL	1800-0145	B








NOTE: UNLESS OTHERWISE SPECIFIED


1. I.C.'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.


	REF.	DESCRIPTION	PER.	MACH.	PART NUMBER			
• "	OTHER DOTUMENTS O	THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OF TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT PRIOR MAITTEN PRAINSION OF SYMPROSITIE PRODUCED.						
	 TOLERANCES UNLESS		915 71	A	SYNERGISTIC PRODUCTS, INC.			
	AN ANN ANGLE	CHECKED	DATE		A Subsidiary of Cavitron Corporation  1902 McGew, Santa Ans, California			
	OF POUNT T.I.R dos	APPROVED	DATE	TITLE 1				
	REMOVE RURRS AND			ן ע	OGIC DIAGRAM: AL REGISTER CLEAR			
	PINIEH	7		BCALE	DY'8 # 1000 0140			


































NOTES: UNLESS OTHERWILE SPECIFIED. 15

- " RESISTORS ARE 2K 5% AND ARE 1/4 WATT
- 2. I.C. 'S ARE BIGNETICS UTILOGIC II, SP SERIES OR EQUIV.

		REF.	DESCRIPTION	PER ASSY.	PER MACH.	PART HUMBER
•		OTHER DOCUME		R USED FOR		E REPPODUCED OR TRANSFERRED TO NO DR ANY GINER PURPOSE WITHOUT
		TOLERANCES U		O MILE I	A S	YNERGISTIC PRODUCTS, INC
		1.01 1.00	ANGLE CHECKED	DATE	1//	A Subsidiery of Cevitron Corporation
			AND OUT APPROVED	DATE	11745 G	1902 McGerr, Santa Ana, California
		BREAK ALL SHAR				MOVE OR PARITY
		PINISH			SCALE .	Dwe #
NEXT ASSY	USED ON		1			1800-0149-2




a.





NOTES! UNLESS OTHERWINE SPECIFIED, Y

- " RESISTORS ARE 2K 5% AND ARE 1/4 WATT
- 2. I.C. 'S ARE BIGNETICS UTILOGIC II, SP SERIES OR EQUIV.


	•	VERTIC	AL TABL	E 50	ER.#290
		ner.	DESCRIPTION	PER	PER PART NUMBER
	. •	OTHER DOLUMENTS	NTAINS PROPRIETARY INFO OR DISCLOSED TO OTHERS MISSION OF SYNERGISTIC P	OR USED FOR A	H SHALL NOT BE PEPROPULED ON THAMEPER 91D TO FANDFACTURING OR ANY OTHER PUPPOLE WITHOUT
		TOLERANCES UNLES		UR 14	SYNERGISTIC PRODUCTS, INC.
		1,01 1,00 10.1 1,01 10,1	E CHECKED	UAIT	A Subudiary of Caritron Corporation 1907 Nt. Crin, Sints Ana, California
		OF HOUND TIR. GE		1140	TITLE LEWY DIN PAN
		REMOVE BURRE AN			START MOVE OF PARITY
		FINISH		Ì	PLALE TOWN O COLAR
NEXT ASSY	USED ON		1	1	1800-0149 - 4








THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OR TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE MITHOUT PRIOR MINITAL PERMISSION OF EVERDESITE PRODUCTS. TOLERANCES UNITEDS
OTHERWISE SPECIFIED
JRK JRK ANGLE
1.91 1.005 JO 30'
CONCENTRICITY AND DV
DF ROUND T.J.R., 205 CHECKED SYNERGISTIC PRODUCTS, INC. A Subsidiary of Cavitron Corporation 1902 McGaw, Santa Ana, Carifornia LOGIC DIAGRAM COARSE RANGE DECODER 1800-0151 USED ON NEXT ASSY







NOTE: UNLESS OTHERWISE SPECIFIED
L. LC'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.

1837 3 5 5 7 7

•						l
	REF. D	ESCRIPTION	PER ASSY.	PFR MACH.	PART NUMBER	
	OTHER DOCUMENTS OR		USED FOR		L NOT BE REPRODUCED OR TRANSFERRED TO ACTURING OR ANY DIHER PURPOSE RITHOUT	B
	TOLERANCES UNLESS OTHERWISE SPECIFIED	" Kolin	J ART		SYNERGISTIC PRODUCTS, INC.	
	1.01 1.005 70730*	CHECKED	DAT	1/:	A Subsidiary of Centron Corporation 1902 McGrw, Santa Ana, California	1
	OF ROUND T I R. 603	APPROVED	DAY	7176		1
	REMOVE BURRS AND BREAK ALL SHARP EDGES	MATERIAL			FINE RANGE DECOBER	
	PINISH			MALA	1800-0152	
NEXT ASSY USED ON				1	1 1000 0132	1
	CONCENTRICITY AND OUT OF ROUND T I R. 803 REMOVE BURRS AND BREAK ALL SHARP EDGES	MATERIAL	UAY	7171.8	LOGIC DIAGRAM— FINE RANGE DECOGER	








NOTE: UNLESS OTHERWISE SPECIFIED


I.C.'S ARE SIGNETICS UTILOGIC II, SP SERIES
OR EQUIV.


			AEF.	DESCRIPTION	ASSY.	MACH.	PART NUMBER
			ОТН	S DOCUMENT CONTAINS PROPRIETARY INFORMA IER DOCUMENTS ON DISCLUSED TO OTHERS OR OR WRITTEN PERMISSION OF SYNERGISTIC PROC	USED PO		
E			1.0 1.0	LERANCES UNLESS LEPHISE SPECIFIED  SI 1.015 10*10* LENTRICITY AND OUT APPROVED  ROUND T. 1.0.05	DAT		SYNERGISTIC PRODUCTS, INC. A Submitting of Caritron Corporation 1902 McGaw Santa Ana, Childrenia
-			DREA	MOVE BURTS AND MAYERIAL			DAC INPUT CLOCKING
-	NEXT ASSY	USED ON	PINIS			SCAL	1800-0154

















	REVISION	
SCHIP 1	SESCRIPTION	AC 3" DATE & APPLOVAL
Α	E.O. 414	300 25-84-2 BUR
В	5.0.519	DIT 4-20-72
C	REV PER ECO 867	as 4/27/73 BDF




I. RESISTORS ARE RATED IN OHMS ±5% AND ARE 1/4 WATT

		ESCRIPTION	ASSV.	QTV. PER MACH.	PART NUMBER	
	OTHER DOCUMENTS OF	DISCLOSED TO OTHERS OR L SION OF SYNERGISTIC PRODU	SEO FOR	MANUFACTURIN	F REPRODUCED OR TRANSFERRED TO ID OR ANY OTHER PURPOSE WITHOUT	
	TOLERANCES UNLESS OTHERWISE SPECIFIED ,XX, XXX ANGLE 1.01 2.005 10-30' CONCENTRICITY AND OUT	CHECKED	DATE SHIFA 71 DATE		YNERGISTIC PRODUCTS, INC. A Substitutery of Cavitron Corporation 1992 McGew, Santa Ana, California	
	OF ROUND T.E.F. 603  REMOVE BURRS AND  BREAK ALL SHARP EDGES	MATERIAL			MATIC - DAC NEGATIVE REFERENCE SUPPLY	
NEXT ASSY USED ON	PINISH			16ALE	°°1800-0161	C











- I. RESISTORS ARE RATED IN OHMS ±5% AND ARE I/4 WATT
- 2. CAPACITORS ARE I MICROFARAD, 35WVDC, 10%


		REF.	. DESCRIPTION	Pen	MACH	PART NUMBER	
		OTH		OTHERS OR USED FOR		L NOT BE REPRODUCED OR TRANSPERRED TO RETURING OR ANY OTHER PURPOSE WITMOUT	B
		ОТН	TERANCES UNLESS AV R. Che		1 /	SYNERGISTIC PRODUCTS, INC.  A Subsidiery of Cavitron Corporation	
,		2.0 COHC	DE 1.005 10-30'	DATE	1/6	1902 McGew, Santa Ana, California	
		AEA	MOVE BURRS AND MATERIAL		nitu	SCHEMATIC- DAC Y AXIS	,
		FINIS			<b>ICALS</b>	AMPLIFIER	
	NEXT ASSY USED ON	سا				1,1000 0100	1


















SDI3 + A
SD23 + K
SD33 + U
SD43 + B
SD53 + K
SD63 + I


NOTE: UNLESS OTHERWISE SPECIFIED


1. FLIP-FLOPS ARE LU32IA OR EQUIV.

2. NAND GATES ARE MC658P OR EQUIV.

									:
			nce.	0	ESCRIPTION	27,5	71 4 71 4 71 4	PART AUMOER	ı
			01111	A DOCUMENTS OF	INS PROPRIETARY INFORMA DISCLESED TO OTHERS OR SION OF SYNERGISTIC PROF	U110 F04		CE PROPERTIES TO BE SEEN TO SEE EN EN EUR LUN EN EUR	
				PANCES UNLESS	"Kehan	15 12 7		SYNERGISTIC PRODUCTS, INC.	ı
			1.0	1 7.455 te 10'	CHECKED	DAT	1/:	A Subudiary of Control Corporation  3 1907 M. Georg Sente Are, Conforms	
-				TIR DES	APPROVED	641	11100		
-			HREA	ALL SHARP EDGES	MATERIAL		Di-	LOGIC OF HAM - OF AY RESPOND RISEGMENT 3	٠,
	NEXT ASSY	USCO ON	PIMIL				***	···· - 00-0165	4
-		THE PERSON NAMED IN COLUMN TWO IS NOT THE OWNER.	سسما	COMMERCIAL STATE OF THE PARTY O	-				










- I. FLIP-FLOPS ARE LU32IA OR EQUIV
- 2. NAND GATES ARE MC858P OR EQUIV

			AEF.	DESCRIPTION	OTY. PYR. ASSY.	PIR MACH.	PART NUMBER
			OTH		MS ON USED PL		L NOT PEREPRODUCED OR TRANSPERRED TO ACTURING OR ANY OU SE PURPOSE WITHOUT
-			07H .X. 1.6 CONC	ENANCES UNLOSS ENANCES EXCEPTED X JAXA ANGLE 11 2.005 20-20* ENTRICITY AND OUT APPROVED APPROVED APPROVED	//3,600 TO DATE		SYNERGISTIC PRODUCTS, INC.  A Subsidiary of Caritron Corporation 1007 McGow, Santa Ana, Chiffenia 1 0 0 1 C 0 1 A 3 5 A M =
L				NOVE BURRS AND MATERIAL NALL SHARF EDGES		7	DISPLAY REGISTER
-	NEXT ASSY	USED ON	PIN'S			SCALE	1800-0169

)










- I. FLIP-FLOPS ARE LU32IA OR EQUIV.
- 2. NAND GATES ARE MC858P OR EQUIV.

	•		HEF.	DI	SCRIPTION	AK V	PER MACH.	PART NUMBER
			ОТН	ER DOCUMENTS OR		N USED FOR		L NOT BE REPRODUCED OR TRANSFERRED TÖ CTURING OR ANY DYNYR PURPOSE WITHOUT
F				CRANCES UNLESS CRITICISTS SCIENTS CRITICISTS SCIENTS	OV Reham	/1 /0°% 7	4 /	SYNERGISTIC PRODUCTS, INC.  A Subsidiary of Capitron Corporation
ŀ					APPROVED	DAT	1/1	1902 McGree, Santa Ana, California
				OVE BURRS AND	MATERIAL		1	LOGIC DIAGRAM PLAY REGISTER SEGMENT 5
L	- NEXT ASSY	USED ON	FIMISH				HEALE	1600-0170









- I. FLIP-FLOPS ARE LU32IA OR EQUIV
- 2. NAND GATES ARE MC858P OR EQUIV

		Aer.	DESCRIPTION	PPR	PTH MACH	PART NUMBER
		OTHER DOCUMENTS O		78 USED FOR I		BE REPRODICE O OR THANSFERRED TO NO OR ANY OTHER PURPOSE WITHINGS
		TOLERANCES UNLESS OTHERWISE SPECIFIED		13 AN 7/		YNERGISTIC PRODUCTS, INC.
		BLON XXX XX.	CHECKED	DATE		A Subditiony of Covitron Corporation
		OF ROUND T,I R 805	UT APPROVED	,		1902 (Action), Sente Ans, California C. (C) Action M.—
		REMOVE BURRS AND			DISP	LAY REGISTER
		FINISH	1	,		10mg *10 (20 017)
NEXT ASSY	USED ON	7	1		استسرا	1 1300-017

7






JOG SD17 + E SD27 + P SD37 + Y SD47 + E SD57 + P SD67 + Y

NOTE: UNLESS OTHERWISE SPECIFIED

- I. FLIP-FLOPS ARE LU32IA OR EQUIV.
- 2. NAND GATES ARE MC858P OR EQUIV.

₩.	-		ner.	Di	ESCRIPTION	ASSY.	PER.	PART NUMBER
			OTHE	A DOCUMENTS OR		A USED FO		II E NOT BE REPRICUCED OR TRANSPERRED PACTURING OR ANY DIMER PURPOSE WITHD
			OTHE	JUNA KKK.	APPROVED	IS FINE DA	<u> </u>	SYNERGISTIC PRODUCTS, IN A Subsidiary of Certron Cerpovation 1902 McGew, Sente Ana, Certorol
			REM	OVE SURES AND ALL SHARP EDGES	MATERIAL		7""	* LOGIC DIAGRAM = SPLAY REGISTER SEGMENT T
NEXT A		USED ON	PIRISH				SEAL.	1800-0172





NOTE: UNLESS OTHERWISE SPECIFIED


1. IC'S ARE SIGNETICS UTILOGIC II, SP SERIES

OR EQUIV.

		REF.	D	ESCRIPTION	PER ASSV.	GTY. FFR MACH.	PART NUMBER	]
		OTHER	OCUMENTS DR	INS PROPRIETARY INFORM DISCLOSED TO OTHERS OF SION OF SYNERBISTIC PRO	U150 POP	CH SHAL	LL NOT BE REPRODUCED OR TRANSPERRED TO ACTURING OR ANY OTHER PURPOSE WITHOUT	
		OTHERW I.O.	SE'NA XXX. 100 10 10 10 10 10 10 10 10 10 10 10 10	EHECKED	DAT	4/	SYNERGISTIC PRODUCTS, INC. A Subililiery of Certifion Cooperation 1902 St. Gine, Santa Ana, California	
		REMUVI BREAK AL	ND T.I R863 E BURRS AND L BHARP EDGES	MATERIAL		1	DISPLAY REGISTER	
NEXT ASSY	USED ON	PINISM				SCALE	1000-0173	1








i.c's are signetics utilogic II, sp series or equiv.


		nsr.	P. DESCRIPTION PAGE		QTY. PER PART NUMBER MACH.	_		
		DTHER DOCUMENT	THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED ON "RANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT PRIOR WHITTEN REMISSION OF SYSTR					
		TOLERANCES UNL OTHERWISE SPECI XX XX AN	HOLE CHECKED	DATE 3 MY-7/ DATE	SYNERGISTIC PRODUCTS, INC.	1		
		1.01 1.005 10 CONCENTRICITY AN OF HOUND T.I.R.	APPROVED	DATE	1902 McCow, Senta Ane, California	4		
		REMOVE BURRS A			TIME DELAY			
NEXT ASSY	USED ON	PINISH		1	1800-0176	18		



i. I.c's are signetics utilogic II, sp series or equiv.

P/2/P DYNAMIC BRAKING MOD & DRILLING MACHINE

	REP. DE		FE 10	MACH.	PART NUMBER
	OTHER SOCUMENTS OR		IC POR		E HOT DE BERROOILER OF TRANSFER FOR E RETURING OR ANY OTHER PUR CIT WITHOUT
	Jos tons for 20'	EMELATO	DATE	/1	A SUNDICIONAL PRODUCTS, 1900.  A SUNDICIONAL PRODUCTS, 1900.  A SUNDICIONAL PRODUCTS, 1900.  1907 ASSORB, Senta Area, Cel 1 white
		MATRAIAL	1001.	-	LOCIC DINGHAM-
NEXT ACAY USED ON	PINIOH			164.1	7500-0176-2





1.c's are signetics utilogic II, SP series OR EQUIV.


MAY BE SAME AS 176-2 FOR


VERTICAL TABLE SER # 290


		POR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT
	AN ANUE CHECKLO	SYNERGISTIC PRODUCTS, INC. A Substituty of Control Corporation  A Substitute of Control Corporation  1110 United Education Corporation  1111
· · · · · · · · · · · · · · · · · · ·	BREAN ALL SMAAP EUSES	TIME DELAY
	PINISH	19:300-0176-2











- Z. RESISTORS ARE 2K ±5% AND ARE 1/4 WATT
- 3. CAPACITORS ARE I MICROFARAD, 35V, 10%

DRILLING MACHINE

THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL MOT SE REPRODUCTS OF TRANSFERRED TO DISK DOCUMENTS ON DISLOSED TO OTHER HOLD ON NATURAL PROPRIETARY INFORMATION WHICH SHALL MOT SE REPRODUCTS OF TRANSFERRED TO DISLOSED TO OTHER HOLD ON NATURAL PROPRIETARY INFORMATION OF MANUFACTURING OR AND UTHER PURPOSE MITHOUT PRIOR WAITTEN FRAULTION OF SYNCROSISTIC PRODUCTS, INC.

TOKERANGE SPECIFIC JAN AND AND ANTERIAL DATE

JAN AND AND ANTERIAL DATE


OF ROUND TIAL SESS


MATERIAL


MATERIAL


NO 1

YEARS OF THE COURT OF TRANSFORM TO THE PURPOSE OF THE PURPOSE











NOTE ! DIMERSS OTHERWISE SEECHIED.


1. RESISTORS ARE 2K ±5% AND ARE 1/4 WATT


2. I.C.'S AZE SIGNETICS UTILOGIC II, SP BERIES OR EQUIV.


		REP.	DESCRIPTION	A.S.Y.	MACH.	tant nuvera
DRILLING	MACHINE	DIMEN DOCUM		OF USED FO		Ų мустрі препроцеву ра тяльсет і се са кручана ря мем рочка пустост му тоцг
		TOLERANCES OF COMPANY SERVICES AND A SERVICE AND A	ANDLE CHILAND	10 ~~		SMNERGISTIC FRODUCTS, INC.  A Sciencia of Calcina Consertion  1002 Notice, Secta Ana. Cello de
		REMOVE SUFF	A COL		11000	ECGIC GIAGHAH MANUAL SWITCH INPUT NO 3
NEXT ASSY	USED ON	PINISH			resid	1800-0180-2











NOTES UNISS OTHERWISE SPECIFIED.


- L RESISTORS ARE 5%,1/4 W.
- 2. I.C.'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.


RE	DESCRIPTION	PER ASSY	MACH.	PARY NUMBER
01	IS DOCUMENT CONTAINS PROPRIETARY INFOR HER DOCUMENTS OR DISCLOSED TO OTHERS O	R USED FO		

- AESET 121,181,186,191,185

		PRIOR WRITTEN PERMIS	SION OF SYNERGISTIC PROD	UC FS	
		OTHERWISE SPECIFIED	OFFICE CHECKED	PATE DATE	A Subsidiary of Caritron Corporation 1902 McGss., Senta Aria, Celdurnia
		REMOVE BURRS AND BREAK ALL SHARP EDGES	MATERIAL		RESET PULSE GENERATION
NEXT ASSY	USED ON	PINISH			"1800-0182

~~~~







NOTES: UNIESS OTHERWISE SPECIFIED.


L RESISTORS ARE 5%,1/4 W.


2. IC'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.

|               |         |            |                                                                                                   | 7::           | 1 <del> </del> |                                                                         |
|---------------|---------|------------|---------------------------------------------------------------------------------------------------|---------------|----------------|-------------------------------------------------------------------------|
| <br>·         |         | ACP.       | DESCRIPTION                                                                                       | A557. W       | X. 9.          | PART HIMIER                                                             |
| DRILLING M    | 1ACHINE | OTHER DOCK | ENT CONTAINS PROPRIETARY INFO<br>JMENTS OR DISCLOSED TO UTHERS<br>TEN PERMISSION OF SYNERGISTIC P | C# USEQ FOR M |                | REPRICULIEG EN TRANSPERPED TU<br>UN AMY LINES RIURPOSE MIZHEUT          |
|               |         | TIMERANCE  |                                                                                                   | 1 S 4147 31   | A. SY          | vergiotic products, inc.                                                |
| ·             |         | 1 01 2.00  | A ANGLE CHECKED                                                                                   | 00.4          |                | Substitute of Cartes Carporation,<br>1967 At Use , Santa Ana, Est force |
| <br>          |         | OF ROUND   | TYANDOUT AFFROYLD                                                                                 | DATE          | ~~~~           | GIC WALLER                                                              |
| ~             |         | HEMOVE BL  |                                                                                                   |               |                | ULSE GENERATION                                                         |
|               |         | Pinish     |                                                                                                   |               | care .         | 780 182-2                                                               |
| <br>NEXT ASSY | USED ON | 1          | 1                                                                                                 | 1-            |                | 1800 184 1                                                              |












## NOTE UNLESS OTHERWISE SPECIFIED


I. I.C.'S ARE SIGNETICS UTILOGIC II, SP SERIES OR EQUIV.


|   | • •       |         | HEF.              | D                                                                                                                                                                                                                                                  | ESCRIPTION        | 1 21 2 | PT R<br>MACH. | PARI NUMBER                      | ] . |
|---|-----------|---------|-------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|--------|---------------|----------------------------------|-----|
|   | •         |         | 0114              | THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL MOT BE REPROSUCED OF TRANSFERED TO<br>OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OF ANY OTHER PURPOSE WITHOUT<br>FROM WRITTER REMINISTOR OF SYNTROTICE PROPRIETS. |                   |        |               |                                  | ,   |
| F |           |         | 01.4<br>.X<br>1.0 | ERWISE SPECIFIED                                                                                                                                                                                                                                   | EMECKED  APPROVED | DATE   |               |                                  |     |
|   |           |         | BREA              | K ALL SHARP EDGES                                                                                                                                                                                                                                  | MATERIAL          |        | Bi            | OGIC DIAGRAM<br>T TIME<br>SUNTER | _   |
| ŀ | NEXT ASSY | USED ON | PINIS             | ·                                                                                                                                                                                                                                                  |                   |        | BEALE         | 1800-0184                        | B   |

























|                   | REP. DESCRIPTION                                                 | OTY DIV. PART NUMBER ASIV. SIZEH.                                                                                              |
|-------------------|------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|
|                   |                                                                  | NMATION WHICH SMALL MOT BE REPRODUCTO OR TRANSPERRECE TO<br>CRIDICO FOR MANUFACTURING OR ART OTHER PUPPOSE RITHOUT<br>RODUCTS. |
|                   | OTHERWISE SPECIFIED AT R. C. | SYNERGISTIC PRODUCTS, INC.  A Subspilary of Caritron Corporation                                                               |
|                   | CONCENTRICITY AND OUT APPROVED OF POUND T.I. 9. 905              | OATE TISE 1 051 OF HAM TO                                                                                                      |
| \\                | PREMOVE PURPS AND MATERIAL                                       | RETU O REF. AND STOP                                                                                                           |
| NEXT ASSY USED ON |                                                                  | 1490-0188-2                                                                                                                    |














THIS DECUMENT CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REFROUTED OR TRANSFERRED TO OTHERS ON USED FOR MANUAL NOT BE REFROUTED OR TRANSFERRED TO OTHERS ON USED FOR MANUACTURING OR ANY UTHER PURPOSE WITHOUT PRICES WITHOUT


REVISION


to believe the same of the same of the same of























































































































| 100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100    |             |                                         | ·           |                                          |           |                            |                                                               |                        | 1                                       |                                |                                                       |          |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|-----------------------------------------|-------------|------------------------------------------|-----------|----------------------------|---------------------------------------------------------------|------------------------|-----------------------------------------|--------------------------------|-------------------------------------------------------|----------|
| 1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992   1992      | 800-0101    | (NO*                                    | 1800-0139   | ACTUAL REGISTER AND ADDER BITS 13-16     | 0177-2    | SYSTEM CLOCK GENERATION    |                                                               |                        |                                         |                                |                                                       |          |
| 1982   1962   1962   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963   1963      | 0105        | THO.                                    | 0140        | ACTUAL REGISTER AND ADDER BITS 9-12      | 0178      | MARICAL SWITCH THPUT NO. 1 | <del></del>                                                   | -                      |                                         |                                |                                                       |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 0103        | S FUNCTION REGISTER WIRE ROUTE DISPLAY  | 0141        | ACTUAL REGISTER AND ADDER BITS 5-8       | 0179      | MANUAL SWITCH INPUT NO. 2  | 2                                                             |                        |                                         |                                |                                                       |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 0104        | READER TRACK GATING AND ASCII-EIA CONV. | 0142        | ACTUAL REGISTER AND ADDER DITS 1-4       | 0180      | MARIUAL SWITCH INPUT NO. 3 | 3                                                             |                        |                                         |                                |                                                       |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 0105        | READER TRACK PARITY DECODER             | 0143        | TACH PULSE SYNCRONIZATION                | 0181      | INDEX, AXIS SAFE, SSI AND  | 0 552 F/F                                                     |                        |                                         |                                |                                                       |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 0106        | TRANSLATOR NO. 1-3 TO 1 OUT OF 8        | 0144        | CONTROL TIME COUNTER                     | 0182      | RESET PULSE GENERATION     |                                                               |                        |                                         |                                | *                                                     |          |
| POP    | 0107        | TRANSLATOR NO. 2.3 TO 1 OUT OF 8        | . 0145      | ACTUAL REGISTER CLOCKING                 | 0183      | DIGIT TIME COUNTER         |                                                               |                        |                                         |                                |                                                       |          |
| ORDER COUNTER CASCAR   100   40   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100      | 0108        | CONTROL CHARACTER DECODER NO. 1         | 0146        | ACTUAL REGISTER CLEAR                    | 0184      | BIT TIME COUNTER           | · · · · · · · · · · · · · · · · · · ·                         | 1                      |                                         |                                |                                                       |          |
| 101                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 0109        | CONTROL CHARACTER DECODER NO. 2         | 0147        | JOG SWITCH GATING                        | 0185      | M AND N FUNCTION AND READ  | CER STROBE F/F                                                |                        |                                         |                                |                                                       |          |
| Part      | 0110        | CONTROL CHARACTER DECODER NO. 3         | 0148-2      | JOG OR MOVE SYNC, AND MOTOR INHIBIT      | 0186      | DIALS AND TAPE DATA TIME   | F/F :                                                         |                        |                                         |                                |                                                       |          |
| 100-24 (100 St.) 2.5   15   16   16   16   16   16   16   1                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    | 0111        | TAPE READER DATA TRACK VERIFICATION     | 0149 - 2    | START MOVE OR PARETY FAILURE             | 0187      | DIALS INTERROGATION CATIF  | NG                                                            | -11                    |                                         |                                |                                                       |          |
| 1012                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 0115        | ALMIA AND NUMERIC CHARACTER DECODER     | 0150        | INDEX, REWIND AND STOP INDICATOR DRIVERS | 0188      | RETURN TO REF. AND STOP I  | F/F SWITCH SINGLE                                             | 1                      |                                         |                                |                                                       |          |
| AUTO   CONTINUE   CO   | 0113        | TRANSLATOR NO. 3-9 TO 1 OUT OF 4        | 0151        | COARSE RANGE DECODER                     | 0189      | TEST AND XY STOPPED F/F    |                                                               |                        |                                         | <del>-,-</del> -               |                                                       |          |
| 0.11-2   CAST CAST CAST   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.12   0.   | 0114        | M FUNCTION REGISTER                     | 0152        | FINE RANGE DECODER                       | 0190      | SHIFT F/F AND LOAD         | · · · · · · · · · · · · · · · · · · ·                         | -                      |                                         |                                |                                                       |          |
| MAIL SAN, DOC.   1015   DOC. INFOLICIOSTR X SIGN AD REG.   1015   TOTAL CONTINUE   1015   TOTAL CONT   | 0115-3      | MOTOR CONTROL (2 SHEETS)                | 0153        | DAG INPUT DIRECT SET-RESET ENABLE        | 0191      | READER CONTROL F/F         |                                                               | 1                      |                                         |                                |                                                       |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 0116-2      | X.AXIS MTR. DR.                         | 0154        | DAC INPUT CLOCKING                       | 0135      | PROCESSOR M RELAYS         |                                                               |                        |                                         |                                | ······································                |          |
| 10.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00   1.00     | 0117-2      | Y.AXIS MTR. DR.                         | 0155        | DAC INPUT REGISTER X SIGN AND MSB        | 0193      | PROCESSOR N RELAYS         | · · · · · · · · · · · · · · · · · · ·                         | 1                      |                                         |                                |                                                       |          |
| 1023   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027   1027      | 0118        | N FUNCTION REGISTER                     | 0156        | DAC IMPUT REGISTER X LSB                 | 0194      | POWER CONTROL              |                                                               | 1                      |                                         |                                |                                                       |          |
| 1012   CAPICATE RESISTER BITS 1-4   1016   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   100   | 0119        | TACH PULSE DECODING XLAXIS              | 0157        | DAC INPUT REGISTER Y SIGN AND MSB        | 0195      | 1                          |                                                               |                        |                                         |                                |                                                       |          |
| ORD   CONTROLLER BITS 1-4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      | 0120        | TACH FULSE DECODING YAXIS               | 0158        | INC INPUT REGISTER Y LSB                 | 0196      | (NOT USED)                 |                                                               |                        |                                         |                                |                                                       |          |
| 0122 CONCESSION RESISTER BITS 5-14  0161 ON MONTH WITCHARD SOUNTY OF THE PROPERTY OF THE PROPE | 0121        | 4-BIT CESTRED TREUT REGISTER            | 0159        | DAC INPUT ZERO DECODER                   | 0197      | (NOT USED)                 |                                                               |                        |                                         | -                              |                                                       |          |
| 0124 CONFESTION REGISTER DITS 15-224 0125 (IL-10 GENERAL AND CESTION AND TESTION AND TESTI | -           | CONTENSION REGISTER BITS 1-4            | 0160        | DAC REFERENCE VOLTAGES                   | 0198      | (NOT USED)                 |                                                               |                        |                                         |                                |                                                       |          |
| 0125   SEC TO STRAM NOT RESISTED ANTITIETTE                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |             | CONVERSION REGISTER BITS 5-14           | 0161        | DAG NEGATIVE REFERENCE SUPPLY            | 0199.     | HOTOR INHUBIT DELAY        |                                                               |                        |                                         |                                |                                                       |          |
| O18   CESTRO RECISTRE SECR.   O184   (A.Y. X. A.T.) 20 CERCUIT                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |             |                                         | 0162        | DAC X AXIS AMPLIFIER                     |           | ·                          |                                                               |                        |                                         | - Annual Antonio de Carro      |                                                       | <b>—</b> |
| 0127   SUBSTITUTE PROJECT OF PROJECT STATE   0165   SACY AND SECRET   1   0166   SOFT TOTAL   0167   SOFT TOTAL   0167   SOFT TOTAL   0168   SOFT TOTAL   0169   SOF   |             |                                         | 0163        | DAC Y AXIS AMPLIFIER                     |           |                            |                                                               | -                      | *************************************** |                                |                                                       |          |
| O168   CLESSIFED RIGISTER BITS 5-TA   O166   (NOT 1220)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |             |                                         | 0164        | DAC X AXIS JOG CIRCUIT                   |           |                            | <del></del>                                                   | 11                     |                                         |                                |                                                       |          |
| 102   1.43   1.53   1.52   1.52   1.53   1.54   1.55   1.54   1.55   1.54   1.55   1.54   1.55   1.54   1.55   1.54   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1.55   1   |             |                                         | 0165        | DAC Y AXIS JOG CIRCUIT                   | 1         |                            | ***************************************                       |                        |                                         |                                |                                                       |          |
| 10.50   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.00   17.0   |             |                                         | 0166        | 1                                        |           |                            |                                                               | 11                     |                                         |                                |                                                       |          |
| 131   X AND Y LESINED REGISTER DUTING DITS 1-4   D169   DISPLAY REGISTER SECRET 5     1013   LESINED REGISTER DUTING DUTING DITS 1-12   D170   DISPLAY REGISTER SECRET 5     1014   DISPLAY REGISTER DUTING   |             |                                         | 0167        |                                          |           |                            |                                                               |                        |                                         |                                |                                                       |          |
| O132 CESTRED REGISTER OUTFUL CATTING DITS 7-12  O133 CESTRED REGISTER OUTFUL CATTING DITS 7-12  O134 DESTRED REGISTER OUTFUL CATTING DITS 7-12  O135 OCSTRED REGISTER OUTFUL CATTING DITS 13-18  O136 X AND REGISTER OUTFUL CATTING DITS 13-18  O137 DISPLAY REGISTER SEGRENT 7  O138 ACTUAL REGISTER AND ACCESS DITS 21-24  O139 ACTUAL REGISTER AND ACCESS BITS 21-24  O139 ACTUAL REGISTER AND ACCESS BITS 21-24  O139 OTFO THE DELLAY COUNTER  O139 ACTUAL REGISTER AND ACCESS BITS 21-24  O139 OTFO THE DELLAY COUNTER  O139 ACTUAL REGISTER AND ACCESS BITS 21-24  O139 OTFO THE DELLAY COUNTER  O139 OFFO THE DELLAY COUNTER  O130 OFFO THE DELLAY CO | . 1         |                                         | 0168        | DISPLAY REGISTER SEGMENT 3               |           |                            |                                                               | 1                      |                                         |                                |                                                       | $\neg$   |
| O133 CESTAD REGISTER COUNTY CATTER DITS 7-12  O134 DESTAD REGISTER SUPPLY CATTER DITS 13-18  O135 OCCIPITO REGISTER OUTPUT CATTER DITS 13-18  O136 OCCIPITO REGISTER OUTPUT CATTER DITS 13-18  O137 OCCIPITO REGISTER OUTPUT CATTER DITS 13-18  O137 ACTIVAL REGISTER AND ADDRESS BITS 13-24  O137 ACTIVAL REGISTER AND ADDRESS BITS 21-24  O138 ACTIVAL REGISTER AND ADDRESS BITS 21-24  O139 ACTIVAL REGISTER AND ADDRESS BITS 21-24  O139 ACTIVAL REGISTER AND ADDRESS BITS 21-24  O139 ACTIVAL REGISTER AND ADDRESS BITS 11-20  O130 THE DELAY COUNTER  THE DECEMPTION  THE DELAY COUNTER  THE DELA |             |                                         |             |                                          |           |                            |                                                               |                        |                                         | *                              |                                                       |          |
| DISHED REGISTER OUTPUT CATING BITS 13-18  O172  O133  OCSIRED REGISTER OUTPUT CATING BITS 19-24  O173  DISHLAY REGISTER SEGRENT 8  O174  OISPLAY REGISTER SEGRENT 9  O136  ACTUAL REGISTER AND ADDER BITS 21-24  O175  DAC INPUT DIRECT SELECT GATING  O176  TIME DELAY COUNTER   ACTUAL REGISTER AND ADDER BITS 17-20  O176  TIME DELAY COUNTER   ACTUAL REGISTER AND ADDER BITS 17-20  O177  TIME DOLLAR FORWARD AND WINDOWS BALL AND INFORMATION WINDOWS BALL AN |             | ·                                       |             | <u></u>                                  |           |                            |                                                               |                        |                                         |                                |                                                       |          |
| OTS OCSERO REGISTER OUTPUT CATING BITS 19-24  OTS OSPILAR REGISTER SECRET 8  OTS DACTUAL REGISTER AND ADDER BITS 21-24  OTTO DESCRIPTION  OTHER DOCUMENT CONTAINS PROPRIE AND UNITED THE DECLAY COUNTER  THIS DOCUMENT CONTAINS PROPRIE AND UNITED THE DECLAY COUNTER  OTHER DOCUMENT CONTAINS PROPRIE AND UNITED THE DECLAY COUNTER  DESCRIPTION  OF THE DOCUMENT CONTAINS PROPRIE AND UNITED THE DECLAY COUNTER WITHOUT OF THE ADDER WI |             |                                         |             |                                          |           |                            | ***************************************                       |                        |                                         |                                |                                                       |          |
| O136 X AND Y DESIRED REGISTER CLOCKING  O174 OISPLAY REGISTER SECRET 9  O137 ACTUAL REGISTER AND ADDER BITS 21-24  O175 DAG INPUT DIRECT SEL-REGET GATING  O138 ACTUAL REGISTER AND ADDER BITS 17-20  O176 TIME DELAY COUNTER  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  OTHER DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  OTHER DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  OTHER DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  OTHER DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIVERS ON DIVERS ON DIVERS ON DIRECT SEL-REGET GATING  OTHER DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  THIS DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIRECT SEL-REGET GATING  OTHER DOCUMENT CONTAINS ACCUSED TO DIVERS ON DIVER |             |                                         |             |                                          |           |                            |                                                               |                        |                                         |                                |                                                       |          |
| O137 ACRIAL REGISTER AND ADDER BITS 21-24  O175 DAC IMPUT DIRECT SET-RESET GATING  O138 ACRIAL REGISTER AND ADDER BITS 17-20  O176 TIME DELAY COUNTER  DESCRIPTION  ASTY, MACH, PART HUNDER  THIS DOCUMENT CONTAINS ADDRESS ON USED FOR ADMINISTRATORY STATES ON USED FOR ADMINISTRATORY FROM WAITER VERMINISTOR OF THE PROPRIET OF THE PROPRI | -           |                                         | <u> </u>    |                                          | •         |                            |                                                               |                        |                                         |                                |                                                       |          |
| ACTUAL REGISTER AND ADDER 8175 17-20  O176  THE DELAY COUNTER  THIS DOCUMENT CONTAINS PROPERTY AND INFORMATION WHICH SHALL NOT BE PERMINDED OF THE PROPERTY OF | -           |                                         |             | 1                                        |           |                            |                                                               |                        |                                         |                                |                                                       |          |
| THIS DOCUMENT CONTAINS PROPRIETARY INFORMATION WITCH HALL NOT BE REPRODUCED OF TRANSPERSANT OF THE DOCUMENT CONTAINS PROPRIETARY INFORMATION WITCH HALL NOT BE REPRODUCED OF TRANSPERSANT OF THE DOCUMENT OF DIRECTOR DOCUMENT OF DIRECTOR DOCUMENT OF THE DOC |             |                                         |             |                                          |           |                            |                                                               |                        |                                         |                                |                                                       |          |
| THIS DOCUMENT CONVAINS PROPRIET ARE UNICED ON THE REPRODUCED ON TRANSPERSED TO PRIOR WRITTEN FRAMILION OF EXPERIMENTAL MICH STATE REPRODUCED.  1 OLKANIES PROCURED TO THE PRODUCED.  1 OLKANIES PROCURED TO THE PROPERTY OF TH | 0138        | ACTION REGISTER AND ADDER BITS TIEZO    | 0176        | TIME DELAY COUNTER                       |           |                            | ,                                                             |                        |                                         |                                |                                                       |          |
| THIS DOCUMENT CONVAINS PROPRIET ARE UNICED ON THE REPRODUCED ON TRANSPERSED TO PRIOR WRITTEN FRAMILION OF EXPERIMENTAL MICH STATE REPRODUCED.  1 OLKANIES PROCURED TO THE PRODUCED.  1 OLKANIES PROCURED TO THE PROPERTY OF TH |             |                                         |             |                                          |           |                            |                                                               | 11                     |                                         |                                |                                                       |          |
| THIS DOCUMENT CONVAINS PROPRIET ARE UNICED ON THE REPRODUCED ON TRANSPERSED TO PRIOR WRITTEN FRAMILION OF EXPERIMENTAL MICH STATE REPRODUCED.  1 OLKANIES PROCURED TO THE PRODUCED.  1 OLKANIES PROCURED TO THE PROPERTY OF TH |             |                                         | 1           |                                          |           |                            |                                                               | 11                     |                                         |                                |                                                       |          |
| P/2/P  OTHER DICTOR MATTER PROMISSION OF SYNCROLISTIC PRODUCTS. WITHOUT PRIOR WATER PURPOSE WITHOUT PRODUCTS. W.C. A Substitute Product of Comparation of State of Conference of Confere |             |                                         |             |                                          |           | [                          |                                                               |                        |                                         |                                |                                                       |          |
| P/2/P  TOLKANICES UNILES OF THE PROCESTIC PRODUCTS, INC.  ASSOCIATED THE PROCESTIC PRODUCTS, INC.  ASSOCIATED THE PROPERTY AND DUTY  CONCERNITATION APPROVED  THE PROVED BURNA AND DUTY  THE PROVED THE PRODUCT PRODUCTS APPROVED  THE PROVED THE PRODUCT PRODUCTS APPROVED  THE PROVED THE PRODUCT PRODUCTS ASSOCIATED TO THE |             |                                         |             |                                          |           |                            | OTHER DOCUMENTS OR                                            | DISCLOSED TO OTHERS OF | A USED FOR                              | H SHALL NOT SE<br>MANUFACTURIN | EREPRODUCEE ON TRANSFERI<br>O DR ANY DIMER PURPOSE WI | 9 FO TO  |
| P/2/P    SX MXX ANGLE   CHECKED   DATE   A Substit any of Coviden Corperation   Concentrative And Duty   Concentrative An |             |                                         |             |                                          |           | <u> </u>                   | TOLKRANCES UNLESS                                             |                        |                                         |                                |                                                       |          |
| P/2/P  OF ACUMP TUR. 601  STANDAR BARRA ALL SHARP EDGES  FINAL  NEXT ACSY  USEO ON  OF ACUMP TUR. 601  1800 CGA T/ OLLER  COMM. SOURCE CO. 600  OF ACUMP TUR. 601  INTER REF DOOL SENTS  1800 CGA T/ OLLER  COMM. SOURCE CO. 600  OF ACUMP TUR. 601  INTER REF DOOL SENTS  INTER REF DOOL SENT | •           |                                         | : •         |                                          |           |                            | BJOMA KRK. RK.<br>195-el cost 1931<br>Tud dna vtigir tradonod | ł                      |                                         |                                |                                                       |          |
| P/2/P  NEXT ASSY USED ON 1800 - 506                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |             |                                         |             |                                          |           |                            | DE ROUND T.LR. 601                                            | MARERIAL               |                                         |                                |                                                       |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |             | PlaIP                                   |             |                                          | TTI-LL .  |                            | FINAN ALL SHARP EDGES                                         |                        | _                                       |                                | tivia f                                               |          |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | FL/71 DIETE | NICH POST OLEANPRINT 2000-10            | <del></del> | <del></del>                              | NEXT ASSY | USED ON                    |                                                               | <b>ļ</b>               |                                         | r > 1                          | 800-010 <b>05</b>                                     |          |


| 00-0101  | (NOT                                      | 1600-0139 | ACTUAL REGISTER AND ADOCR BITS 13-16     | 177-3     | SYSTEM CLOCK GENERATION               |                                                | W/4 1800                                       | 21140-5                                |                    | PUTER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|----------|-------------------------------------------|-----------|------------------------------------------|-----------|---------------------------------------|------------------------------------------------|------------------------------------------------|----------------------------------------|--------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 0102     | THOT                                      | 0140      | ACTUAL REGISTER AND ADDER BITS 9-12      | 0178-2    | MAPUAL SUITCH THPUT NO. 1             |                                                | W/N:                                           | S LIST:                                | 11a. 3 1975        | "ITRIX"                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| 0103     | 5 FUNCTION REGISTER WIRE ROUTE DISPLAY    | 0141      | ACTUAL REGISTER AND ADDER BITS 5-8       | 0179      | MANUAL SWITCH INPUT NO. 2             |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0104-2   | HEADER TRACK GATING AND ASCIILEIA CONV.   | 0142      | ACTUAL REGISTER AND ADDER BITS 1-4       | 0180 -2   | MANUAL SWITCH INPUT NO. 3             |                                                | W/2 1800                                       | 2-1000-                                | 505 110            | NO WINE                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| C105     | REALER TRACK PARTTY DECODER               | 0143-L    | TACH PULSE SYNGRONIZATION                | 0191 2    | INDEX, AXIS SAFE, SSI AND S           | sse f/f                                        |                                                |                                        | R PRANT            |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0106     | TRANSLATOR NO. 1-3 TO 1 OUT OF 8          | 0144-2    | CONTROL TIME COUNTER                     | 0162 -2   | RESET PULSE GENERATION '              |                                                |                                                | L MACH.                                |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0107     | TRANSLATOR NO. 2-3 TO 1 OUT OF 8          | 0145      | ACTUAL REGISTER CLOCKING                 | 0183      | DIGIT TIME COUNTER                    | ,                                              |                                                |                                        |                    | en remain de parecente de la composition della c |
| 0108-2   | CONTROL CHARACTER DECOCER NO. 1           | 0146      | ACTUAL REGISTER CLEAR                    | 0184-2    | BIT TIME COUNTER                      |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0109-2   | CONTROL CHARACTER DECOCER NO. 2           | 0147-2    | JOG SWITCH GATING                        | 0185      | M AND N FUNCTION AND READER           | STROUE F/F                                     |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0110     | CONTROL CHARACTER DECODER NO. 3           | 0148-3    | JOG OR MOVE SYNC, AND MOTOR INHIBIT      | 0186      | DIALS AND TAPE DATA TIME F/           | · .                                            |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0111     | TAPE READER DATA TRACK VERIFICATION       | 0149 -3   | START MOVE OR PARITY FAILURE             | 0187-2    | DIALS INTERROGATION CATING            |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0112-2   | ALPHA AND NUMERIC CHARACTER DECODER       | 0150 - 2  | INCEX, REWIND AND STOP INDICATOR DRIVERS | 0188 -2   | RETURN TO REF. AND STOP F/F           | SWITCH SINGLE                                  |                                                |                                        |                    | ·                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| 0113-2   | TRANSLATOR NO. 329 TO 1 OUT OF 4          | 0151      | CCARSE RANGE DECODER                     | 0189-2    | TEST AND XY STOPPED F/F               |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| - 1      | M FUNCTION REGISTER .                     | 0152      | FINE RANGE DECODER                       | 0190-2    | SHIFT F/F AND LOAD                    |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0115-3   | HOTOR CONTROL (2 SHEETS)                  | 0153      | DAC INPUT DIRECT SET_RESET ENABLE        | 0191-2    | READER CONTROL F/F                    |                                                | 1                                              | <del></del>                            | <u></u>            |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| f        | X.AXIS MTR. DR.                           | 0154      | DAC INPUT CLOCKING                       | 0192      | PROCESSOR HICKMS . NOT                | USED.                                          | 1                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0117-2   | Y_AXIS MTR. DR.                           | 0155      | DAC INPUT REGISTER X SIGN AND MSB        | 0193      | FREECOSCA NEGLANS NOT                 | USED                                           |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0118     | N FUNCTION REGISTER                       | 0156      | DAC INPUT REGISTER X LSB                 | 0194-2    | POWER CONTROL                         | *                                              |                                                | ······································ |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0119-2   | TACH PULSE DECODING XLAXIS                | 0157      | DAC INPUT REGISTER Y SIGN AND MSB        | 0195-1    | CONTROL PANEL (3 SHEETS)              | · "д                                           | 1                                              |                                        |                    | 4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| 0120 - 2 | TACH FULSE DECODING YLAXIS                | 0158      | DAC INPUT REGISTER Y LSB                 | 0196      | (NOT USED)                            |                                                | 1                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0121     | 4-BIY OCSINEO IMPUT REGISTER              | 0159      | DAC INPUT ZERO DECODER                   | 0197      | (NOT USED)                            | ·····                                          |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0122     | CONTRESSION REGISTER BITS 1-4             | 0160      | DAC REFERENCE VOLTAGES                   | 0198      | (HOT USED)                            |                                                |                                                | ·····                                  |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0123     | CONVERSION REGISTER BITS 5-14             | 0161      | DAC NEGATIVE REFERENCE SUPPLY            | 0199-7    | MOTOR INHIBIT DELAY                   | <del></del>                                    | 1                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0124     | CONVERSION REGISTER BITS 15-24            | 0162      | DAC X AXIS AMPLIFIER                     | 02/2      | DIGITIZER MODE                        | CONTROL                                        |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0125     | SED TO BINARY AND DESTRED ARTHMETIC       | 0163      | DAC Y AXIS AMPLIFIER                     | 02.13     | TAPE DUPLICATOR C                     |                                                | ·                                              |                                        | ·                  | •                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| 1        | DESTREO REGISTER STOT                     | 0164-2.   | DAC X AXIS JOG CIRCUIT                   | 6216      | +15 VDC REGULATOR                     |                                                | 11                                             |                                        | ••••               |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0127     | X-DESTRED REGISTER BITS 15-24             | 0165-2    | DAC Y AXIS JOG CIRCUIT                   |           |                                       |                                                | 1]                                             |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0128 .   | K-DESTRED REGISTER BITS 5-14              | 0166      | (NOT USED)                               | -         |                                       | ~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~         |                                                |                                        | <u> </u>           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0129     | Y-DESTRED REGISTER BITS 15-24             | 0167      | BCD TO 1 SEGNENT DECODER                 |           |                                       |                                                | 11                                             |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0130     | V-DESTRED REGISTER BITS 5-14              | 0168      | DISPLAY REGISTER SEGMENT 3               |           |                                       |                                                |                                                | -                                      |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0131     | K AND Y DESTREU REGISTER BITS 1.4         | 0169      | DISPLAY REGISTER SEGMENT 4               |           |                                       |                                                | 1                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0132     | DESTRED REGISTER OUTPUT GATING BITS 1-6   | 0170      | DISPLAY REGISTER SEGMENT 5               |           |                                       |                                                | 1                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0133     | DESTRED REGISTER CUTPUT GATING BITS 1-12  | 0171      | DISPLAY REGISTER SEGNENT 6               |           |                                       |                                                | 11                                             | · · · · · · · · · · · · · · · · · · ·  | <del></del>        |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| G134     | DESTRED REGISTER OUTPUT GATING BITS 13-18 | 0172      | DISPLAY REGISTER SEGMENT 7               |           |                                       |                                                | 1                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0135     | STRED REGISTER OUTPUT GATING BITS 19-24   | 0173      | DISPLAY REGISTER SEGMENT &               | <u> </u>  |                                       |                                                | 1                                              | <del></del>                            |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0136     | CAND Y DESTRED REGISTER CLOCKING          | 0174      | DISPLAY REGISTER SEGMENT 9               |           |                                       |                                                | l                                              |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0137     | ACTUAL REGISTER AND ADDER BITS 21-24      | 0175      | DAC INPUT DIRECT SET_RESET GATING        |           |                                       |                                                | 11                                             |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 0136     | ACTUAL REGISTER AND ADDER BITS 17-20      | 0176-2    | TIME DELAY COUNTER                       | -         |                                       | **************************************         | 1                                              | # <del>2 </del>                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|          |                                           |           |                                          |           |                                       |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| 1        |                                           |           |                                          |           |                                       |                                                |                                                |                                        |                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|          |                                           |           |                                          |           | , lase                                |                                                | SCRIPTION .                                    | STY. STY.                              | PART               | NUMBER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|          |                                           |           |                                          |           | THI                                   | IIS DOCUMENT CONTAI                            | NS PROPRIATARY INFOR                           | MATION WHICH SHAL                      | L HOT BE REPRODUCE | O CR THANIFEMPED TO                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|          |                                           |           |                                          |           | 1 071                                 | THER DOCUMENTS OR I                            | DISCLOSED TO OTHERS O<br>HON OF SYNERGISTIC PR | R GILD FOR MANUF                       | ACTURING OR AHY DI | PTH PURPOSE WITHOUT                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|          |                                           |           |                                          |           | 1 ! 01                                | DLERANCES UNLESS<br>HERWISE SPECIFIED          | JABARRA                                        |                                        | SYNERGISTI         | C PRODUCTS, INC.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|          |                                           |           | _                                        | 11        | COH                                   | ALDINA XXX. XX. VX. VX. VX. VX. VX. VX. VX. VX | 977 1 95                                       | 1000                                   | 1602 McCar         | v, Senta Ane, Californie,                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|          |                                           | •         |                                          |           |                                       | EMOVE BURRS AND<br>AX ALL SHAKP EDGES          | HATERIAL.                                      |                                        | 水に产 かたい<br>すぐかだ とう | 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|          |                                           |           |                                          |           | i i i i i i i i i i i i i i i i i i i |                                                |                                                | - Time                                 | Tong               |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|          | NO. PORT OF SAMPLING MANAGEMENT           |           |                                          | NEXT ASSY | USED ON                               |                                                | **************************************         |                                        |                    | 0100-54                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |


| ∞-0101 | MACHINE CUNCTION DIAGRAM                  | 1800-0139 | ACTUAL REGISTER AND ADDER BITS 13-16                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 177-2      | SYSTEM CLOCK GENERATION  |                                                                    |                                                                           |                |                                        |                                                                        |             |
|--------|-------------------------------------------|-----------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------|--------------------------|--------------------------------------------------------------------|---------------------------------------------------------------------------|----------------|----------------------------------------|------------------------------------------------------------------------|-------------|
| 0125   | (NOT WELL                                 | 0140      | ACTUAL REGISTER AND ADDER BITS 9-12                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 0178       | HENUAL SWITCH THPUT NO.  | 1                                                                  |                                                                           |                | •                                      | William Comments                                                       |             |
| 0103   | S FUNCTION REGISTER WIRE ROUTE DISPLAY    | 0141      | ACTUAL REGISTER AND ADDER BITS 5-8                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | 0179       | MANUAL SWITCH INPUT NO.  | 2                                                                  |                                                                           |                |                                        |                                                                        |             |
| 0104   | READER TRACK CATING AND ASCII-EIA CONV.   | 0142      | ACTUAL REGISTER AND ADDER BITS 1-4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | 0180       | MANUAL SWITCH INPUT NO.  | 3                                                                  | 1                                                                         | Water Strategy |                                        |                                                                        |             |
| 0105   | READER TRACK PARITY DECODER               | 0143      | TACH PULSE SYNCRONIZATION                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      | 0181       | INDEX, AXIS SAFE, SSI A  | ND SS2 F/F                                                         |                                                                           |                |                                        |                                                                        | $\neg$      |
| 0106   | TRANSLATOR NO. 1-3 TO 1 OUT OF 8          | 0144      | CONTROL TIME COUNTER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 0162       | RESET PULSE GENERATION   | ······································                             |                                                                           |                |                                        | · · · · · · · · · · · · · · · · · · ·                                  | $\neg$      |
| 0107   | THANSLATOR NO. 2-3 TO 1 OUT OF 8          | 0145      | ACTUAL REGISTER CLOCKING                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       | 0183       | DIGIT TIME COUNTER       |                                                                    |                                                                           |                |                                        |                                                                        | $\neg$      |
| 0106   | CONTROL CHARACTER DECODER NO. 1           | 0146      | ACTUAL REGISTER CLEAR                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          | 0184       | BIT TIME COUNTER         |                                                                    | 1                                                                         |                |                                        |                                                                        | $\neg$      |
| 0109   | CONTROL CHARACTER DECODER NO. 2           | C147      | JOG SWITCH GATING                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              | 0185       | M AND N FUNCTION AND RE  | ADER STROBE F/F                                                    |                                                                           |                |                                        |                                                                        | $\dashv$    |
| 0110   | CONTROL CHARACTER DECODER NO. 3           | 0146-2    | JOG OR MOVE SYNC, AND MOTOR INHIBIT                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 0185       | DIALS AND TAPE DATA TIME | E F/F                                                              | <del>  </del>                                                             |                |                                        |                                                                        | $\dashv$    |
| 0111   | TAPE READER DATA TRACK VERIFICATION       | 0149 -2   | START MOVE OR PARITY FAILURE                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   | 0187       | DIALS INTERROGATION GAT  | ING                                                                | <del> </del>                                                              |                |                                        |                                                                        | $\dashv$    |
| 0112   | ALPHA AND NUMERIC CHARACTER DECODER       | 0150      | INDEX, REWIND AND STOP INDICATOR DRIVERS                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       | 0188       | RETURN TO REF. AND STOP  | F/F SHITCH SINGLE                                                  | <del> </del>                                                              |                |                                        |                                                                        | $\dashv$    |
| 6113   | TRANSLATOR NO. 3-9 TO 1 OUT OF 4          | 0151      | COARSE RANGE DECODER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 0189       | TEST AND XY STOPPED F/F  |                                                                    | <del> </del>                                                              |                |                                        |                                                                        | $\dashv$    |
| 0114   | M FUNCTION REGISTER                       | 0152      | FINE RANGE DECODER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | 0190       | SHIFT F/F AND LOAD       |                                                                    | <b> </b>                                                                  |                | <u> </u>                               |                                                                        | $\dashv$    |
| 6115   | MOTOR CONTROL (2 SHEETS)                  | 0153      | DAC INPUT DIRECT SET_RESET ENABLE                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              | 0191       | READER CONTROL F/F       |                                                                    | <del>  </del>                                                             |                |                                        |                                                                        | _           |
| 0116-2 | X-AXIS MTR. DR.                           | 0154      | DAC INPUT CLOCKING                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | . 0192     | PROCESSOR M RELAYS       |                                                                    | <del>  </del>                                                             | ~              |                                        |                                                                        | $\dashv$    |
| 0117-2 | Y_AXIS MTR. DR.                           | 0155      | DAC INPUT REGISTER X SIGN AND MSB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              | 0193       | PROCESSOR N RELAYS       |                                                                    | H                                                                         |                |                                        |                                                                        |             |
| 3118   | N FORETION REGISTER                       | 0156      | DAC INPUT REGISTER X LSB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       | 0194       | POWER CONTROL            |                                                                    |                                                                           | <del></del>    |                                        |                                                                        |             |
| C119   | TACH PULSE DECODING X-AXIS                |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 0195       | CONTROL PANEL (3 SHEETS  | ·                                                                  | <b>  </b>                                                                 |                |                                        | ·                                                                      |             |
| 6120   | TACH PULSE DECODING Y-AXIS                | 0157      | CAC INPUT REGISTER Y SIGN AND MOB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |            | <u> </u>                 |                                                                    | <b> </b>                                                                  |                |                                        |                                                                        | _           |
| 0121   | 4-SIT DESIRED INPUT REGISTER              | 0158      | DAC INPUT REGISTER Y LSB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       | 0196       | (NOT USED)               |                                                                    |                                                                           |                |                                        |                                                                        |             |
| 0122   |                                           | 0159      | DAC INPUT ZERO DECODER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 0197       | (NOT USED)               |                                                                    |                                                                           |                |                                        |                                                                        | _           |
|        | CONVERSION REGISTER BITS 1-4              | 0160      | DAC REFERENCE VOLTAGES                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 0198       | (NOT USED)               |                                                                    | <u> </u>                                                                  |                |                                        |                                                                        | _           |
| 0123   | CONVERSION REGISTER SITS 5-14             | 0161      | DAC NEGATIVE REFERENCE SUPPLY                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  | 0199       | MOTOR INHIBIT DELAY      |                                                                    | ()                                                                        |                |                                        |                                                                        |             |
| 0124   | CONVERSION REGISTER BITS 15-24            | 0162      | DAC X AXIS AMPLIFIER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 1750-0001. | SCHEMATIC - BIN L        | ITES                                                               |                                                                           |                |                                        |                                                                        |             |
| 0125   | SCO TO BINARY AND DESTREE ARTHMETIC       | . 0163    | DAC Y AXIS AMPLIFIER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           | 1750-0002  | SCHEMATIC- CONTE         | ROL PANEL                                                          |                                                                           |                |                                        |                                                                        | $\neg$      |
| 0126   | DESTRED REGISTER STON                     | 0154      | DAC X AXIS JOG CIRCUIT                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         | 1750-0003  | SCHEMATIC- CABLE         | E ASSY                                                             |                                                                           |                |                                        |                                                                        | $\neg$      |
| 0127   | X-DESTRED HEGISTER BITS 15-24             | 0165      | DAC Y AXIS JOG CIRCUIT                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |            |                          |                                                                    |                                                                           |                |                                        |                                                                        | $\neg$      |
| 0128   | X-DESTRED REGISTER BITS 5-14              | 0166      | (NOT USED)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    |                                                                           |                |                                        |                                                                        | $\neg$      |
| 0129   | Y-DESTRED REGISTER BITS 15-24             | 0167      | 6CD TO 7 SECILENT DECODER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |            |                          | ····                                                               | l                                                                         |                | ······································ |                                                                        | $\dashv$    |
| 0130   | Y-DESTRED REGISTER BITS 5-14              | . 0168    | DISPLAY REGISTER SEGMENT 3                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    |                                                                           |                | <del></del>                            |                                                                        | $\dashv$    |
| 0131   | X AND Y DESIRED REGISTER BITS 1-4         | 0169      | DISPLAY REGISTER SEGMENT 4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    |                                                                           |                | ······································ |                                                                        | -1          |
| 0132   | DESTRED REGISTER OUTPUT GATING BITS 1-6   | 0170      | DISPLAY REGISTER SEGMENT 5                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    |                                                                           |                |                                        |                                                                        |             |
| 0133   | DESTREC REGISTER CUTPUT GATING BITS 1-12  | 0171      | DISPLAY REGISTER SEGMENT 6                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    | <del>  </del>                                                             |                |                                        |                                                                        | $\dashv$    |
| 0134   | DESIRED REGISTER OUTPUT GATING BITS 13-16 | 0172      | DISPLAY REGISTER SEGMENT 7                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    |                                                                           |                |                                        | ***************************************                                | $\dashv$    |
| 0135   | DESTRED REGISTER OUTPUT GATING BITS 19-24 | 0173      | DISPLAY REGISTER SEGMENT &                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          | -                                                                  | -                                                                         |                | *                                      |                                                                        | $\dashv$    |
| 0136   | X AND Y DESIRED REGISTER CLOCKING         | 0174      | DISPLAY REGISTER SEGMENT 9                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |            |                          |                                                                    | <del>  </del>                                                             |                |                                        |                                                                        | $\dashv$    |
| C137   | ACTUAL REGISTER AND ADDER BITS 21-24      | 0175      | DAC INPUT DIRECT SET_RESET GATING                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |            |                          |                                                                    | <del>  </del>                                                             |                |                                        |                                                                        | $\dashv$    |
| 0138   | ACTUAL REGISTER AND ADDER 6175 17-20      | 0176      | TIME DELAY COUNTER                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |            |                          |                                                                    | <del>  </del>                                                             |                |                                        |                                                                        | _           |
| *      |                                           |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |            |                          |                                                                    |                                                                           |                |                                        |                                                                        | 1           |
|        |                                           |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |            |                          | •                                                                  |                                                                           |                |                                        |                                                                        | 1           |
|        | •                                         | •         |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | :          |                          | ·                                                                  | <u> </u>                                                                  | 1 2,0 1        |                                        |                                                                        | _           |
|        |                                           |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |            |                          | <u> </u>                                                           | SCRIPTION                                                                 |                | Z.                                     | PART NUMBER                                                            |             |
|        | •                                         |           | •                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |            | •                        | DTHER DOCUMENTS OR                                                 | NS PROPRIETARY INFORM<br>DISCLOSED TO OTHERS OF<br>ION OF STREEGISTIC PRO | R USED FOR M   | H SHALL HOT E<br>MANUFACTURIN          | E REPRODUCTO DA TRANSFERRE<br>IG DR ANY UTHER PURPOSE WITH             | 376<br>TUE: |
|        |                                           |           | and the second s |            | <u> </u>                 | TOLERANCES UNLESS<br>OTHERWISE SPECIFIED<br>IXX IXXX ANGLE         |                                                                           |                |                                        | YNERGISTIC PRODUCTS,                                                   |             |
|        |                                           |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |            |                          | 1.01 1.005 3 7-39                                                  |                                                                           |                | 1                                      | A Subsidictly of Cavitron Corporat<br>1902 McGlevi, Santa Ana, Civillo | ion .       |
|        |                                           |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |            |                          | CONCENTRICITY AND OUT<br>OF ROUND T I R. 100 T<br>DEMOVE BURNE AND |                                                                           | DATE           | 112 K 67                               | : 25 00 BATS                                                           |             |
|        |                                           |           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |            |                          | TIMEL                                                              |                                                                           | j              | 4631                                   | VERTICAL TARL                                                          |             |


NEXT ASSY


USED ON


1800-0100-516
















































































| ODD PARTY ETA ES                       | gept       | EVEN PARITY                       |
|----------------------------------------|------------|-----------------------------------|
| 436 8 400<br>37654 321                 | ON ARACTOR | 6432168 42 1<br>1 7 5 5 4   0 2 1 |
| 00 00 00 00 00 00 00 00 00 00 00 00 00 | PORTOR TAB |                                   |

Figure 2. EIA-& ASCH Topo Coding